SWIFT-UVOT

MULLARD SPACE SCIENCE LABORATORY H. E. Huckle, P. J. Smith, L.K.Gilbert UNIVERSITY COLLEGE LONDON

SWIFT-UVOT ICU CODE BUILD 5 TEST PLAN

Document: MSSL/SWT-UVOT/SP/0024.01

| Distribution: | | |
|----------------------------------|--|------|
| Penn. State | J. Nousek P. Roming P. Broos S. Koch P. Altimore | |
| GSFC | D. Bundas R. Borelli | |
| Mullard Space Science Laboratory | R. Card M. Carter M. Cropper B. Hancock M. Hailey H. Huckle H. Kawakami K. Mason P. Smith A. Smith P. Thomas J. Tandy | |
| SWIFT-UVOT Project Office | T. Kennedy | Orig |
| Author: | Date: | |
| Authorised By: | Date: | |
| Distributed: | Date: | |

| Issue | Date | Comments |
|---------|----------------|---|
| Draft | Feb 2002 | Draft version for comment |
| Issue 1 | September 2002 | Version for final Operational Code test |
| | | |
| | | |
| | | |

| 1. | INTRODUCTION AND TEST ENVIRONMENT11 |
|-----|-------------------------------------|
| 2. | TIME12 |
| 2.1 | 1PPS12 |
| 2.2 | TIMETONE alterations14 |
| 3. | FAST TELECOMMANDING16 |
| 3.1 | Tasks16 |
| 4. | MEMORY |
| 4.1 | EEPROM B boundary checks18 |
| 4.2 | Dump during load21 |
| 5. | HOUSEKEEPING22 |
| 5.1 | Contents |
| 5.2 | Copy to TDRSS |
| 5.3 | Rate changes |
| 5.4 | Stop and start43 |
| 5.5 | Task |
| 6. | DPU46 |
| 6.1 | DPU Task |
| 6.2 | DPU Mode48 |
| 6.3 | Other commands |
| 6.4 | Other messages |
| 6.5 | Heartbeat monitor53 |
| 7. | EXCEPTIONS |

| 7.1 | Main ada program54 |
|------|---|
| 7.2 | DPU Data manager55 |
| 7.3 | Heater Control |
| 7.4 | Housekeeping type57 |
| 7.5 | Memory dump type58 |
| 7.6 | Limit Monitoring59 |
| 7.7 | Mech |
| 7.8 | TCQ61 |
| 7.9 | Feed 1553 type |
| 7.10 | Watchdog task |
| 7.11 | HK change rate64 |
| 7.12 | RTS type65 |
| 7.13 | Perform ramp type |
| 7.14 | Load centroid table task |
| 7.15 | Load window table task type68 |
| 7.16 | SSI feed type |
| 7.17 | Starcat task |
| 7.18 | Poll TC type71 |
| 8. P | ACKETS AND MESSAGES NOT COVERED ELSEWHERE72 |
| 8.1 | Reboot72 |
| 8.2 | Memory dump74 |
| 8.3 | Table loads 76 |
| 8.4 | Verification errors79 |
| 8.5 | TDRSS |
| 8.6 | State Changes |

| 8.7 | SC1553 |
|------|--|
| 8.8 | SSI |
| 8.9 | EEPROM |
| 9. | COMMANDS NOT COVERED ELSEWHERE88 |
| 9.1 | Table loads 88 |
| 9.2 | BPE Commands92 |
| 9.3 | ICB commands using ICB slave94 |
| 9.4 | State commands97 |
| 9.5 | NHK Echo |
| 9.6 | Watchdog102 |
| 9.7 | Test104 |
| 10. | HEATERS105 |
| 10.1 | Enable/disable automatic heater control105 |
| 10.2 | Automatic heater setting112 |
| 11. | DCS116 |
| 11.1 | DCS116 |
| 12. | SC1553120 |
| 13. | SSI123 |
| 14. | FUNDAMENTAL STATE CHANGES125 |
| 14.1 | Safe to idle transition125 |
| 14.2 | AT at a never before observed location126 |
| 14.3 | AT with no XRT position given131 |
| 14.4 | РТ135 |
| 14.5 | Calibration PT – Intensifier Characteristics / Pulse Height137 |

| 14.6 | A PT with a non-full-image detector window138 |
|-------|---|
| 14.7 | Safepointing140 |
| 14.8 | Two AT's at the same pointing, with a PT between them141 |
| 14.9 | One AT followed by another at almost the same pointing144 |
| 14.10 | Interruption in finding state147 |
| 14.11 | Finding state untenable150 |
| 14.12 | A PT interrupted by an AT155 |
| 14.13 | Safehold157 |
| 15. | BRIGHT SOURCE AVOIDANCE158 |
| 15.1 | Requested AT with Sun in field of view158 |
| 15.2 | Requested AT with Earth in field of view160 |
| 15.3 | Requested AT with Moon in field of view162 |
| 15.4 | Requested AT with a planet in the field of view164 |
| 15.5 | Requested AT with a bright star in the field of view166 |
| 15.6 | AT exposure shortened due to presence of dim stars |
| 15.7 | Requested PT with Sun in field of view170 |
| 15.8 | Requested PT with Earth in field of view172 |
| 15.9 | Requested PT with Moon in field of view174 |
| 15.10 | Requested PT with a planet in the field of view176 |
| 15.11 | Requested PT with a bright star in the field of view178 |
| 15.12 | PT exposure shortened due to presence of dim stars179 |
| 15.13 | Several bright stars in the field of view181 |
| 15.14 | Drift towards Sun, Moon or Earth182 |
| 16. | STATE CHANGES INVOLVING THE SAA |
| 16.1 | Safe to idle transition in the SAA184 |

| 16.2 | Entering and exiting SAA during slew185 |
|-------|--|
| 16.3 | Starting the slew while in the SAA and exiting it during slew187 |
| 16.4 | Entering the SAA while slewing and exiting it in the settling state |
| 16.5 | Entering and exiting the SAA in the settling state |
| 16.6 | Entering and exiting the SAA in the finding state |
| 16.7 | Staying a long time in the SAA in the finding state195 |
| 16.8 | Entering the SAA during slew and leaving it in the finding state |
| 16.9 | Entering the SAA in the settling state and exiting it in the finding state 199 |
| 16.10 | Entering and exiting the SAA during an AT exposure |
| 16.11 | Entering the SAA during slew and exiting it during an AT exposure 204 |
| 16.12 | Entering and leaving the SAA during a PT exposure |
| 16.13 | Entering the SAA during slew and exiting it during a PT exposure 208 |
| 16.14 | Entering and exiting the SAA during a safe pointing |
| 16.15 | Entering the SAA during slew and exiting it during a safe pointing212 |
| 16.16 | Entering and exiting the SAA while in the idle state |
| 16.17 | Entering and exiting the SAA in the safe state |
| 17. | ERROR CONDITIONS |
| 17.1 | Loss of spacecraft messaging |
| 17.2 | Loss of spacecraft messaging during exposure |
| 17.3 | Out of limits triggering a power off UVOT request |
| 17.4 | Out of limits triggering a power off UVOT TM request |
| 17.5 | TMPSU out of limits |
| 17.6 | BPE out of limits |
| 17.7 | DPU out of limits |
| 17.8 | DPUHB out of limits |

| 17.9 | Bad is_settled flag in ACS | 230 |
|-------|--|-----|
| 17.10 | A glitch in the is_settled flag | 231 |
| 17.11 | Bad pointing values | 232 |
| 17.12 | Slewing towards the Sun | 237 |
| 17.13 | Slewing towards the Earth | 239 |
| 17.14 | Drift off target once settled | 241 |
| 17.15 | Settled on wrong target | 244 |
| 17.16 | Corrupted star catalogue | 245 |
| 17.17 | Unknown UVOT modes | 247 |
| 17.18 | Bright star store exhausted | 249 |
| 17.19 | Exposures commanded while UVOT is safed | 251 |
| 18. | MANUAL STATE TRANSITIONS | 252 |
| 18.1 | Manual state transitions | 252 |
| 19. | CORRUPTED TABLES | 256 |
| 19.1 | Random corruption | 256 |
| 19.2 | Corrupted token in DCS | 266 |
| 20. | FORCED STATE CHANGES TO SAFE, IDLE OR SLEW | 267 |
| 20.1 | From slew to safe | 267 |
| 20.2 | From slewSAA to safe | 268 |
| 20.3 | From idle to safe | 269 |
| 20.4 | From settling to safe | 270 |
| 20.5 | From finding to safe | 271 |
| 20.6 | From AT to safe | 272 |
| 20.7 | From PT to safe | 273 |

| 20.8 | From safepointing to safe | |
|-------|--|-----|
| 20.9 | From SAA to safe | |
| 20.10 | From settling to idle | |
| 20.11 | From finding to idle | |
| 20.12 | From AT to idle | |
| 20.13 | From PT to idle | |
| 20.14 | From safepointing to idle | |
| 20.15 | From settling and safepointing to slew | |
| 21. | SOAK TEST | 282 |
| 21.1 | 72hr Soak | |

1. INTRODUCTION AND TEST ENVIRONMENT

This test is designed to cover Swift-UVOT ICU software function, to flight level.

All sections should be run on the telescope simulator, running configuration file hv0vc0fw0.dat, the software DPU simulator and the Spectrum Astro spacecraft simulator, unless otherwise stated.

Nominal values for UVOT currents are (write in as appropriate for current test set up); Vcathode Vmcp1 Vmcp23 Flood LED

Nominal values for the safety circuit are (write in as appropriate for current test set up);

For some of these tests the spacecraft time will be altered to enable a particular planetary/solar/lunar configuration scenario to be used. After these have been done a manual reset of the spacecraft time will be necessary, and this must be calculated at the reset time. As a baseline measurement;

Midnight beginning 1st February 2002 is 1063238404 seconds on the spacecraft clock.

Two other separate tests are provided, the Filter Wheel Special Test and the HV Special Test. These should be performed before this test, with as much of the real hardware as possible.

2. TIME

2.1 1PPS

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Check on the spacecraft display that 1PPS A is being used.

1PPS A used Y/N_____

Turn off 1PPS A and turn on 1PPS B using
/iTimesync Enable=Off, Channel=0

Check that UVOT switches to using 1PPS B.

Switches to 1PPS B Y/N_____

Return to 1PPS A using /iTimesync Enable=On, Channel=0

Check on the spacecraft display that 1PPS A is being used.

1PPS A used Y/N_____

Disconnect 1PPS A.

Check on the spacecraft display that after 2s UVOT automatically switches to using 1PPS B, and that an NHK 'Timesync too long since' message is received.

Switches to 1PPS B after 2s Y/N_____ 'Timesync too long since' received Y/N_____

Connect up the 1PPS hardware simulator.

Check on the spacecraft display that 1PPS A is being used.

1PPS A used Y/N_____

Configure the 1PPS simulator to interrupt 1PPS A twice in one second.

Check that UVOT automatically switches to using 1PPS B.

Switches to 1PPS B Y/N_____

If all the above responses are Y's then the test is successful.

Test Successful

Initials _____ Date _____ Time _____

2.2 TIMETONE alterations

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Note the timestamp on the next housekeeping packet that arrives _____

Change the UTC Delta using /SDISCLKMOD seconds=5

Note the timestamp on the subsequent housekeeping packet _____

The difference between the two timestamps should be 15 seconds

15s difference Y/N_____

Reset the UTC Delta using /SDISCLKMOD seconds=-5

Note the timestamp on the subsequent housekeeping packet _____

The difference between the two timestamps should be 5 seconds

5s difference Y/N_____

Try to command the spacecraft time to alter to a too large value using Start changetimes

Check on the NHK display that a 'Timesync Overflow' message has been received.

'Timesync Overflow' received Y/N_____

Reset clock to a sensible value using /SDISCLKSET seconds=1146528004

Command the spacecraft time to jump forwards using /SDISCLKMOD seconds=600

Check on the NHK display that a 'Timesync Jump' message has been received.

'Timesync Jump' received Y/N_____

Edit the code to force out a 'Timesync Too Late' message, and run this test code.

'Timesync Too Late' received Y/N_____

Reload normal flight code.

If all the above responses are Y's then the test is successful.

Test Successful

Initials _____ Date _____ Time _____

3. FAST TELECOMMANDING

3.1 Tasks

NB: Fast commanding of the filter wheel will take place in the FW Special Test

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

From the housekeeping display write down the number of good and bad telecommands received so far;

TC Good_____ TC Bad_____

Run the ITOS script fastcommands.proc with the command Start fastcommands

From the housekeeping display write down the number of good and bad telecommands received now;

TC Good_____

TC Bad_____

Check on the NHK display that no error messages have been received ('Busy' is acceptable).

NHK error messages received Y/N_____

Check that the following are all as stated;

| Limit checking on Y/N |
|-----------------------|
| DPU task on Y/N |
| Watchdog on Y/N |
| Heater control on Y/N |
| RTS Trace off Y/N |
| HK rate 1 per 10s Y/N |

If the number of good telecommands has increased by 64, the number of bad telecommands has increased by 2, no unexpected NHK error messages have been received, and the final block of responses are all Y's then the test is successful.

Test Successful

Initials _____ Date _____ Time _____

4. MEMORY

EEPROM A was thoroughly tested during the PROM test, and so does not need testing here. Only boundary checks need to be performed on EEPROM B.

4.1 EEPROM B boundary checks

NB – This test overwrites some of the star catalogue, which must be reloaded afterwards.

Open packet dump screens for memory dumps and CRCs using Pktdump vc0 0x390 Pktdump vc0 0x391

Check RAM briefly (already checked in some detail during the PROM test) by sending the commands

/iICUDump Mid=0, Offset=0x2000, Numbytes=5, APID=0x390
/iICUCRC Mid=0, Offset=0x2000, Length=5, APID=0x391

Write down the five dumped values here:

Check that the five values dumped do give the CRC value given.

CRC is consistent with five dumped values Y/N_____

Run the ITOS script checkeepromb.proc line by line with the command Start checkeepromb halted

In the first block of commands, after each dump or CRC command, check the values that are dumped with the list below;

| Dump $1 - 0x52$, $0x53$, $0x54$ and any other 7 values $- Y/N_{$ |
|---|
| CRC 1 – 0x424E – Y/N |
| Dump 2 – a value, $0x55$, $0x56$, $0x57$ and any other 6 values – Y/N |
| Dump 3 - 0x55, 0x56, 0x57 and any other 7 values – Y/N |
| Dump 4 - 0x56, 0x57 and any other 8 values – Y/N |
| Dump 5 - 0x55, 0x58, 0x59, 0x5A and any other 6 values – Y/N |
| Dump 6 - 0x58, 0x59, 0x5A and any other 7 values – Y/N |
| CRC 2 – 0x04C6 – Y/N |
| CRC 3 – 0xB873 – Y/N |
| Dump 7 - 0x5B, 0x5C, 0x5D and any other 7 values – Y/N |
| Dump 8 - 0x5C, 0x5D and any other 8 values – Y/N |
| Dump 9 - 0x5B, 0x5E, 0x5F, 0x60 and any other 6 values – Y/N |
| Dump 10 - 0x5E, 0x5F, 0x60 and any other 7 values – Y/N |
| CRC 4 – 0x1908 – Y/N |
| |

| CRC 5 – 0x6A15 – Y/N |
|---|
| Dump 11 - 0x61, 0x62, 0x63 and any other 7 values – Y/N |
| Dump 12 - 0x62, 0x63 and any other 8 values – Y/N |
| Dump 13 - 0x61, 0x64, 0x65, 0x66 and any other 6 values – Y/N |
| CRC 6 – 0xC635 – Y/N |
| CRC 7 – 0xFF68– Y/N |
| Dump 14 - 0x64, 0x65, 0x66 and any other 7 values – Y/N |
| Dump 15 – any 13 values, then 0x67, 0x68 – Y/N |
| Dump 16 – 0x69 – Y/N |
| Dump 17 – 0x6A – Y/N |
| Dump 18 – 0x68, 0x6A – Y/N |
| CRC 8 – 0xD0E3 – Y/N |
| |

For the second block of commands, check that all five are rejected.

| Command 1 rejected Y/N |
|------------------------|
| Command 2 rejected Y/N |
| Command 3 rejected Y/N |
| Command 4 rejected Y/N |
| Command 5 rejected Y/N |

For the third block, check that all four commands complete successfully. There is no need to check all the output. These will take some time. Also check before command 1 that in housekeeping task mem dump is asleep and its task counter is not increasing, whilst during the first commanded dump this task comes alive and the counter increases.

Before command 1, mem dump task asleep Y/N_____ And mem dump task counter unchanging Y/N_____

During command 1, mem dump task alive Y/N_____ And mem dump task counter increases Y/N_____

 Command 1 completed Y/N_____

 Command 2 completed Y/N_____

 Command 3 completed Y/N_____

 Command 4 completed Y/N______

For the fourth block, check that both commands receive an 'Unsuccessful Acceptance' verification message, due to 'invalid length'.

Command 1 has invalid length Y/N_____ Command 2 has invalid length Y/N_____

NB It would be possible to run test 17.16 now without editing code, as the star catalogue is currently in a seriously corrupted state.

Reload the star catalogue, addendum and pointer table before running any other tests, using

load "cat.img"
load "addendum.img"
load "pointers.img"

If all the above responses are Y's then the test is successful.

Test Successful

Initials _____ Date _____ Time _____

4.2 Dump during load

Start a long memory dump using
/iICUDump Mid=5, Offset=0, Numbytes=0xFFFF, APID=0x390

While this is running, command a load using Load "pointers.img"

Check the NHK display for a 'Busy' message.

'Busy' received Y/N_____

If the response above is Y then the test is successful.

Test Successful

Initials _____ Date _____ Time _____

5. HOUSEKEEPING

5.1 Contents

Note that this is a very awkward test. There are 179 different items in each housekeeping packet. Some of them are tested in other tests in this document, so they do not appear here. Some will always keep the same value and only need to be tested once. Some increment, and only the rate of increment is important, not the absolute value. To cover all possibilities three valid housekeeping configuration files, one with all values as high as possible, one with all values low, one mid-range have been prepared. Each one should be run once and each item given checked against its expected value. The items whose value never changes are only checked in the mid-range test. The DPU temperature and voltage flags can each take one of four values, each of which must be tested. Consequently, once the mid-range test has been run, four subtests, one for each flag setting, must be done with the mid-range configuration files. With the same configuration files, the code must also be edited to change the settings of Version Basic and version Oper, and another subtest run to check that these are picked up correctly. The filter wheel counter is only checked in the high range test, as its lower ranges are tested in the safing tests. The values of iSC1553Ints, iSC1553IHTC and iSC1553TCPckt should be the same, or within 1 of each other, at all times. Finally watchdog tasks 15 to 24 and software tasks 15 to 24 are spares and do not need to be tested.

Test 1, all values low

Run the telescope simulator with valid housekeeping configuration file hk_all_low.dat. Check that the values displayed on the telescope simulator window are the same as those given in the table below – if they are not, check against the configuration file and make any alterations necessary to get agreement before running this test. Enter a low range set of values (A to D channels, parity errors and reserves, mode and submode) into the DPU simulator, as defined in the table below.

Check one housekeeping packet against the configuration file to make sure that they are the same.

Note that in the case of incrementing values, there may be some beating with the housekeeping display, and so the value given should be an average over several packets. It is given in the table below as a decimal value.

All values that are indicated in hex in the housekeeping are given in hex here.

| Variable | Description | Value or | Value or | Are values |
|----------|-------------|-------------|----------|--------------|
| | | increase in | increase | seen and |
| | | value seen | in value | expected the |
| | | | expected | same Y/N |

| [| | | |
|------------------------|---------------|----------|--|
| iBPETemp | BPE | 0 | |
| | Thermistor | | |
| | Readings | | |
| iBPERefBTemp | BPE | 0 | |
| 1 | Thermistor | - | |
| | Readings | | |
| iBPERefCTemp | BPE | 0 | |
| IBLEKEICIEMP | | 0 | |
| | Thermistor | | |
| | Readings | | |
| iBPEMainTemp | BPE | 0 | |
| | Thermistor | | |
| | Readings | | |
| | BPE | 0 | |
| iBPEForward1Temp | Thermistor | | |
| 1 | Readings | | |
| | BPE | 0 | |
| iBPEForward2Temp | Thermistor | 5 | |
| The section wards remp | | | |
| | Readings | <u>^</u> | |
| iBPECCDTemp | BPE | 0 | |
| | Thermistor | | |
| | Readings | | |
| iBPERefATemp | BPE | 0 | |
| | Thermistor | | |
| | Readings | | |
| iHVmcp1 | Vmcp1 | 0 | |
| iHVmcp23 | Vmcp23 | 0 | |
| iHVCathode | Vcathode | 0 | |
| | | - | |
| iLVPlus5 | Low Voltage | 0 | |
| | +5 | | |
| iLVPlus15 | Low Voltage | 0 | |
| | +15 | | |
| iLVMinus15 | Low Voltage | 0 | |
| | -15 | | |
| iLVRef | Low Voltage | 0 | |
| | 1.23 V | | |
| | Reference | | |
| iFWPickOff | F/W Analogue | 0 | |
| IF WPICKOII | _ | 0 | |
| | Pick-Off | <u>^</u> | |
| 1. | BPE | 0 | |
| iBPEIntegratNbld | Integration | | |
| | Enabled | | |
| iBPEAcqMode | BPE | 0 | |
| | Acquisition | | |
| | Mode | | |
| | Frame Tag | 1 | |
| iBPEFrameTagNbld | | - | |
| iBPECentrdTblOk | Centroid | 0 | |
| TBLECENCLUIDIOK | Table Access | 0 | |
| | | 0 | |
| iBPECamStarted | Camera | 0 | |
| | Started/No | | |
| | Window Tble | | |
| | Access | | |
| iTMPSUPlus28 | +28V Rail | 0 | |
| | Current | | |
| iTMPSUPlus11 | +11V Rail | 0 | |
| | · ⊥ ⊥ v ⊥\u⊥⊥ | ~ | |

| | Current | |
|------------------|----------------------------|------------|
| iTMPSUPlus15 | +15V Rail | 0 |
| IIMPSOPIUSIS | Current | 0 |
| iTMPSUMinus15 | -15V Rail | 0 |
| 11MP SOMIIIUSI S | Current | 0 |
| iTMPSUPlus5B | +5VB Rail | 0 |
| IIMPSOPIUSSB | Current | 0 |
| iTMPSUPlus5A | +5VA Rail | 0 |
| I IME SOF LUSSA | Current | 0 |
| iTMPSUMinus5A | -5VA Rail | 0 |
| TIMPSOMILIUSJA | Current | 0 |
| iTMPSUDisMon | DISMON, | 0 |
| 1111 5001511011 | Ballast | 0 |
| | Resistor Temp | |
| | Comparitor | |
| | Status | |
| iSC1553Ints | 1553 | Increments |
| 10010001000 | Interrupt | by 60 per |
| | Count | packet |
| iSC1553IHTC | 1553 IHTC | Increments |
| | Count | by 60 per |
| | | packet |
| iSC1553TCPckt | 1553 TC | Increments |
| | Packet Count | by 60 per |
| | | packet |
| iDPUMode | DPU Mode | 0 |
| iDPUSubMode | DPU SubMode | 0 |
| iDPUTempPSUA | DPU Temp PSU | 0 |
| _ | A | |
| iDPUTempPSUB | DPU Temp PSU | 0 |
| | В | |
| iDPUTempICUCPU | DPU Temp ICU | 0 |
| | CPU Module | |
| iDPUTempICUIF | DPU Temp ICU | 0 |
| | I/F Module | |
| iDPUTempComm | DPU Temp DPU | 0 |
| | Comm/Mem | |
| | Module | |
| iDPUTempRes1 | DPU Temp | 0 |
| | Reserve 1 | |
| iDPUTempRes2 | DPU Temp | 0 |
| | Reserve 2 | |
| iDPUPlus5VA | DPU Voltage | 0 |
| | PSU A +5V | |
| iDPUPlus5VB | DPU Voltage | 0 |
| | PSU B +5V | |
| iDPUPlus12VA | DPU Voltage | 0 |
| iDPUMinus12VA | PSU A +12V | 0 |
| IDFOMINUSIZVA | DPU Voltage | U |
| iDPUPlus5VRef | PSU A -12V | |
| IDFOFIUSSVKEI | DPU Voltage PSU +5V Ref | 0 |
| iDPUMinus5VRef | DPU Voltage | 0 |
| TDEOMTHUSSAKEL | PSU -5V Ref | v |
| | DPU Power | 0 |
| iDPUPowerRes | DEO EOMET | U |

| | Reserve | | |
|------------------|-------------|---|--|
| | DPU Parity | 0 | |
| iDPUParityErrors | Errors | | |
| iDPURes1 | DPU Reserve | 0 | |
| | 1 | | |
| iDPURes2 | DPU Reserve | 0 | |
| | 2 | | |

If all responses in column 5 of the table above are Y's then the test is successful.

Test Successful _____

Initials _____ Date _____ Time _____

Test 2, all values mid-range

Run the telescope simulator with valid housekeeping configuration file hk_in_limits.dat. Check that the values displayed on the telescope simulator window are the same as those given in the table below – if they are not, check against the configuration file and make any alterations necessary to get agreement before running this test. Enter a mid range set of values (A to D channels, parity errors and reserves, mode and submode) into the DPU simulator, as defined in the table below.

Check one housekeeping packet against the configuration file to make sure that they are the same.

Note that in the case of incrementing values, there may be some beating with the housekeeping display, and so the value given should be an average over several packets. It is given in the table below as a decimal value.

All values that are indicated in hex in the housekeeping are given in hex here.

| Variable | Description | Value or increase in value seen | Value or increase in value expected | Are values seen and expected the same Y/N |
|---------------|----------------------------------|---------------------------------------|--|--|
| iDebugIntCntr | Debug Int Counter (HK SID) | | Increments by 35 per packet | |
| iBPETemp | BPE Thermistor Readings | | 0x1F8 | |
| iBPERefBTemp | BPE Thermistor Readings | | 0x1F9 | |

| | [] | | |
|------------------|-------------------|-------|--|
| iBPERefCTemp | BPE | 0x1FA | |
| | Thermistor | | |
| | Readings | | |
| iBPEMainTemp | BPE | 0x1FB | |
| - | Thermistor | | |
| | Readings | | |
| | BPE | 0x1FC | |
| | Thermistor | UXIIC | |
| iBPEForward1Temp | | | |
| | Readings | | |
| | BPE | 0x1FD | |
| iBPEForward2Temp | Thermistor | | |
| | Readings | | |
| iBPECCDTemp | BPE | 0x1FE | |
| 1 | Thermistor | | |
| | Readings | | |
| ippepofAtomp | BPE | 0x1FF | |
| iBPERefATemp | BPE Thermistor | UXIFF | |
| | | | |
| | Readings | | |
| iHVmcp1 | Vmcpl | 0x201 | |
| iHVmcp23 | Vmcp23 | 0x202 | |
| iHVCathode | Vcathode | 0x200 | |
| iLVPlus5 | Low Voltage | 0x203 | |
| 11011035 | +5 | 07203 | |
| | | 0.004 | |
| iLVPlus15 | Low Voltage | 0x204 | |
| | +15 | | |
| iLVMinus15 | Low Voltage | 0x205 | |
| | -15 | | |
| iLVRef | Low Voltage | 0x206 | |
| | 1.23 V | | |
| | Reference | | |
| iFWPickOff | F/W Analogue | 0x207 | |
| IFWPICKULL | | 0x207 | |
| | Pick-Off | | |
| | BPE | 1 | |
| iBPEIntegratNbld | Integration | | |
| | Enabled | | |
| iBPEAcqMode | BPE | 3 | |
| 1 | Acquisition | | |
| | Mode | | |
| | Frame Tag | 0 | |
| | | U | |
| iBPEFrameTagNbld | Enabled | | |
| iBPECentrdTblOk | Centroid | 1 | |
| | Table Access | | |
| iBPECamStarted | Camera | 1 | |
| | Started/No | | |
| | Window Tble | | |
| | Access | | |
| iBPEEventThold | Event Detect | 0 | |
| TELEVAULTUOTO | | U | |
| <u> </u> | Threshold | | |
| iHtrMetering | Metering | 0 | |
| | Rods Htr | | |
| iHtrSecondary | Secondary | 0 | |
| | Mirror Htr | | |
| iDMCounter | Dichroic | 0 | |
| | Position | | |
| | Counter | | |
| 1 | COULLET | | |

| iOnePPSSyncStat | Time Sync | 0 | |
|-----------------|---------------|------------|--|
| | Status | | |
| iOnePPSSyncChan | Time Sync | 0 | |
| | Channel | | |
| iTMPSUPlus28 | +28V Rail | 0x7C | |
| | Current | | |
| iTMPSUPlus11 | +11V Rail | 0x7D | |
| | Current | | |
| iTMPSUPlus15 | +15V Rail | 0x7E | |
| | Current | | |
| iTMPSUMinus15 | -15V Rail | 0x7F | |
| | Current | | |
| iTMPSUPlus5B | +5VB Rail | 0x80 | |
| | Current | | |
| iTMPSUPlus5A | +5VA Rail | 0x81 | |
| | Current | | |
| iTMPSUMinus5A | -5VA Rail | 0x82 | |
| TIMPSOMILIUSSA | Current | UXOZ | |
| iTMPSUDisMon | | 0x83 | |
| TIMPSODISMON | DISMON, | 0x05 | |
| | Ballast | | |
| | Resistor Temp | | |
| | Comparitor | | |
| | Status | | |
| iSSISent | SSI Sent | 0 | |
| | Count | | |
| iOnePPSInts | 1 PPS A | 0 | |
| | Interrupt | | |
| | Count | | |
| iOnePPSInts2 | 1 PPS B | 0 | |
| | Interrupt | | |
| | Count | | |
| | (Redundant) | | |
| iSC1553Ints | 1553 | Increments | |
| | Interrupt | by 60 per | |
| | Count | packet | |
| iSC1553IHTC | 1553 IHTC | Increments | |
| | Count | by 60 per | |
| | | packet | |
| iSC1553TCPckt | 1553 TC | Increments | |
| | Packet Count | by 60 per | |
| | | packet | |
| iUVOTState | UVOT State | 0 | |
| iActiveDEM | Active DEM | 1 | |
| iDPUHeartbeats | DPU | Increments | |
| | Heartbeat | by 1 per | |
| | Counts | packet | |
| iDPUMode | DPU Mode | 0x7F | |
| iDPUSubMode | DPU SubMode | 0x7F | |
| iDPUTempPSUA | DPU Temp PSU | 0x810 | |
| - | A | | |
| iDPUTempPSUB | DPU Temp PSU | 0x820 | |
| - | В | | |
| iDPUTempICUCPU | DPU Temp ICU | 0x830 | |
| 1 | CPU Module | | |
| iDPUTempICUIF | DPU Temp ICU | 0x840 | |
| | 210 10mp 100 | 011010 | |

| | I/F Module | | |
|-------------------------|----------------------------|--------------|--|
| iDPUTempComm | DPU Temp DPU | 0x850 | |
| IDI OI empeonum | Comm/Mem | 02030 | |
| | Module | | |
| iDPUTempRes1 | DPU Temp | 0x860 | |
| IDPOIEmpResi | Reserve 1 | 08880 | |
| iDPUTempRes2 | DPU Temp | 0x870 | |
| IDPOIEmpResz | Reserve 2 | 0x870 | |
| iDPUPlus5VA | DPU Voltage | 0x880 | |
| IDPOPIUSJVA | PSU A +5V | 0x080 | |
| iDPUPlus5VB | DPU Voltage | 0×890 | |
| IDPOPIUSSVB | PSU B +5V | 0x890 | |
| iDPUPlus12VA | DPU Voltage | 0x900 | |
| IDPOPIUSIZVA | PSU A +12V | 0x900 | |
| iDPUMinus12VA | DPU Voltage | 0x910 | |
| IDPOMINUSIZVA | - | 0X910 | |
| iDPUPlus5VRef | PSU A -12V | 0x920 | |
| iDPOPIUSSVRei | DPU Voltage PSU +5V Ref | 0x920 | |
| iDPUMinus5VRef | | 0020 | |
| iDPOMinussvker | DPU Voltage PSU -5V Ref | 0x930 | |
| | | 0.040 | |
| iDPUPowerRes | DPU Power | 0x940 | |
| | Reserve | 0.2000 | |
| | DPU Parity | 0x7FFF | |
| iDPUParityErrors | Errors | 0.050 | |
| iDPURes1 | DPU Reserve | 0x950 | |
| | 1 | | |
| iDPURes2 | DPU Reserve | 0x960 | |
| | 2 | | |
| iSCVoltage | S/C Voltage | 0 | |
| iACSCount | ACS Counter | Increments | |
| | | by 50 per | |
| | | packet | |
| iTimetoneCount | Timetone | Increments | |
| | Counter | by 10 per | |
| | | packet | |
| iWatchdogTsk01 | Task TCQ | Alive | |
| | Monitored by | | |
| | Watchdog | | |
| iWatchdogTsk02 | Task HV_Ramp | Asleep | |
| | Monitored by | | |
| Wot chalant 100 | Watchdog | م ا <u>۱</u> | |
| iWatchdogTsk03 | Task | Alive | |
| | DPU_Mntr | | |
| | Monitored by | | |
| i Wet els de amoi 1 0 4 | Watchdog | م ا <u>ا</u> | |
| iWatchdogTsk04 | Task | Alive | |
| | Htr_Cntrol | | |
| | Monitored by | | |
| | Watchdog | | |
| iWatchdogTsk05 | Task | Alive | |
| | Limit_Chck | | |
| | Monitored by | | |
| | Watchdog | | |
| iWatchdogTsk06 | Task | Asleep | |
| | Mechanism | | |

| | Monitored by | | |
|----------------|---------------|------------|--|
| | Watchdog | | |
| iWatchdogTsk07 | Task | Alive | |
| | Feed_1553 | | |
| | Monitored by | | |
| | Watchdog | | |
| iWatchdogTsk08 | Task HK | Alive | |
| | Monitored by | | |
| | Watchdog | | |
| iWatchdogTsk09 | Task Mem | Asleep | |
| indeendogionos | Dump | 101000 | |
| | Monitored by | | |
| | _ | | |
| | Watchdog | | |
| IWatchdogTsk10 | Task DCS | Asleep | |
| | Monitored by | | |
| | Watchdog | | |
| IWatchdogTsk11 | Task Load | Asleep | |
| | Centroid | | |
| | Monitored by | | |
| | Watchdog | | |
| IWatchdogTsk12 | Task Load | Asleep | |
| | Window | | |
| | Monitored by | | |
| | Watchdog | | |
| IWatchdogTsk13 | Task Feed | Deleen. | |
| IWatchdogISKI3 | | Asleep | |
| | SSI Monitored | | |
| | by Watchdog | | |
| IWatchdogTsk14 | Task Star | Asleep | |
| | Cat Monitored | | |
| | by Watchdog | | |
| iDebug1stEx | Debug First | 0 | |
| | Exception | | |
| iDebug1stProg | Debug First | 0 | |
| | Progress | | |
| iSWTaskCntr01 | S/w task TCO | Increments | |
| 10110010101 | counter | by 60 per | |
| | councer | packet | |
| iSWTaskCntr02 | S/w task | 1 | |
| ISWIASKUNTTUZ | -, | | |
| | HV_Ramp | | |
| | counter | | |
| iSWTaskCntr03 | S/w task | Increments | |
| | DPU_Mntr | by 1 per | |
| | counter | packet | |
| iSWTaskCntr04 | S/w task | Increments | |
| | Htr_Cntrol | by 10 per | |
| | counter | packet | |
| iSWTaskCntr05 | S/w task | Increments | |
| | Limit_chck | by 6 per | |
| | counter | packet | |
| iSWTaskCntr06 | S/w task | 1 | |
| TOWTGOVCHICTOO | | 1 × | |
| | Mechanism | | |
| | counter | | |
| iSWTaskCntr07 | S/w task | Increments | |
| | Feed_1553 | by 10 per | |
| | counter | packet | |
| iSWTaskCntr08 | S/w task HK | Increments | |
| | • | I | |

| | counter | by 7 per packet | |
|------------------|--------------------------------------|----------------------------------|--|
| iSWTaskCntr09 | S/w task Mem Dump counter | No increment | |
| ISWTaskCntr10 | S/w task DCS counter | No increment | |
| ISWTaskCntr11 | S/w task Load Centroid counter | No increment | |
| ISWTaskCntr12 | S/w task Load Window counter | No increment | |
| ISWTaskCntr13 | S/w task Feed SSI counter | No increment | |
| ISWTaskCntr14 | S/w task Star Cat counter | No increment | |
| iWatchdogTskCntr | Watchdog Task Counter | Increments by 2 per packet | |
| H0864SEQCNT | Packet Sequence Count | Increments by 1 per packet | |

If all responses in column 5 of the table above are Y's then the test is successful.

Test Successful _____

Initials _____ Date _____ Time _____

Subtest 1, both flags 0

| Variable | Description | Value seen | Value expected | Are values seen and expected the same Y/N |
|-----------------|---|------------|-------------------|--|
| iDPUTempPSUAF | DPU Temp PSU A Status Flags | | 00 | |
| iDPUTempPSUBF | DPU Temp PSU B Status Flags | | 00 | |
| iDPUTempICUCPUF | DPU Temp ICU CPU Module Status Flags | | 00 | |
| iDPUTempICUIFF | DPU Temp ICU I/F Module Status Flags | | 00 | |
| iDPUTempCommF | DPU Temp | | 00 | |

| | DDU Comm /Mar | | | |
|-----------------|---------------|---|----|--|
| | DPU Comm/Mem | | | |
| | Module | | | |
| | Status Flags | | | |
| iDPUTempRes1F | DPU Temp | | 00 | |
| | Reserve 1 | | | |
| | Status Flags | | | |
| iDPUTempRes2F | DPU Temp | | 00 | |
| | Reserve 2 | | | |
| | Status Flags | | | |
| iDPUPlus5VAF | DPU Voltage | | 00 | |
| | PSU A +5V | | | |
| | Status Flags | | | |
| iDPUPlus5VBF | DPU Voltage | | 00 | |
| | PSU B +5V | | | |
| | Status Flags | | | |
| iDPUPlus12VAF | DPU Voltage | | 00 | |
| | PSU A +12V | | | |
| | Status Flags | | | |
| iDPUMinus12VAF | DPU Voltage | | 00 | |
| | PSU A -12V | | | |
| | Status Flags | | | |
| iDPUPlus5VRefF | DPU Voltage | | 00 | |
| | PSU +5V Ref | | | |
| | Status Flags | | | |
| iDPUMinus5VRefF | DPU Voltage | | 00 | |
| | PSU -5V Ref | | | |
| | Status Flags | | | |
| iDPUPowerResF | DPU Power | | 00 | |
| | Reserve | | | |
| | Status Flags | | | |
| | Statub I Lagb | I | 1 | |

If all responses in column 5 of the table above are Y's then the test is successful.

Test Successful _____

Initials _____ Date _____ Time _____

Subtest 2, first flag 0, second flag 1

| Variable | Description | Value seen | Value expected | Are values seen and expected the same Y/N |
|-----------------|-----------------------------------|------------|-------------------|--|
| iDPUTempPSUAF | DPU Temp PSU A Status Flags | | 01 | |
| iDPUTempPSUBF | DPU Temp PSU B Status Flags | | 01 | |
| iDPUTempICUCPUF | DPU Temp ICU CPU Module | | 01 | |

| | Status Flags | | |
|-----------------|--------------|----|--|
| iDPUTempICUIFF | DPU Temp | 01 | |
| 1 | ICU I/F | | |
| | Module | | |
| | Status Flags | | |
| iDPUTempCommF | DPU Temp | 01 | |
| 1 | DPU Comm/Mem | | |
| | Module | | |
| | Status Flags | | |
| iDPUTempRes1F | DPU Temp | 01 | |
| _ | Reserve 1 | | |
| | Status Flags | | |
| iDPUTempRes2F | DPU Temp | 01 | |
| | Reserve 2 | | |
| | Status Flags | | |
| iDPUPlus5VAF | DPU Voltage | 01 | |
| | PSU A +5V | | |
| | Status Flags | | |
| iDPUPlus5VBF | DPU Voltage | 01 | |
| | PSU B +5V | | |
| | Status Flags | | |
| iDPUPlus12VAF | DPU Voltage | 01 | |
| | PSU A +12V | | |
| | Status Flags | | |
| iDPUMinus12VAF | DPU Voltage | 01 | |
| | PSU A -12V | | |
| | Status Flags | | |
| iDPUPlus5VRefF | DPU Voltage | 01 | |
| | PSU +5V Ref | | |
| | Status Flags | | |
| iDPUMinus5VRefF | DPU Voltage | 01 | |
| | PSU -5V Ref | | |
| | Status Flags | | |
| iDPUPowerResF | DPU Power | 01 | |
| | Reserve | | |
| | Status Flags | | |

If all responses in column 5 of the table above are Y's then the test is successful.

Test Successful _____

Initials _____ Date _____ Time _____

Subtest 3, first flag 1, second flag 0

| Variable | Description | Value seen | Value expected | Are values seen and expected the same Y/N |
|---------------|-----------------------------------|------------|-------------------|--|
| iDPUTempPSUAF | DPU Temp PSU A Status Flags | | 10 | |

| iDPUTempPSUBF | DPU Temp | 10 | |
|------------------|----------------------------|-----|----------|
| L | PSU B Status | 10 | |
| | Flags | | |
| iDPUTempICUCPUF | DPU Temp | 10 | |
| - | ICU CPU | | |
| | Module | | |
| | Status Flags | | |
| iDPUTempICUIFF | DPU Temp | 10 | |
| | ICU I/F | | |
| | Module | | |
| | Status Flags | | |
| iDPUTempCommF | DPU Temp | 10 | |
| | DPU Comm/Mem | | |
| | Module | | |
| | Status Flags | | |
| iDPUTempRes1F | DPU Temp | 10 | |
| | Reserve 1 | | |
| | Status Flags | | |
| iDPUTempRes2F | DPU Temp | 10 | |
| | Reserve 2 | | |
| | Status Flags | | |
| iDPUPlus5VAF | DPU Voltage | 10 | |
| | PSU A +5V | | |
| | Status Flags | | |
| iDPUPlus5VBF | DPU Voltage | 10 | |
| | PSU B +5V | | |
| | Status Flags | | |
| iDPUPlus12VAF | DPU Voltage | 10 | |
| | PSU A +12V | | |
| | Status Flags | | |
| iDPUMinus12VAF | DPU Voltage | 10 | |
| | PSU A -12V | | |
| | Status Flags | 1.0 | |
| iDPUPlus5VRefF | DPU Voltage | 10 | |
| | PSU +5V Ref | | |
| iDPUMinus5VRefF | Status Flags | 1.0 | |
| 1DPUMINUS5VKeff' | DPU Voltage PSU -5V Ref | 10 | |
| | | | |
| | Status Flags | 1.0 | |
| iDPUPowerResF | DPU Power | 10 | |
| | Reserve | | |
| | Status Flags | | <u> </u> |

If all responses in column 5 of the table above are Y's then the test is successful.

Test Successful _____

Initials _____ Date _____ Time _____

Subtest 4, both flags 1

| Variable | Description | Value seen | Value | Are values |
|----------|-------------|------------|-------|------------|
|----------|-------------|------------|-------|------------|

| | | expected | seen and expected the same Y/N |
|-----------------|--|----------|--------------------------------------|
| iDPUTempPSUAF | DPU Temp PSU A Status Flags | 11 | |
| iDPUTempPSUBF | DPU Temp PSU B Status Flags | 11 | |
| iDPUTempICUCPUF | DPU Temp ICU CPU Module Status Flags | 11 | |
| iDPUTempICUIFF | DPU Temp ICU I/F Module Status Flags | 11 | |
| iDPUTempCommF | DPU Temp DPU Comm/Mem Module Status Flags | 11 | |
| iDPUTempRes1F | DPU Temp Reserve 1 Status Flags | 11 | |
| iDPUTempRes2F | DPU Temp Reserve 2 Status Flags | 11 | |
| iDPUPlus5VAF | DPU Voltage PSU A +5V Status Flags | 11 | |
| iDPUPlus5VBF | DPU Voltage PSU B +5V Status Flags | 11 | |
| iDPUPlus12VAF | DPU Voltage PSU A +12V Status Flags | 11 | |
| iDPUMinus12VAF | DPU Voltage PSU A -12V Status Flags | 11 | |
| iDPUPlus5VRefF | DPU Voltage PSU +5V Ref Status Flags | 11 | |
| iDPUMinus5VRefF | DPU Voltage PSU -5V Ref Status Flags | 11 | |
| iDPUPowerResF | DPU Power Reserve Status Flags | 11 | |

If all responses in column 5 of the table above are Y's then the test is successful.

Test Successful

Initials _____ Date _____ Time _____

Subtest 5, change basic and oper version numbers

Use all of the configuration files from test 2 above but edit the code to give the basic version number as 126 (decimal) and the oper version as 60 (decimal). Check that these values are now picked up by the housekeeping.

| Variable | Description | Value seen | Value expected | Are values seen and expected the same Y/N |
|---------------|-------------|------------|-------------------|--|
| iVersionBasic | Basic S/W | | 0x7E | |
| | Version | | | |
| iVersionOper | Oper S/W | | 0x3C | |
| | Version | | | |

If all responses in column 5 of the table above are Y's then the test is successful.

Test Successful _____

Initials _____ Date _____ Time _____

Test 3, all values high

Run the telescope simulator with valid housekeeping configuration file hk_all_high.dat. Check that the values displayed on the telescope simulator window are the same as those given in the table below – if they are not, check against the configuration file and make any alterations necessary to get agreement before running this test. Enter a high range set of values (A to D channels, parity errors and reserves, mode and submode) into the DPU simulator, as defined in the table below.

Check one housekeeping packet against the configuration file to make sure that they are the same.

Note that in the case of incrementing values, there may be some beating with the housekeeping display, and so the value given should be an average over several packets. It is given in the table below as a decimal value.

All values that are indicated in hex in the housekeeping are given in hex here.

| Variable | Description | Value or increase in value seen | Value or increase in value expected | Are values seen and expected the same Y/N |
|----------|-------------|---------------------------------------|--|--|
| iBPETemp | BPE | | 0x3FF | |
| | Thermistor | | | |

| | Readings | | |
|-----------------------|--------------|-------|--|
| iBPERefBTemp | BPE | 0x3FF | |
| тврекетвтешр | Thermistor | UXSEE | |
| | | | |
| | Readings | | |
| iBPERefCTemp | BPE | 0x3FF | |
| | Thermistor | | |
| | Readings | | |
| iBPEMainTemp | BPE | 0x3FF | |
| | Thermistor | | |
| | Readings | | |
| | BPE | 0x3FF | |
| iBPEForward1Temp | Thermistor | | |
| - | Readings | | |
| | BPE | 0x3FF | |
| iBPEForward2Temp | Thermistor | | |
| ibi bi of war az remp | Readings | | |
| iBPECCDTemp | BPE | 0x3FF | |
| TBFFCCDIemp | Thermistor | UXSEE | |
| | | | |
| | Readings | | |
| iBPERefATemp | BPE | 0x3FF | |
| | Thermistor | | |
| | Readings | | |
| iHVmcp1 | Vmcp1 | 0x3FF | |
| iHVmcp23 | Vmcp23 | 0x3FF | |
| iHVCathode | Vcathode | 0x3FF | |
| iLVPlus5 | Low Voltage | 0x3FF | |
| | +5 | | |
| iLVPlus15 | Low Voltage | 0x3FF | |
| | +15 | | |
| iLVMinus15 | Low Voltage | 0x3FF | |
| THVIITINGSTO | -15 | | |
| iLVRef | Low Voltage | 0x3FF | |
| ITAKEI | 1.23 V | UXSEE | |
| | | | |
| | Reference | 0.077 | |
| iFWPickOff | F/W Analogue | 0x3FF | |
| | Pick-Off | | |
| | BPE | 1 | |
| iBPEIntegratNbld | Integration | | |
| | Enabled | | |
| iBPEAcqMode | BPE | 7 | |
| _ | Acquisition | | |
| | Mode | | |
| | Frame Tag | 0 | |
| iBPEFrameTagNbld | Enabled | | |
| iBPECentrdTblOk | Centroid | 1 | |
| TELECTICIAIDION | Table Access | | |
| iBPECamStarted | Camera | 1 | |
| TDEECAMOLALLEU | | | |
| | Started/No | | |
| | Window Tble | | |
| | Access | | |
| iFWCounter | F/W Position | Blank | |
| | Counter | | |
| iTMPSUPlus28 | +28V Rail | OxFF | |
| | 120V Raii | | |
| | Current | | |

| | Cummont | |
|--------------------|---------------|------------|
| | Current | 0.55 |
| iTMPSUPlus15 | +15V Rail | 0xFF |
| | Current | |
| iTMPSUMinus15 | -15V Rail | 0 xFF |
| | Current | |
| iTMPSUPlus5B | +5VB Rail | OxFF |
| | Current | |
| iTMPSUPlus5A | +5VA Rail | 0xFF |
| | Current | |
| iTMPSUMinus5A | -5VA Rail | 0xFF |
| | Current | |
| iTMPSUDisMon | DISMON, | 0xFF |
| | Ballast | |
| | Resistor Temp | |
| | Comparitor | |
| | Status | |
| iSC1553Ints | 1553 | Increments |
| TOCTODOTICS | Interrupt | by 60 per |
| | Count | packet |
| iSC1553IHTC | | <u> </u> |
| 1SCI553IHTC | 1553 IHTC | Increments |
| | Count | by 60 per |
| | | packet |
| iSC1553TCPckt | 1553 TC | Increments |
| | Packet Count | by 60 per |
| | | packet |
| iDPUMode | DPU Mode | OxFF |
| iDPUSubMode | DPU SubMode | OxFF |
| iDPUTempPSUA | DPU Temp PSU | 0xFFF |
| - | A | |
| iDPUTempPSUB | DPU Temp PSU | OxFFF |
| L. | В | |
| iDPUTempICUCPU | DPU Temp ICU | OxFFF |
| | CPU Module | |
| iDPUTempICUIF | DPU Temp ICU | OxFFF |
| Theorempicori | I/F Module | |
| iDPUTempComm | DPU Temp DPU | 0×FFF |
| TDF0Tempcomm | Comm/Mem | OXFFF |
| | Module | |
| | | 0xFFF |
| iDPUTempRes1 | DPU Temp | UXFFF |
| | Reserve 1 | |
| iDPUTempRes2 | DPU Temp | Oxfff |
| | Reserve 2 | |
| iDPUPlus5VA | DPU Voltage | OxFFF |
| | PSU A +5V | |
| iDPUPlus5VB | DPU Voltage | OxFFF |
| | PSU B +5V | |
| iDPUPlus12VA | DPU Voltage | OxFFF |
| | PSU A +12V | |
| iDPUMinus12VA | DPU Voltage | OxFFF |
| | PSU A -12V | |
| iDPUPlus5VRef | DPU Voltage | OxFFF |
| | PSU +5V Ref | |
| iDPUMinus5VRef | DPU Voltage | 0xFFF |
| TDI OLITIINSOAIVET | PSU -5V Ref | VALIT |
| i DDUD otrombo o | | |
| iDPUPowerRes | DPU Power | OxFFF |

| | Reserve | | |
|------------------|-------------|--------|--|
| | DPU Parity | OxFFFF | |
| iDPUParityErrors | Errors | | |
| iDPURes1 | DPU Reserve | OxFFFF | |
| | 1 | | |
| iDPURes2 | DPU Reserve | OxFFFF | |
| | 2 | | |

If all responses in column 5 of the table above are Y's then the test is successful.

Test Successful _____

5.2 Copy to TDRSS

Open two packet dump windows using Pktdump vc0 0x3C1 Pktdump vc0 0x362

Make a note of the TDRSS counter value from housekeeping here _____

Send a copy of the next HK packet to TDRSS using /iHKTDRSS Packets=1

Check that the TDRSS counter increases by 1

TDRSS Counter increases by 1 Y/N_____

Check that a packet appears in the 0x3C1 packet dump window, and that, except for the header, this packet is identical to the corresponding packet in the 0x360 window.

TDRSS HK copy packet appears Y/N_____ TDRSS copy identical to standard HK Y/N_____

Send the command
/iHKTDRSS Packets=0

Check that this is rejected ie no packets appear.

TDRSS HK copy packet appears Y/N_____

Send the command /iHKTDRSS Packets=301

Check that this is rejected ie no packets appear.

TDRSS HK copy packets appear Y/N_____

Send the maximum allowed number of packets to TDRSS using /iHKTDRSS Packets=300

Check that packets appear in the packet dump window.

TDRSS HK copy packets appear Y/N_____

If the above responses are Y, Y, N, N and Y respectively then the test is successful.

 Test Successful Y/N_____

 Initials _____ Date _____ Time _____

5.3 Rate changes

First use a sequence print or the packet dump window in ITOS to examine two successive housekeeping packets. Check that the sequence count of the second is one greater than the sequence count of the first, and that the timestamp on the second is 1s greater than that on the first. Also check the packet length on one of them – it should be 223.

Sequence count of second packet 1 greater than that of first Y/N_____ Timestamp of second packet 10s greater than that of first Y/N_____ Packet length is 223 Y/N______

Command housekeeping rate to be 1 per 4, 6, 10, 60 and 100s. Eg /iHKRate Rate=4

Check the housekeeping telemetry at each rate.

Check the rate the housekeeping packets are arriving at, with a stopwatch for a rough guide, or by examining their timestamps. Note that due to timing matters on the display and elsewhere a jitter of +/-1 s on the observed timestamp is acceptable.

| Requested housekeeping rate | Observed housekeeping rate | Requested and observed rates are the same Y/N |
|-----------------------------|-------------------------------|--|
| 1 per 4s | | |
| 1 per 6s | | |
| 1 per 10s | | |
| 1 per 60s | | |
| 1 per 100s | | |

Disable range checking on the iHKRate command in ITOS.

Check that illegal rates are rejected by commanding the rate to be 1 per 0, 3, 101 and 200s.

In each case an 'Illegal Parameter Values' NHK message should be received.

| Requested housekeeping rate | 'Illegal Parameter Values' received Y/N |
|-----------------------------|---|
| 1 per 0s | |
| 1 per 3s | |
| 1 per 101s | |
| 1 per 200s | |

Re-enable range checking on the iHKRate command in ITOS.

If all responses above and in column 3 of the first table and column 2 of the second table above are Y's then the test is successful.

 Test Successful Y/N_____

 Initials _____ Date _____ Time _____

5.4 Stop and start

Command the housekeeping to stop using. /iHKOff

Check that no housekeeping packets arrive.

HK packets arrive Y/N_____

Wait 2 minutes, then command housekeeping to start using / iHKOn

Check that housekeeping packets start arriving within 30s.

HK packets start arriving within 20s Y/N_____

Wait 2 minutes, then command housekeeping to start when started using /iHK <code>Enable=On</code>

Check that the housekeeping continues.

HK packets keep arriving Y/N_____

Wait 2 minutes, then command housekeeping to stop when started using /iHK <code>Enable=Off</code>

Check that the housekeeping stops within 20s.

HK packets stop arriving within 20s Y/N_____

Wait 2 minutes, then command housekeeping to stop when stopped using / iHKOff

Check over 1 minute that the housekeeping stays stopped.

HK packets stay stopped Y/N_____

Wait 2 minutes, then command housekeeping to start after stoppage (this is different from starting it after a stop at initial switch on, as the system is in a different state in this case) using

/iHKOn

Check that the housekeeping starts within 20s.

HK packets start arriving within 20s Y/N_____

If the first response above is a N and all other responses are Y's then the test is successful.

Test Successful Y/N_____

5.5 Task

Command a long memory dump using /iICUDump Mid=0, Offset=0, NumBytes=0xFFFF, APID=0x390

Check that the housekeeping rate is normal by examining the timestamps in housekeeping under iTIME and iSUBSECS – the packets should arrive one every 10s

HK packets arriving 1 per 10s Y/N_____

If the above response is Y then the test is successful.

Test Successful _____

6. **DPU**

Note that the processing of DPU commands is the responsibility of the DPU team. The tests in this section are only concerned with checking that these commands can be passed by the ICU to the DPU correctly.

6.1 DPU Task

Check on the housekeeping display that the DPU task and data manager are enabled, and that the DPU Task counter increases by 10 per hk packet.

DPU task enabled Y/N_____ DPU Data Manager enabled Y/N_____ DPU Task counter increases by 10 per hk packet Y/N______

Send the command /iDPUTask Enable=Off

Check on the housekeeping display that the DPU task and monitor are disabled, and that the DPU task counter does not increase.

DPU task disabled Y/N_____ DPU Monitor disabled Y/N_____ DPU task counter unchanging Y/N_____

Again send the command /iDPUTask Enable=Off

Check on the housekeeping display that the DPU task is still disabled.

DPU task disabled Y/N_____

Send the command /iDPUTask Enable=On

Check on the housekeeping display that the DPU task is enabled again.

DPU task enabled Y/N_____

Again send the command /iDPUTask Enable=On

Check on the housekeeping display that the DPU task is still enabled.

DPU task enabled Y/N_____

If the responses above are all Y's then the test is successful.

Test Successful Y/N_____

6.2 DPU Mode

Run the ITOS script testdpumode.proc using Start testdpumode

Check on the housekeeping display that the DPU does not crash. Check on the DPU display that 'DPU Mode Ready' and 'DPU Mode Complete' messages are received.

DPU crashed Y/N_____ 'DPU Mode Ready' received Y/N_____ 'DPU Mode Complete' received Y/N_____

If the responses above are N, Y and Y respectively then the test is successful.

Test Successful Y/N_____

6.3 Other commands

Make a note from the housekeeping display of the Feed SSI task counter value _____

Send the command /iDPUStop

Check on the housekeeping display that the Feed SSI task counter has increased by 1.

Feed SSI task counter increased by 1 Y/N_____

Check that a verification 'Successful Acceptance' message and a DPU ACK message are received.

'Successful Acceptance' received Y/N_____ DPU ACK received Y/N_____

Send the command /iDPUPurgeDCX

Check that a verification 'Successful Acceptance' message and a DPU ACK message are received.

'Successful Acceptance' received Y/N_____ DPU ACK received Y/N_____

Send the command /iDPUPurgeSci

Check that a verification 'Successful Acceptance' message and a DPU ACK message are received.

'Successful Acceptance' received Y/N_____ DPU ACK received Y/N_____

Run the ITOS script testdpuxrtpos.proc using Start testdpuxrtpos

Check that a verification 'Successful Acceptance' message and a DPU ACK message are received.

'Successful Acceptance' received Y/N_____ DPU ACK received Y/N_____

Send the command /iDPUAbort

Check that a verification 'Successful Acceptance' message and a DPU ACK message are received.

'Successful Acceptance' received Y/N_____ DPU ACK received Y/N_____

Send the command /iDPUNoop

Check that a verification 'Successful Acceptance' message and a DPU ACK message are received.

'Successful Acceptance' received Y/N_____
DPU ACK received Y/N_____

Send the command /iDPUReboot

Wait 3 minutes, then check on the housekeeping display that the DPU is sending heartbeats, and check on the DPU display that a 'DPU Boot Complete' message is received.

DPU heartbeats restart Y/N______ 'DPU Boot Complete' received Y/N______

If all the responses above are Y's then the test is successful.

Test Successful Y/N_____

6.4 Other messages

Edit the code to force out a 'DPU NAK' NHK message, and run this test code.

'DPU NAK' received Y/N_____

Edit the code to force out a 'DPU Timeout' NHK message, and run this test code.

'DPU Timeout' received Y/N_____

Edit the code to force out a 'DPU Incorrect ACK' NHK message, and run this test code.

'DPU Incorrect ACK' received Y/N_____

Edit the code to force out a 'DPU Unexpected ACK NAK' NHK message, and run this test code.

'DPU Unexpected ACK NAK' received Y/N_____

Edit the code to force out a 'DPU Inconsistent APID ID' NHK message, and run this test code.

'DPU Inconsistent APID ID' received Y/N_____

Edit the code to force out a 'DPU Invalid APID or ID' NHK message, and run this test code.

'DPU Invalid APID or ID' received Y/N_____

Alter the DPU simulator so it always responds to the DPU aliveness test with a NAK.

Send the aliveness test. /iDPUNoop

Check on the NHK display that a NAK is received, and forwarded by the ICU.

NAK received Y/N_____ NAK forwarded Y/N_____

Check that the ICU retries the aliveness test twice and then gives up.

ICU retries twice Y/N_____ ICU discontinues retrying Y/N_____

If all the responses above are Y's then the test is successful.

Test Successful Y/N_____

6.5 Heartbeat monitor

Load flight code icu.hex

Command the ICU to the idle state /istate state=idle

Make sure from the NHK display that DPU heartbeats are on and being forwarded.

DPU heartbeats being forwarded Y/N_____

Switch off the DPU heartbeats, and make sure that the ICU safes itself.

ICU goes to safe Y/N_____

Restart the DPU heartbeats.

Check on the housekeeping display that the heartbeat monitor value is increasing between successive updates.

Heartbeat monitor value increasing Y/N_____

Upload a new table to stop the heartbeat monitor.

Load flight code icu.hex

Check on the housekeeping display that the heartbeat monitor value is static between successive updates.

Heartbeat monitor value static Y/N_____

Reload the standard table, to restart the heartbeat monitor.

If all the responses above are Y's then the test is successful.

Test Successful Y/N_____

7. EXCEPTIONS

7.1 Main ada program

Force an Ada exception by making a divide by zero error in the main loop of icu.ada. Recompile this test version of the code and run it.

Make sure that the code doesn't crash.

Make sure that an nhk packet arrives detailing a constraint error, with package code 0x10, error 0xEC, Param1 0x1000, Param2 0x1000 and last progress the same as the last progress before where the code causing the exception was inserted. Eg if the divide by zero was inserted at line 50, and the last progress before that was 40, then the nhk packet should give the last progress as 40. Also make sure an hk packet arrives with debug first exception set to the same as nhk Param1 and debug first progress set to the same as nhk Param3.

| | Result | Expected result | Are result and expected result the same Y/N |
|---------------------------|--------|-------------------------|---|
| Code crashes Y/N | | N | |
| NHK packet arrives Y/N | | Y | |
| NHK pkg value | | 0x10 | |
| NHK err value | | 0xEC | |
| NHK Param1 value | | 0x1000 | |
| NHK Param2 value | | 0x1000 | |
| Last progress in code | | Any value is permitted | |
| before error inserted | | | |
| Last progress reached | | The same value as was | |
| when running (ie NHK | | written in for 'last | |
| Param3 value) | | progress in code before | |
| | | error inserted' | |
| HK iDebug1stEx value | | 0x1000 | |
| HK iDebug1stProg | | The same value as was | |
| value | | written in for 'last | |
| | | progress in code before | |
| | | error inserted' | |

If all the responses in column 4 of the table above are Y's then the test is successful.

Test Successful Y/N_____

7.2 DPU Data manager

Force an Ada exception by making a divide by zero error in the main loop of DPU_DATA_MANAGER.

Recompile this test version of the code and run it.

Make sure that the code doesn't crash.

Make sure that an NHK packet arrives detailing a constraint error, with package code 0xD0, error 0xEC, Param1 0xD000, Param2 0xD000 and last progress the same as the last progress before where the code causing the exception was inserted. Eg if the divide by zero was inserted at line 50, and the last progress before that was 40, then the NHK packet should give the last progress as 40. Also make sure an hk packet arrives with debug first exception set to the same as nhk Param1 and debug first progress set to the same as nhk Param3.

| | Result | Expected result | Are result and expected result the same Y/N |
|---|--------|--|---|
| Code crashes Y/N | | N | |
| NHK packet arrives Y/N | | Y | |
| NHK pkg value | | 0xD0 | |
| NHK err value | | 0xEC | |
| NHK Param1 value | | 0xD000 | |
| NHK Param2 value | | 0xD000 | |
| Last progress in code | | Any value is permitted | |
| before error inserted | | | |
| Last progress reached when running (ie NHK | | The same value as was written in for 'last | |
| Param3 value) | | progress in code before | |
| | | error inserted' | |
| HK iDebug1stEx value | | 0xD000 | |
| HK iDebug1stProg | | The same value as was | |
| value | | written in for 'last | |
| | | progress in code before | |
| | | error inserted' | |

If all the responses in column 4 of the table above are Y's then the test is successful.

Test Successful Y/N_____

7.3 Heater Control

Force an Ada exception by making a divide by zero error in the main loop of HEATER_CONTROL.

Recompile this test version of the code and run it.

Make sure that the code doesn't crash.

Make sure that an NHK packet arrives detailing a constraint error, with package code 0x45, error 0xEC, Param1 0x4500, Param2 0x4500 and last progress the same as the last progress before where the code causing the exception was inserted. Eg if the divide by zero was inserted at line 50, and the last progress before that was 40, then the NHK packet should give the last progress as 40. Also make sure an hk packet arrives with debug first exception set to the same as nhk Param1 and debug first progress set to the same as nhk Param3.

| | Result | Expected result | Are result and expected result the same Y/N |
|--|--------|---|---|
| Code crashes Y/N | | N | |
| NHK packet arrives Y/N | | Y | |
| NHK pkg value | | 0x45 | |
| NHK err value | | 0xEC | |
| NHK Param1 value | | 0x4500 | |
| NHK Param2 value | | 0x4500 | |
| Last progress in code before error inserted | | Any value is permitted | |
| Last progress reached when running (ie NHK Param3 value) | | The same value as was written in for 'last progress in code before error inserted' | |
| HK iDebug1stEx value | | 0x4500 | |
| HK iDebug1stProg | | The same value as was | |
| value | | written in for 'last progress in code before error inserted' | |

If all the responses in column 4 of the table above are Y's then the test is successful.

Test Successful Y/N_____

7.4 Housekeeping type

Force an Ada exception by making a divide by zero error in the main loop of HOUSEKEEPING_TYPE.

Recompile this test version of the code and run it.

Make sure that the code doesn't crash.

Make sure that an NHK packet arrives detailing a constraint error, with package code 0x23, error 0xEC, Param1 0x2300, Param2 0x2300 and last progress the same as the last progress before where the code causing the exception was inserted. Eg if the divide by zero was inserted at line 50, and the last progress before that was 40, then the NHK packet should give the last progress as 40. Also make sure an hk packet arrives with debug first exception set to the same as nhk Param1 and debug first progress set to the same as nhk Param3.

| | Result | Expected result | Are result and expected result the same Y/N |
|--|--------|---|---|
| Code crashes Y/N | | N | |
| NHK packet arrives Y/N | | Y | |
| NHK pkg value | | 0x23 | |
| NHK err value | | 0xEC | |
| NHK Param1 value | | 0x2300 | |
| NHK Param2 value | | 0x2300 | |
| Last progress in code before error inserted | | Any value is permitted | |
| Last progress reached when running (ie NHK Param3 value) | | The same value as was written in for 'last progress in code before error inserted' | |
| HK iDebug1stEx value | | 0x2300 | |
| HK iDebug1stProg | | The same value as was | |
| value | | written in for 'last progress in code before error inserted' | |

If all the responses in column 4 of the table above are Y's then the test is successful.

Test Successful Y/N_____

7.5 Memory dump type

Force an Ada exception by making a divide by zero error in the main loop of MEMORY_DUMP_TYPE.

Recompile this test version of the code and run it.

Make sure that the code doesn't crash.

Make sure that an NHK packet arrives detailing a constraint error, with package code 0x12, error 0xEC, Param1 0x120A, Param2 0x120A and last progress the same as the last progress before where the code causing the exception was inserted. Eg if the divide by zero was inserted at line 50, and the last progress before that was 40, then the NHK packet should give the last progress as 40. Also make sure an hk packet arrives with debug first exception set to the same as nhk Param1 and debug first progress set to the same as nhk Param3.

| | Result | Expected result | Are result and expected result the same Y/N |
|---------------------------|--------|-------------------------|---|
| Code crashes Y/N | | N | |
| NHK packet arrives Y/N | | Y | |
| NHK pkg value | | 0x12 | |
| NHK err value | | 0xEC | |
| NHK Param1 value | | 0x120A | |
| NHK Param2 value | | 0x120A | |
| Last progress in code | | Any value is permitted | |
| before error inserted | | | |
| Last progress reached | | The same value as was | |
| when running (ie NHK | | written in for 'last | |
| Param3 value) | | progress in code before | |
| | | error inserted' | |
| HK iDebug1stEx value | | 0x120A | |
| HK iDebug1stProg | | The same value as was | |
| value | | written in for 'last | |
| | | progress in code before | |
| | | error inserted' | |

If all the responses in column 4 of the table above are Y's then the test is successful.

Test Successful Y/N_____

7.6 Limit Monitoring

Force an Ada exception by making a divide by zero error in the main loop of LIMIT_MONITORING.

Recompile this test version of the code and run it.

Make sure that the code doesn't crash.

Make sure that an NHK packet arrives detailing a constraint error, with package code 0x11, error 0xEC, Param1 0x1100, Param2 0x1100 and last progress the same as the last progress before where the code causing the exception was inserted. Eg if the divide by zero was inserted at line 50, and the last progress before that was 40, then the NHK packet should give the last progress as 40. Also make sure an hk packet arrives with debug first exception set to the same as nhk Param1 and debug first progress set to the same as nhk Param3.

| | Result | Expected result | Are result and expected result the same Y/N |
|---|--------|---|---|
| Code crashes Y/N | | N | |
| NHK packet arrives Y/N | | Y | |
| NHK pkg value | | 0x11 | |
| NHK err value | | 0xEC | |
| NHK Param1 value | | 0x1100 | |
| NHK Param2 value | | 0x1100 | |
| Last progress in code | | Any value is permitted | |
| before error inserted | | | |
| Last progress reached when running (ie NHK | | The same value as was written in for 'last | |
| Param3 value) | | progress in code before error inserted' | |
| HK iDebug1stEx value | | 0x1100 | |
| HK iDebug1stProg | | The same value as was | |
| value | | written in for 'last | |
| | | progress in code before | |
| | | error inserted' | |

If all the responses in column 4 of the table above are Y's then the test is successful.

Test Successful Y/N_____

7.7 Mech

Force an Ada exception by making a divide by zero error in the main loop of MECH. Recompile this test version of the code and run it.

Make sure that the code doesn't crash.

Make sure that an NHK packet arrives detailing a constraint error, with package code 0x40, error 0xEC, Param1 0x400A, Param2 0x400A and last progress the same as the last progress before where the code causing the exception was inserted. Eg if the divide by zero was inserted at line 50, and the last progress before that was 40, then the NHK packet should give the last progress as 40. Also make sure an hk packet arrives with debug first exception set to the same as nhk Param1 and debug first progress set to the same as nhk Param3.

| | Result | Expected result | Are result and expected result the same Y/N |
|--|--------|---|---|
| Code crashes Y/N | | N | |
| NHK packet arrives Y/N | | Y | |
| NHK pkg value | | 0x40 | |
| NHK err value | | 0xEC | |
| NHK Param1 value | | 0x400F | |
| NHK Param2 value | | 0x400F | |
| Last progress in code before error inserted | | Any value is permitted | |
| Last progress reached when running (ie NHK Param3 value) | | The same value as was written in for 'last progress in code before error inserted' | |
| HK iDebug1stEx value | | 0x400F | |
| HK iDebug1stProg | | The same value as was | |
| value | | written in for 'last progress in code before error inserted' | |

If all the responses in column 4 of the table above are Y's then the test is successful.

Test Successful Y/N_____

7.8 TCQ

Force an Ada exception by making a divide by zero error in the main loop of TCQ. Recompile this test version of the code and run it.

Make sure that the code doesn't crash.

Make sure that an NHK packet arrives detailing a constraint error, with package code 0x2C, error 0xEC, Param1 0x2C0F, Param2 0x2C0F and last progress the same as the last progress before where the code causing the exception was inserted. Eg if the divide by zero was inserted at line 50, and the last progress before that was 40, then the NHK packet should give the last progress as 40. Also make sure an hk packet arrives with debug first exception set to the same as nhk Param1 and debug first progress set to the same as nhk Param3.

| | Result | Expected result | Are result and expected result the same Y/N |
|--|--------|---|---|
| Code crashes Y/N | | N | |
| NHK packet arrives Y/N | | Y | |
| NHK pkg value | | 0x2C | |
| NHK err value | | 0xEC | |
| NHK Param1 value | | 0x2C0F | |
| NHK Param2 value | | 0x2C0F | |
| Last progress in code | | Any value is permitted | |
| before error inserted | | | |
| Last progress reached when running (ie NHK Param3 value) | | The same value as was written in for 'last progress in code before error inserted' | |
| HK iDebug1stEx value | | 0x2C0F | |
| HK iDebug1stProg | | The same value as was | |
| value | | written in for 'last | |
| | | progress in code before error inserted' | |

If all the responses in column 4 of the table above are Y's then the test is successful.

Test Successful Y/N_____

7.9 Feed 1553 type

Force an Ada exception by making a divide by zero error in the main loop of FEED_1553_TYPE.

Recompile this test version of the code and run it.

Make sure that the code doesn't crash.

Make sure that an NHK packet arrives detailing a constraint error, with package code 0x2F, error 0xEC, Param1 0x2F0A, Param2 0x2F0A and last progress the same as the last progress before where the code causing the exception was inserted. Eg if the divide by zero was inserted at line 50, and the last progress before that was 40, then the NHK packet should give the last progress as 40. Also make sure an hk packet arrives with debug first exception set to the same as nhk Param1 and debug first progress set to the same as nhk Param3.

| | Result | Expected result | Are result and expected result the same Y/N |
|--|--------|---|---|
| Code crashes Y/N | | N | |
| NHK packet arrives Y/N | | Y | |
| NHK pkg value | | 0x2F | |
| NHK err value | | 0xEC | |
| NHK Param1 value | | 0x2F0A | |
| NHK Param2 value | | 0x2F0A | |
| Last progress in code before error inserted | | Any value is permitted | |
| Last progress reached when running (ie NHK Param3 value) | | The same value as was written in for 'last progress in code before error inserted' | |
| HK iDebug1stEx value | | 0x2F0A | |
| HK iDebug1stProg | | The same value as was | |
| value | | written in for 'last progress in code before error inserted' | |

If all the responses in column 4 of the table above are Y's then the test is successful.

Test Successful Y/N_____

7.10 Watchdog task

Force an Ada exception by making a divide by zero error in the main loop of WATCHDOG_TASK.

Recompile this test version of the code and run it.

Make sure that the code doesn't crash.

Make sure that an NHK packet arrives detailing a constraint error, with package code 0x16, error 0xEC, Param1 0x1600, Param2 0x1600 and last progress the same as the last progress before where the code causing the exception was inserted. Eg if the divide by zero was inserted at line 50, and the last progress before that was 40, then the NHK packet should give the last progress as 40. Also make sure an hk packet arrives with debug first exception set to the same as nhk Param1 and debug first progress set to the same as nhk Param3.

| | Result | Expected result | Are result and expected result the same Y/N |
|--|--------|---|---|
| Code crashes Y/N | | N | |
| NHK packet arrives Y/N | | Y | |
| NHK pkg value | | 0x16 | |
| NHK err value | | 0xEC | |
| NHK Param1 value | | 0x1600 | |
| NHK Param2 value | | 0x1600 | |
| Last progress in code before error inserted | | Any value is permitted | |
| Last progress reached when running (ie NHK Param3 value) | | The same value as was written in for 'last progress in code before error inserted' | |
| HK iDebug1stEx value | | 0x1600 | |
| HK iDebug1stProg | | The same value as was | |
| value | | written in for 'last progress in code before error inserted' | |

If all the responses in column 4 of the table above are Y's then the test is successful.

Test Successful Y/N_____

7.11 HK change rate

Force an Ada exception by making a divide by zero error in HK.CHANGE_RATE. Recompile this test version of the code and run it – this may mean that after starting the code a command to change the housekeeping rate must be sent, eg /iHKRate Rate=11

Make sure that the code doesn't crash.

Make sure that an NHK packet arrives detailing a constraint error, with package code 0x23, error 0xEC, Param1 0x2314, Param2 0x2314 and last progress the same as the last progress before where the code causing the exception was inserted. Eg if the divide by zero was inserted at line 50, and the last progress before that was 40, then the NHK packet should give the last progress as 40. Also make sure an hk packet arrives with debug first exception set to the same as nhk Param1 and debug first progress set to the same as nhk Param3.

| | Result | Expected result | Are result and expected result the same Y/N |
|--|--------|---|---|
| Code crashes Y/N | | N | |
| NHK packet arrives Y/N | | Y | |
| NHK pkg value | | 0x23 | |
| NHK err value | | 0xEC | |
| NHK Param1 value | | 0x2314 | |
| NHK Param2 value | | 0x2314 | |
| Last progress in code | | Any value is permitted | |
| before error inserted | | | |
| Last progress reached when running (ie NHK Param3 value) | | The same value as was written in for 'last progress in code before error inserted' | |
| HK iDebug1stEx value | | 0x2314 | |
| HK iDebug1stProg | | The same value as was | |
| value | | written in for 'last | |
| | | progress in code before error inserted' | |

If all the responses in column 4 of the table above are Y's then the test is successful.

Test Successful Y/N_____

7.12 RTS type

Force an Ada exception by making a divide by zero error in RTS_TYPE Recompile this test version of the code and run it. *Make sure that the code doesn't crash. Make sure that an nhk packet arrives detailing a constraint error, with package code 0xDC, error 0xEC, Param1 0xDC14, Param2 0xDC14 and last progress the same as the last progress before where the code causing the exception was inserted. Eg if the divide by zero was inserted at line 50, and the last progress before that was 40, then the nhk packet should give the last progress as 40. Also make sure an hk packet arrives with*

debug first exception set to the same as nhk Param1 and debug first progress set to the same as nhk Param3.

| | Result | Expected result | Are result and expected result the same Y/N |
|--|--------|---|---|
| Code crashes Y/N | | N | |
| NHK packet arrives Y/N | | Y | |
| NHK pkg value | | 0xDC | |
| NHK err value | | 0xEC | |
| NHK Param1 value | | 0xDC14 | |
| NHK Param2 value | | 0xDC14 | |
| Last progress in code | | Any value is permitted | |
| before error inserted | | | |
| Last progress reached when running (ie NHK Param3 value) | | The same value as was written in for 'last progress in code before error inserted' | |
| HK iDebug1stEx value | | 0xDC14 | |
| HK iDebug1stProg | | The same value as was | |
| value | | written in for 'last | |
| | | progress in code before error inserted' | |

If all the responses in column 4 of the table above are Y's then the test is successful.

Test Successful Y/N_____

7.13 Perform ramp type

Force an Ada exception by making a divide by zero error in PERFORM_RAMP_TYPE Recompile this test version of the code and run it.

Make sure that the code doesn't crash.

Make sure that an nhk packet arrives detailing a constraint error, with package code 0xDA, error 0xEC, Param1 0xDA41, Param2 0xDA41 and last progress the same as the last progress before where the code causing the exception was inserted. Eg if the divide by zero was inserted at line 50, and the last progress before that was 40, then the nhk packet should give the last progress as 40. Also make sure an hk packet arrives with debug first exception set to the same as nhk Param1 and debug first progress set to the same as nhk Param3.

| | Result | Expected result | Are result and expected result the same Y/N |
|--|--------|---|---|
| Code crashes Y/N | | N | |
| NHK packet arrives Y/N | | Y | |
| NHK pkg value | | 0xDA | |
| NHK err value | | 0xEC | |
| NHK Param1 value | | 0xDA41 | |
| NHK Param2 value | | 0xDA41 | |
| Last progress in code | | Any value is permitted | |
| before error inserted | | | |
| Last progress reached when running (ie NHK Param3 value) | | The same value as was written in for 'last progress in code before error inserted' | |
| HK iDebug1stEx value | | 0xDA41 | |
| HK iDebug1stProg | | The same value as was | |
| value | | written in for 'last | |
| | | progress in code before error inserted' | |

If all the responses in column 4 of the table above are Y's then the test is successful.

Test Successful Y/N_____

7.14 Load centroid table task

Force an Ada exception by making a divide by zero error in LOAD_CENTROID_TABLE_TASK Recompile this test version of the code and run it.

Make sure that the code doesn't crash.

Make sure that an nhk packet arrives detailing a constraint error, with package code 0xDD, error 0xEC, Param1 0xDD0A, Param2 0xDD0A and last progress the same as the last progress before where the code causing the exception was inserted. Eg if the divide by zero was inserted at line 50, and the last progress before that was 40, then the nhk packet should give the last progress as 40. Also make sure an hk packet arrives with debug first exception set to the same as nhk Param1 and debug first progress set to the same as nhk Param3.

| | Result | Expected result | Are result and expected result the same Y/N |
|--|--------|---|---|
| Code crashes Y/N | | N | |
| NHK packet arrives Y/N | | Y | |
| NHK pkg value | | 0xDD | |
| NHK err value | | 0xEC | |
| NHK Param1 value | | 0xDD1E | |
| NHK Param2 value | | 0xDD1E | |
| Last progress in code before error inserted | | Any value is permitted | |
| Last progress reached when running (ie NHK Param3 value) | | The same value as was written in for 'last progress in code before error inserted' | |
| HK iDebug1stEx value | | 0xDD1E | |
| HK iDebug1stProg | | The same value as was | |
| value | | written in for 'last progress in code before error inserted' | |

If all the responses in column 4 of the table above are Y's then the test is successful.

Test Successful Y/N_____

7.15 Load window table task type

Force an Ada exception by making a divide by zero error in LOAD_WINDOW_TABLE_TASK_TYPE Recompile this test version of the code and run it.

Make sure that the code doesn't crash.

Make sure that an nhk packet arrives detailing a constraint error, with package code 0xDD, error 0xEC, Param1 0xDD0F, Param2 0xDD0F and last progress the same as the last progress before where the code causing the exception was inserted. Eg if the divide by zero was inserted at line 50, and the last progress before that was 40, then the nhk packet should give the last progress as 40. Also make sure an hk packet arrives with debug first exception set to the same as nhk Param1 and debug first progress set to the same as nhk Param3.

| | Result | Expected result | Are result and expected result the same Y/N |
|--|--------|---|---|
| Code crashes Y/N | | Ν | |
| NHK packet arrives Y/N | | Y | |
| NHK pkg value | | 0xDD | |
| NHK err value | | 0xEC | |
| NHK Param1 value | | 0xDD23 | |
| NHK Param2 value | | 0xDD23 | |
| Last progress in code before error inserted | | Any value is permitted | |
| Last progress reached when running (ie NHK Param3 value) | | The same value as was written in for 'last progress in code before error inserted' | |
| HK iDebug1stEx value | | 0xDD23 | |
| HK iDebug1stProg | | The same value as was | |
| value | | written in for 'last progress in code before error inserted' | |

If all the responses in column 4 of the table above are Y's then the test is successful.

Test Successful Y/N_____

7.16 SSI feed type

Force an Ada exception by making a divide by zero error in SSI_FEED_TYPE Recompile this test version of the code and run it.

Make sure that the code doesn't crash.

Make sure that an nhk packet arrives detailing a constraint error, with package code 0xD0, error 0xEC, Param1 0xD023, Param2 0xD023 and last progress the same as the last progress before where the code causing the exception was inserted. Eg if the divide by zero was inserted at line 50, and the last progress before that was 40, then the nhk packet should give the last progress as 40. Also make sure an hk packet arrives with debug first exception set to the same as nhk Param1 and debug first progress set to the same as nhk Param3.

| | Result | Expected result | Are result and expected result the same Y/N |
|--|--------|---|---|
| Code crashes Y/N | | N | |
| NHK packet arrives Y/N | | Y | |
| NHK pkg value | | 0xD0 | |
| NHK err value | | 0xEC | |
| NHK Param1 value | | 0xD028 | |
| NHK Param2 value | | 0xD028 | |
| Last progress in code before error inserted | | Any value is permitted | |
| Last progress reached when running (ie NHK Param3 value) | | The same value as was written in for 'last progress in code before error inserted' | |
| HK iDebug1stEx value | | 0xD028 | |
| HK iDebug1stProg | | The same value as was | |
| value | | written in for 'last progress in code before error inserted' | |

If all the responses in column 4 of the table above are Y's then the test is successful.

Test Successful Y/N_____

7.17 Starcat task

Force an Ada exception by making a divide by zero error in STARCAT_TASK Recompile this test version of the code and run it.

Make sure that the code doesn't crash.

Make sure that an nhk packet arrives detailing a constraint error, with package code 0xCA, error 0xEC, Param1 0xCA00, Param2 0xCA00 and last progress the same as the last progress before where the code causing the exception was inserted. Eg if the divide by zero was inserted at line 50, and the last progress before that was 40, then the nhk packet should give the last progress as 40. Also make sure an hk packet arrives with debug first exception set to the same as nhk Param1 and debug first progress set to the same as nhk Param3.

| | Result | Expected result | Are result and expected result the same Y/N |
|--|--------|---|---|
| Code crashes Y/N | | N | |
| NHK packet arrives Y/N | | Y | |
| NHK pkg value | | 0xCA | |
| NHK err value | | 0xEC | |
| NHK Param1 value | | 0xCA00 | |
| NHK Param2 value | | 0xCA00 | |
| Last progress in code before error inserted | | Any value is permitted | |
| Last progress reached when running (ie NHK Param3 value) | | The same value as was written in for 'last progress in code before error inserted' | |
| HK iDebug1stEx value | | 0xCA00 | |
| HK iDebug1stProg value | | The same value as was written in for 'last progress in code before error inserted' | |

If all the responses in column 4 of the table above are Y's then the test is successful.

Test Successful Y/N_____

7.18 Poll TC type

Force an Ada exception by making a divide by zero error in POLL_TC_TYPE Recompile this test version of the code and run it.

Make sure that the code doesn't crash.

Make sure that an nhk packet arrives detailing a constraint error, with package code 0x2C, error 0xEC, Param1 0x2C0F, Param2 0x2C0F and last progress the same as the last progress before where the code causing the exception was inserted. Eg if the divide by zero was inserted at line 50, and the last progress before that was 40, then the nhk packet should give the last progress as 40. Also make sure an hk packet arrives with debug first exception set to the same as nhk Param1 and debug first progress set to the same as nhk Param3.

| | Result | Expected result | Are result and expected result the same Y/N |
|--|--------|---|---|
| Code crashes Y/N | | N | |
| NHK packet arrives Y/N | | Y | |
| NHK pkg value | | 0x2C | |
| NHK err value | | 0xEC | |
| NHK Param1 value | | 0x2C0F | |
| NHK Param2 value | | 0x2C0F | |
| Last progress in code before error inserted | | Any value is permitted | |
| Last progress reached when running (ie NHK Param3 value) | | The same value as was written in for 'last progress in code before error inserted' | |
| HK iDebug1stEx value | | 0x2C0F | |
| HK iDebug1stProg value | | The same value as was written in for 'last progress in code before error inserted' | |

If all the responses in column 4 of the table above are Y's then the test is successful.

Test Successful Y/N_____

8. PACKETS AND MESSAGES NOT COVERED ELSEWHERE

This section will force examples of all possible packets that have not already been covered in this test.

8.1 Reboot

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Check on the housekeeping display that Boot Status is set to 'Cmd'

Boot Status Cmd Y/N_____

To aid checking that the safety circuit resets correctly after reboot, load unusual values into it now, and write them down here

Trip the watchdog.

Check on the NHK display that an 'ICU Watchdog Trip' message has been received.

'ICU Watchdog Trip' received Y/N_____

Check on the housekeeping display that Boot Status is set to 'Wdog'

Boot Status Wdog Y/N_____

Check on the boot display that the boot report has been received.

'Boot Report' received Y/N_____

Check that the safety circuit values have been reset to nominal

Safety circuit values nominal Y/N_____

If all the above responses are Y's then the test is successful.

Test Successful

8.2 Memory dump

Switch off the housekeeping and open a packet dump window with the commands /iHK Off Pktdump

Send the command below to force a memory dump TDRSS report /iICUDump Mid=5, Offset=0x1412, Numbytes=1, APID=0x3C2

Check in the packet dump window that a packet with APID 0x3C2 appears, with value 0x9F15.

Value 0x9F15 appears Y/N_____

Send the command below to force a memory dump ST report /iICUDump Mid=5, Offset=0x1412, Numbytes=1, APID=0x450

Check in the packet dump window that a packet with APID 0x450 appears, with value 0x9F15.

Value 0x9F15 appears Y/N_____

Send the command below to force a memory CRC TDRSS report /iICUCRC Mid=5, Offset=0, Numbytes=0x1413, APID=0x3C3

Check in the packet dump window that a packet with APID 0x3C3 appears, with value 0.

Value 0 appears Y/N_____

Send the command below to force a memory CRC ST report /iICUCRC Mid=5, Offset=0, Numbytes=0x1413, APID=0x451

Check in the packet dump window that a packet with APID 0x451 appears, with value 0.

Value 0 appears Y/N_____

Switch the housekeeping back on with /iHK \mbox{On}

If all the above responses are Y's then the test is successful.

Test Successful

8.3 Table loads

Make sure that the telescope simulator display is enabled.

Send the commands

/iBPEStartCntrdLd Verify=Off, Force=1, x0=-1000, x1=-750, x2=-500, x3=-250, x4=0, x5=250, x6=500, x7=750, x8=1000, y0=-1000, y1=-750, y2=-500, y3=-250, y4=0, y5=250, y6=500, y7=750, y8=1000 /iBPEStopCntrdLd

Check on the NHK display that a 'Centroid Table Load Aborted' message has been received.

'Centroid Table Load Aborted' received Y/N

Send the commands

```
/iBPEStartWndwLd Verify=Off, Force=1, NWdw=1, xLow1=0,
yLow1=1, xSize1=255, ySize1=255
/iBPEStopWndwLd
```

Check on the NHK display that a 'Window Table Load Aborted' message has been received.

'Window Table Load Aborted' received Y/N _____

```
Send the following command, which is unsupported by the BPE simulator
/iBPEStartCntrdLd Verify=On, Force=1, x0=-1000, x1=-750,
x2=-500, x3=-250, x4=0, x5=250, x6=500, x7=750, x8=1000,
y0=-1000, y1=-750, y2=-500, y3=-250, y4=0, y5=250, y6=500,
y7=750, y8=1000
```

Check on the NHK display that a 'Centroid Table Load Failure' message has been received.

'Centroid Table Load Failure' received Y/N

Send the following command, which is unsupported by the BPE simulator /iBPEStartWndwLd Verify=Off, Force=1, NWdw=1, xLow1=0, yLow1=1, xSize1=255, ySize1=255

Check on the NHK display that a 'Window Table Load Failure' message has been received.

'Window Table Load Failure' received Y/N

Check on the housekeeping display that the centroid load task is asleep and its counter is not increasing.

Centroid Load task is asleep Y/N_____ Centroid Load Task counter is unchanging Y/N_____

```
Send the following commands, which only differ in the force parameter
/iBPEStartCntrdLd Verify=Off, Force=1, x0=-1000, x1=-750,
x2=-500, x3=-250, x4=0, x5=250, x6=500, x7=750, x8=1000,
y0=-1000, y1=-750, y2=-500, y3=-250, y4=0, y5=250, y6=500,
y7=750, y8=1000
/iBPEStartCntrdLd Verify=Off, Force=0, x0=-1000, x1=-750,
x2=-500, x3=-250, x4=0, x5=250, x6=500, x7=750, x8=1000,
y0=-1000, y1=-750, y2=-500, y3=-250, y4=0, y5=250, y6=500,
y7=750, y8=1000
```

While the first command is running check on the housekeeping display that the window load task is alive and its counter is increasing, and on the telescope simulator display that the standard fan shaped display is created.

Centroid Load task is alive Y/N_____ Centroid Load Task counter is increasing Y/N_____ Fan shaped display showing Y/N______

Check on the NHK display that a 'Centroid Table Already Loaded' message has been received.

'Centroid Table Already Loaded' received Y/N

```
Send the following commands, which only differ in the force parameter
/iBPEStartWndwLd Verify=Off, Force=1, NWdw=1, xLow1=0,
yLow1=1, xSize1=255, ySize1=255
/iBPEStartWndwLd Verify=Off, Force=0, NWdw=1, xLow1=0,
yLow1=1, xSize1=255, ySize1=255
```

While the first command is running check on the telescope simulator display that the standard square shaped display is created.

Square shaped display showing Y/N_____

Check on the NHK display that a 'Window Table Already Loaded' message has been received.

'Window Table Already Loaded' received Y/N _____

If all the above responses are Y's then the test is successful.

Test Successful

8.4 Verification errors

Note the value of the TM Bad counter on the housekeeping display here_____

Edit the code to force out a packet with incorrect checksum 0xFFFF. Compile this test version of the code and run it.

Check on the verification display that the message 'Incorrect Checksum' is received, and on the housekeeping display that the TM Bad counter increments by 1.

'Incorrect Checksum' received Y/N_____ TM Bad increments by 1 Y/N_____

Edit the code to force out a packet with incorrect APID 0x7FF. Compile this test version of the code and run it.

Check on the verification display that the message 'Illegal APID' is received.

'Illegal APID' received Y/N_____

Note the value of the TC Bad counter on the housekeeping display here_____

Send the command below, which has an illegal function code /iBad660

Check on the verification display that the message 'Illegal Function Code' is received, and on the housekeeping display that the TC Bad counter increments by 1.

'Illegal Function Code' received Y/N_____ TC Bad increments by 1 Y/N_____

Edit the code to force out a packet with incorrect length 0xFFFF. Compile this test version of the code and run it.

Check on the verification display that the message 'Invalid Length' is received.

'Invalid Length' received Y/N_____

Disable range checking on the iState command in ITOS.

Send the command below, which has an illegal state number /iState State=20

Check on the verification display that the message 'Illegal State' is received.

'Illegal State' received Y/N_____

Re-enable range checking on the iState command in ITOS.

Disable range checking on the iICUDump command in ITOS.

Send the command below, which has an illegal Mid /iICUDump Mid=9, Offset=0, Numbytes=1, APID=0x390

Check on the verification display that the message 'Illegal Mid' is received.

'Illegal Mid' received Y/N_____

Send the command below, which has an illegal start address /iICUDump Mid=1, Offset=0xFFFFFFF, Numbytes=1, APID=0x390

Check on the verification display that the message 'Illegal Start Address' is received.

'Illegal Start Address' received Y/N_____

Send the command below, which has an illegal dump APID /iICUDump Mid=1, Offset=0, Numbytes=1, APID=0x38F

Check on the verification display that the message 'Illegal Memory APID' is received.

'Illegal Memory APID' received Y/N_____

Re-enable range checking on the iICUDump command in ITOS.

Edit the code to force out a packet with illegal APID length 0xFFFF. Compile this test version of the code and run it.

Check on the verification display that the message 'Illegal APID Length' is received.

'Illegal APID Length' received Y/N_____

Note the value of the RT-RT Bad counter on the housekeeping display here_____

Edit the code to force out a FONEXTOBSINFO message with an incorrect checksum. Compile this test version of the code and run it.

Check on the housekeeping display that the TM Bad counter increments by 1.

RT-RT Bad increments by 1 Y/N_____

If all the above responses are Y's then the test is successful.

Test Successful

8.5 TDRSS

First make sure that the debug screen is not active – if it is press key 'q' while on the debug screen. Also make sure that the TDRSS display is up - use 'seqprt TDRSS' if not.

```
Force a watchdog reset.using
/iWatchdogInt ResetInterval=100, TaskCheckFreq=3,
TaskCheckMask=0xFFFF
```

Check on the TDRSS display that a 'TDRSS Emergency Report' message has been received.

'TDRSS Emergency Report' received Y/N_____

```
Load a heater control table with bad data into EEPROM and make sure it is seen using
load "heaterbl.img"
load "heaterb2.img"
/iHtr Enable=Off
/iHtr Enable=On
```

Check on the TDRSS display that a 'Bad EEPROM Data' message has been received.

'Bad EEPROM Data' received Y/N_____

Reset the heater table using

load "heater1.img"
load "heater2.img"
/iHtr Enable=Off
/iHtr Enable=On

If all the above responses are Y's then the test is successful.

Test Successful

8.6 State Changes

Alter the state transition table to allow but have no RTS defined for a given transition and upload this test version, then reload the flight code using load "???.img" load icu.hex

Command the altered state transition using /iState State=???

Check on the NHK display that a 'Forbidden State RTS' message has been received.

'Forbidden State RTS' received Y/N _____

Reload the original state transition table and flight code using load "???.img" load icu.hex

Check that the ICU is in the safe state

ICU safe Y/N_____

Command a disallowed state transition using /iState State=AT

Check on the NHK display that an 'Impossible State Transition' message has been received.

'Impossible State Transition' received Y/N _____

Run the ITOS script getnoconfig.proc using Start getnoconfig

Check on the NHK display that a 'No Such PT UVOT Mode' message has been received.

'No Such PT UVOT Mode' received Y/N

Run the ITOS script getnouvotmode.proc using Start getnouvotmode

Check on the NHK display that a 'No Such AT UVOT Mode' message has been received.

'No Such AT UVOT Mode' received Y/N _____

If all the above responses are Y's then the test is successful.

Test Successful

8.7 SC1553

Edit the code to force out an 'SC1553 Startup Error' NHK message, and run this test code.

'SC1553 Startup Error' received Y/N_____

Edit the code to force out an 'SC1553 Read Error' NHK message, and run this test code.

'SC1553 Read Error' received Y/N_____

Edit the code to force out an 'SC1553 Dump Report SID' NHK message, and run this test code.

'SC1553 Dump Report SID' received Y/N_____

Edit the code to force out an 'SC1553 Error Report' NHK message, and run this test code.

'SC1553 Error Report' received Y/N_____

If all the responses above are Y's then the test is successful.

Test Successful Y/N_____

8.8 SSI

Edit the code to force out an 'SSI Error' NHK message, and run this test code.

'SSI Error' received Y/N_____

If all the responses above are Y's then the test is successful.

Test Successful Y/N_____

8.9 EEPROM

Edit the code to force out an 'EEPROM Write Error' NHK message, and run this test code.

'EEPROM Write Error' received Y/N_____

Edit the code to force out an 'EEPROM Code Compare Error' NHK message, and run this test code.

'EEPROM Code Compare Error' received Y/N_____

Edit the code to force out an 'EEPROM Star Cat Compare Error' NHK message, and run this test code.

'EEPROM Star Cat Compare Error' received Y/N_____

If all the responses above are Y's then the test is successful.

Test Successful Y/N_____

9. COMMANDS NOT COVERED ELSEWHERE

9.1 Table loads

Send the commands

- 1. /iBPEStartCntrdLd Verify=Off, Force=1, x0=-1000, x1=750, x2=-500, x3=-250, x4=0, x5=500, x6=250, x7=750,
 x8=1000, y0=-1000, y1=-750, y2=-500, y3=-250, y4=0,
 y5=250, y6=500, y7=750, y8=1000
- 2. /iBPEStartCntrdLd Verify=Off, Force=1, x0=-1000, x1=-750, x2=-500, x3=-250, x4=0, x5=250, x6=500, x7=750, x8=1000, y0=-1000, y1=-750, y2=-500, y3=-250, y4=0, y5=250, y6=750, y7=500, y8=1000
- 3. /iBPEStartCntrdLd Verify=Off, Force=1, x0=-900, x1=-750, x2=-500, x3=-250, x4=0, x5=250, x6=500, x7=750, x8=1000, y0=-1000, y1=-750, y2=-500, y3=-250, y4=0, y5=250, y6=500, y7=750, y8=1000
- 4. /iBPEStartCntrdLd Verify=Off, Force=1, x0=-1000, x1=750, x2=-500, x3=-250, x4=0, x5=250, x6=500, x7=750,
 x8=1000, y0=-900, y1=-750, y2=-500, y3=-250, y4=0,
 y5=250, y6=500, y7=750, y8=1000
- 5. /iBPEStartCntrdLd Verify=Off, Force=1, x0=-1000, x1=750, x2=-500, x3=-250, x4=0, x5=250, x6=500, x7=750,
 x8=900, y0=-1000, y1=-750, y2=-500, y3=-250, y4=0,
 y5=250, y6=500, y7=750, y8=1000
- 6. /iBPEStartCntrdLd Verify=Off, Force=1, x0=-1000, x1=750, x2=-500, x3=-250, x4=0, x5=250, x6=500, x7=750,
 x8=1000, y0=-1000, y1=-750, y2=-500, y3=-250, y4=0,
 y5=250, y6=500, y7=750, y8=900
- 7. /iBPEStartCntrdLd Verify=Off, Force=1, x0=-1000, x1=-750, x2=-1500, x3=-250, x4=0, x5=250, x6=500, x7=750, x8=1000, y0=-1000, y1=-750, y2=-500, y3=-250, y4=0, y5=250, y6=500, y7=750, y8=1000
- 8. /iBPEStartCntrdLd Verify=Off, Force=1, x0=-1000, x1=750, x2=-500, x3=-250, x4=1500, x5=250, x6=500,
 x7=750, x8=1000, y0=-1000, y1=-750, y2=-500, y3=-250,
 y4=0, y5=250, y6=500, y7=750, y8=1000
- 9. /iBPEStartCntrdLd Verify=Off, Force=1, x0=-1000, x1=750, x2=-500, x3=-250, x4=0, x5=250, x6=500, x7=750,
 x8=1000, y0=-1000, y1=-1500, y2=-500, y3=-250, y4=0,
 y5=250, y6=500, y7=750, y8=1000
- 10. /iBPEStartCntrdLd Verify=Off, Force=1, x0=-1000, x1=-750, x2=-500, x3=-250, x4=0, x5=250, x6=500, x7=750, x8=1000, y0=-1000, y1=-750, y2=-500, y3=-250, y4=0, y5=1500, y6=500, y7=750, y8=1000

Check that in each case an 'Illegal Parameter Values' NHK message is received.

| For command 1, 'Illegal Parameter Values' received Y/N |
|---|
| For command 2, 'Illegal Parameter Values' received Y/N |
| For command 3, 'Illegal Parameter Values' received Y/N |
| For command 4, 'Illegal Parameter Values' received Y/N |
| For command 5, 'Illegal Parameter Values' received Y/N |
| For command 6, 'Illegal Parameter Values' received Y/N |
| For command 7, 'Illegal Parameter Values' received Y/N |
| For command 8, 'Illegal Parameter Values' received Y/N |
| For command 9, 'Illegal Parameter Values' received Y/N |
| For command 10, 'Illegal Parameter Values' received Y/N |

Check on the housekeeping display that the window load task is asleep and its counter is not increasing.

Window Load task is asleep Y/N_____ Window Load Task counter is unchanging Y/N_____

Send the command

```
/iBPEStartWndwLd Verify=Off, Force=1, NWdw=6, xLow1=10,
yLow1=9, xSize1=20, ySize1=20, xLow2=100, yLow2=9,
xSize2=20, ySize2=20, xLow3=200, yLow3=9, xSize3=20,
ySize3=20, xLow4=10, yLow4=109, xSize4=20, ySize4=20,
xLow5=100, yLow5=109, xSize5=20, ySize5=20, xLow6=200,
yLow6=109, xSize6=20, ySize6=20
```

While the load is running, check on the housekeeping display that the window load task is alive and its counter is increasing.

Window Load task is alive Y/N_____ Window Load Task counter is increasing Y/N_____

Check that a 'Successful Acceptance' verification message is received.

'Successful Acceptance' received Y/N_____

Send the commands

1. /iBPEStartWndwLd Verify=Off, Force=1, NWdw=7, xLow1=10, yLow1=9, xSize1=20, ySize1=20, xLow2=100, yLow2=9, xSize2=20, ySize2=20, xLow3=200, yLow3=9, xSize3=20, ySize3=20, xLow4=10, yLow4=109, xSize4=20, ySize4=20, xLow5=100, yLow5=109, xSize5=20, ySize5=20, xLow6=200, yLow6=109, xSize6=20, ySize6=20

- 2. /iBPEStartWndwLd Verify=Off, Force=1, NWdw=6, xLow1=5, yLow1=9, xSize1=20, ySize1=20, xLow2=100, yLow2=9, xSize2=20, ySize2=20, xLow3=200, yLow3=9, xSize3=20, ySize3=20, xLow4=10, yLow4=109, xSize4=20, ySize4=20, xLow5=100, yLow5=109, xSize5=20, ySize5=20, xLow6=200, yLow6=109, xSize6=20, ySize6=20
- 3. /iBPEStartWndwLd Verify=Off, Force=1, NWdw=6, xLow1=10, yLow1=8, xSize1=20, ySize1=20, xLow2=100, yLow2=9, xSize2=20, ySize2=20, xLow3=200, yLow3=9, xSize3=20, ySize3=20, xLow4=10, yLow4=109, xSize4=20, ySize4=20, xLow5=100, yLow5=109, xSize5=20, ySize5=20, xLow6=200, yLow6=109, xSize6=20, ySize6=20
- 4. /iBPEStartWndwLd Verify=Off, Force=1, NWdw=6, xLow1=10, yLow1=9, xSize1=20, ySize1=20, xLow2=100, yLow2=9, xSize2=1, ySize2=20, xLow3=200, yLow3=9, xSize3=20, ySize3=20, xLow4=10, yLow4=109, xSize4=20, ySize4=20, xLow5=100, yLow5=109, xSize5=20, ySize5=20, xLow6=200, yLow6=109, xSize6=20, ySize6=20
- 5. /iBPEStartWndwLd Verify=Off, Force=1, NWdw=6, xLow1=10, yLow1=9, xSize1=20, ySize1=20, xLow2=100, yLow2=9, xSize2=20, ySize2=20, xLow3=200, yLow3=9, xSize3=20, ySize3=1, xLow4=10, yLow4=109, xSize4=20, ySize4=20, xLow5=100, yLow5=109, xSize5=20, ySize5=20, xLow6=200, yLow6=109, xSize6=20, ySize6=20
- 6. /iBPEStartWndwLd Verify=Off, Force=1, NWdw=6, xLow1=10, yLow1=9, xSize1=20, ySize1=20, xLow2=100, yLow2=9, xSize2=20, ySize2=20, xLow3=200, yLow3=9, xSize3=20, ySize3=20, xLow4=10, yLow4=109, xSize4=257, ySize4=20, xLow5=100, yLow5=109, xSize5=20, ySize5=20, xLow6=200, yLow6=109, xSize6=20, ySize6=20
- 7. /iBPEStartWndwLd Verify=Off, Force=1, NWdw=6, xLow1=10, yLow1=9, xSize1=20, ySize1=20, xLow2=100, yLow2=9, xSize2=20, ySize2=20, xLow3=200, yLow3=9, xSize3=20, ySize3=20, xLow4=10, yLow4=109, xSize4=20, ySize4=20, xLow5=100, yLow5=109, xSize5=20, ySize5=257, xLow6=200, yLow6=109, xSize6=20, ySize6=20
- 8. /iBPEStartWndwLd Verify=Off, Force=1, NWdw=6, xLow1=10, yLow1=9, xSize1=20, ySize1=20, xLow2=100, yLow2=9, xSize2=20, ySize2=20, xLow3=200, yLow3=9, xSize3=20, ySize3=20, xLow4=10, yLow4=109, xSize4=20, ySize4=20, xLow5=100, yLow5=109, xSize5=20, ySize5=20, xLow6=0, yLow6=109, xSize6=1, ySize6=20
- 9. /iBPEStartWndwLd Verify=Off, Force=1, NWdw=6, xLow1=10, yLow1=9, xSize1=20, ySize1=20, xLow2=100, yLow2=9, xSize2=20, ySize2=20, xLow3=200, yLow3=9, xSize3=20, ySize3=20, xLow4=10, yLow4=109, xSize4=20,

ySize4=20, xLow5=100, yLow5=109, xSize5=20, ySize5=20, xLow6=200, yLow6=1, xSize6=20, ySize6=0 10. /iBPEStartWndwLd Verify=Off, Force=1, NWdw=6, xLow1=10, yLow1=9, xSize1=256, ySize1=20, xLow2=100, yLow2=9, xSize2=20, ySize2=20, xLow3=200, yLow3=9, xSize3=20, ySize3=20, xLow4=10, yLow4=109, xSize4=20, ySize4=20, xLow5=100, yLow5=109, xSize5=20, ySize5=20, xLow6=200, yLow6=109, xSize6=20, ySize6=20 11. /iBPEStartWndwLd Verify=Off, Force=1, NWdw=6, xLow1=10, yLow1=9, xSize1=20, ySize1=20, xLow2=100, yLow2=9, xSize2=20, ySize2=256, xLow3=200, yLow3=9, xSize3=20, ySize3=20, xLow4=10, yLow4=109, xSize4=20, ySize4=20, xLow5=100, yLow5=109, xSize5=20, ySize5=20, xLow6=200, yLow6=109, xSize6=20, ySize6=20

Check that in each case an 'Illegal Parameter Values' NHK message is received.

For command 1, 'Illegal Parameter Values' received Y/N______For command 2, 'Illegal Parameter Values' received Y/N______For command 3, 'Illegal Parameter Values' received Y/N______For command 4, 'Illegal Parameter Values' received Y/N______For command 5, 'Illegal Parameter Values' received Y/N______For command 6, 'Illegal Parameter Values' received Y/N______For command 7, 'Illegal Parameter Values' received Y/N______For command 8, 'Illegal Parameter Values' received Y/N______For command 9, 'Illegal Parameter Values' received Y/N______For command 10, 'Illegal Parameter Values' received Y/N______For command 11, 'Illegal Parameter Values' received Y/N______

If all the above responses are Y's then the test is successful.

Test Successful

9.2 BPE Commands

Send the commands /iBPEAcqMode AcqMode=0 /iBPEAcqMode AcqMode=7 /iBPEAcqMode AcqMode=8

In the first two cases check on the housekeeping display that the values are as commanded. In the third case check that an NHK 'Illegal Parameter Values' message is received.

For AcqMode=0, display shows 0 Y/N_____ For AcqMode=7, display shows 7 Y/N_____ For AcqMode=8, 'Illegal Parameter Values' received Y/N_____

Send the commands /iBPEThreshold Threshold=0 /iBPEThreshold Threshold=255 /iBPEThreshold Threshold=256

In the first two cases check on the housekeeping display that the values are as commanded. In the third case check that an NHK 'Illegal Parameter Values' message is received.

For Threshold=0, display shows 0 Y/N_____ For Threshold=255, display shows 255 Y/N_____ For Threshold=256, 'Illegal Parameter Values' received Y/N_____

Send the commands /iBPEInteg Enable=On /iBPEInteg Enable=Off

For each command check on the housekeeping display that the value is as commanded.

BPE integration enabled Y/N_____ BPE integration disabled Y/N_____

Send the commands /iBPEFrameTags Enable=On /iBPEFrameTags Enable=Off

For each command check on the housekeeping display that the value is as commanded.

BPE frame tags enabled Y/N_____

BPE frame tags disabled Y/N_____

Send the commands

/iBPECamera Enable=On /iBPECamera Enable=Off

For each command check on the housekeeping display that the value is as commanded.

BPE camera enabled Y/N_____ BPE camera disabled Y/N_____

If all the above responses are Y's then the test is successful.

Test Successful

9.3 ICB commands using ICB slave

Attach the ICB slave to the MACSbus before running this test.

Before enabling direct ICB commands send these commands /iICBWrite Address=0x7, SubAddress=0, Datum=0x1234 /iICBRead Address=0x7, SubAddress=0x0

Check that an 'unsuccessful acceptance' verification message was received, and also an NHK 'illegal function code' message.

'Successful acceptance' received Y/N______ 'Illegal function code' received Y/N______

Open a packet dump window using Pktdump vc0 0x3B0

Enable direct ICB commands using /iICBEnable On

Send the commands

/iICBRead Address=0x18, SubAddress=0
 /iICBRead Address=0x7, SubAddress=0x31
 /iICBRead Address=0x18, SubAddress=0x32
 /iICBRead Address=0x11, SubAddress=0

In the first two cases check that a 'successful acceptance' verification message was received, and that a task management report packet appears in the packet dump window. In the latter two cases check that an 'Illegal Parameter Values' NHK message was received.

For command 1, 'Successful Acceptance' received Y/N_____ And task management report packet received Y/N_____ For command 2, 'Successful Acceptance' received Y/N_____ And task management report packet received Y/N_____ For command 3, 'Illegal Parameter Values' received Y/N_____ For command 4, 'Illegal Parameter Values' received Y/N_____

Send the commands

```
    /iICBWrite Address=0x18, SubAddress=0, Datum=0x1234
    /iICBWrite Address=0x7, SubAddress=0x31, Datum=0x1234
    /iICBWrite Address=0x18, SubAddress=0x32, Datum=0x1234
    /iICBWrite Address=0x11, SubAddress=0, Datum=0x1234
```

In the first two cases check that a 'successful acceptance' verification message was received. In the latter three cases check that an 'Illegal Parameter Values' NHK message was received.

For command 1, 'Successful Acceptance' received Y/N_____ For command 2, 'Successful Acceptance' received Y/N_____ For command 3, 'Illegal Parameter Values' received Y/N_____ For command 4, 'Illegal Parameter Values' received Y/N_____

Disable direct ICB commands using /iICBEnable Off

Check on the housekeeping display that the ICB is alive.

ICB Alive Y/N_____

From the housekeeping display write down the following;

| ICB Errors | |
|----------------|--|
| ICB Status | |
| ICB Err Datum | |
| ICB Err Cmd Wd | |

Disconnect the ICB slave.

Disconnect the ICB itself.

Check on the housekeeping display that the ICB is dead.

ICB Dead Y/N_____

Enable direct ICB commands and try to write to the ICB using
/iICBEnable On
/iICBWrite Address=7, SubAddress=0, Datum=0x1234

Check on the housekeeping display that the following have changed;

ICB Errors changed Y/N_____ ICB Status changed Y/N_____ ICB Err Datum changed Y/N_____ ICB Err Cmd Wd changed Y/N_____

Check on the NHK display that an 'ICB Error' message has been received, followed by a 'Heater ICB Shutdown' message.

'ICB Error' received Y/N _____ 'Heater ICB Shutdown' received Y/N _____

Disable direct ICB commands using /iICBEnable Off

Now perform a crash test. Edit the code to simulate ICB values of 0 to 0xFFFF in a loop repeatedly for 2 days. Make sure that no ICB errors or crashes occur.

ICB error/crash occurs Y/N_____

If all the above responses except the last are Y's and the last is a N then the test is successful.

Test Successful

9.4 State commands

Load a dummy state transition table in which the action for each commanded state transition is no-op, using Load "???.img"

Send the commands

1. /iState State=0 2. /iState State=1 3. /iState State=2 4. /iState State=3 5. /iState State=4 6. /iState State=5 7. /iState State=6 8. /iState State=7 9. /iState State=8 10. /iState State=9 11. /iState State=10 12. /iState State=11 13. /iState State=12

Check that in each case except the last a response is issued – this could be that the state transition is allowed or disallowed, it doesn't matter which. Check that in the last case an 'Illegal Parameter Values' NHK message is received.

For command 1, response made Y/N______ For command 2, response made Y/N______ For command 3, response made Y/N______ For command 4, response made Y/N______ For command 5, response made Y/N______ For command 6, response made Y/N______ For command 7, response made Y/N______ For command 8, response made Y/N______ For command 9, response made Y/N______ For command 10, response made Y/N______ For command 11, response made Y/N______ For command 12, response made Y/N______ For command 13, 'Illegal Parameter Values' received Y/N______

Reload the good state transition table, using Load "???.img"

Go to the idle state using /iState State=Idle

Send the command
/iStateTrans Enable=Off, ATEnable=On, PTEnable=On,
SPEnable=On

Command a safepointing by running ITOS script safepoint.proc using Start safepoint

Check that nothing happens

Nothing happens Y/N_____

Send the command
/iStateTrans Enable=Off, ATEnable=Off, PTEnable=Off,
SPEnable=Off

Command a safepointing by running ITOS script safepoint.proc using Start safepoint

Check that nothing happens

Nothing happens Y/N_____

Send the command
/iStateTrans Enable=On, ATEnable=Off, PTEnable=Off,
SPEnable=On

Command a safepointing by running ITOS script safepoint.proc using Start safepoint

Check that the UVOT state transitions to safepointing

UVOT safepointing Y/N_____

```
Send the command
/iStateTrans Enable=On, ATEnable=On, PTEnable=Off,
SPEnable=Off
```

 $\begin{array}{l} Command \mbox{ an AT by running ITOS script firstat.proc using } \\ {\tt Start firstat} \end{array}$

Check that the UVOT state transitions to AT

UVOT in AT Y/N_____

Command a PT by running ITOS script pt.proc using

Start pt

Check that nothing happens

Nothing happens Y/N_____

Send the command
/iStateTrans Enable=On, ATEnable=Off, PTEnable=On,
SPEnable=Off

Command a PT by running ITOS script pt.proc using Start $\ensuremath{\text{pt}}$

Check that the UVOT state transitions to PT

UVOT in PT Y/N_____

Check that nothing happens

Nothing happens Y/N_____

If all the above responses are Y's then the test is successful.

Test Successful

9.5 NHK Echo

Note here the values from the housekeeping display of TM Good_____

Send the commands

| 1. | /iNHKEcho TMAPID=0x360, PackageNo=256, ErrorCode=0, |
|----------|--|
| | Param1=0, Param2=0, Param3=0 |
| 2. | /iNHKEcho TMAPID=0x451, PackageNo=65535, |
| | ErrorCode=255, Param1=0xFFFF, Param2=0xFFFF, |
| | Param3=0xFFFF |
| 3. | /iNHKEcho TMAPID=0x35F, PackageNo=256, ErrorCode=0, |
| | Param1=0, Param2=0, Param3=0 |
| 4. | /iNHKEcho TMAPID=0x452, PackageNo=256, ErrorCode=0, |
| | Param1=0, Param2=0, Param3=0 |
| 5. | /iNHKEcho TMAPID=0x360, PackageNo=255, ErrorCode=0, |
| | Param1=0, Param2=0, Param3=0 |
| C | |
| 6. | /iNHKEcho TMAPID=0x360, PackageNo=65536, |
| б. | <pre>/INHKECHO IMAPID=0x360, PackageNo=65536, ErrorCode=0, Param1=0, Param2=0, Param3=0</pre> |
| ь. 7. | |
| | ErrorCode=0, Param1=0, Param2=0, Param3=0 |
| | ErrorCode=0, Param1=0, Param2=0, Param3=0 /iNHKEcho TMAPID=0x360, PackageNo=256, |
| 7. | ErrorCode=0, Param1=0, Param2=0, Param3=0 /iNHKEcho TMAPID=0x360, PackageNo=256, ErrorCode=256, Param1=0, Param2=0, Param3=0 |
| 7. | ErrorCode=0, Param1=0, Param2=0, Param3=0 /iNHKEcho TMAPID=0x360, PackageNo=256, ErrorCode=256, Param1=0, Param2=0, Param3=0 /iNHKEcho TMAPID=0x360, PackageNo=256, ErrorCode=0, |
| 7. 8. | <pre>ErrorCode=0, Param1=0, Param2=0, Param3=0 /iNHKEcho TMAPID=0x360, PackageNo=256, ErrorCode=256, Param1=0, Param2=0, Param3=0 /iNHKEcho TMAPID=0x360, PackageNo=256, ErrorCode=0, Param1=0xFFFFF, Param2=0, Param3=0</pre> |

For the first two cases, check that the NHK display shows the echoed command. For the rest, check that an 'Illegal Parameter Values' NHK message is received. Also, after the first command check that the TM Good counter has incremented by 1.

| For command 1, command correctly echoed Y/N | | | | |
|---|--|--|--|--|
| TM Good incremented by 1 Y/N | | | | |
| For command 2, command correctly echoed Y/N | | | | |
| For command 3, 'Illegal Parameter values' received Y/N | | | | |
| For command 4, 'Illegal Parameter values' received Y/N | | | | |
| For command 5, 'Illegal Parameter values' received Y/N | | | | |
| For command 6, 'Illegal Parameter values' received Y/N | | | | |
| For command 7, 'Illegal Parameter values' received Y/N | | | | |
| For command 8, 'Illegal Parameter values' received Y/N | | | | |
| For command 9, 'Illegal Parameter values' received Y/N | | | | |
| For command 10, 'Illegal Parameter values' received Y/N | | | | |

Param1=0, Param2=0, Param3=0xFFFFF

If all the above responses are Y's then the test is successful.

Test Successful

9.6 Watchdog

Send the commands

- 1. /iWatchdogInt ResetInterval=1, TaskCheckFreq=1, TaskCheckMask=1
- 2. /iWatchdogInt ResetInterval=65535, TaskCheckFreq=65535, TaskCheckMask=1
- 3. /iWatchdogInt ResetInterval=0, TaskCheckFreq=1, TaskCheckMask=1
- 4. /iWatchdogInt ResetInterval=1, TaskCheckFreq=0, TaskCheckMask=1

For the first two, check that a 'Successful Acceptance' message is received. For the latter two, check on the verification display that the message 'Unsuccessful Acceptance' is received.

For command 1, 'Successful Acceptance' received Y/N_____ For command 2, 'Successful Acceptance' received Y/N_____ For command 3, 'Unsuccessful Acceptance' received Y/N_____ For command 4, 'Unsuccessful Acceptance' received Y/N_____

Then command it back to defaults using

/iWatchdogInt ResetInterval=1, TaskCheckFreq=0, TaskCheckMask=1

Send the following commands, with a 2 minute wait between each

/iWatchdog On /iWatchdog Off /iWatchdog Off /iWatchdog On /iWatchdog On

Check on the housekeeping display that the watchdog task is first enabled, then disabled, then stays disabled, then is re-enabled and finally stays enabled.

| Watchdog enabled Y/N | _ |
|-----------------------------|---|
| Watchdog disabled Y/N | |
| Watchdog stays disabled Y/N | |
| Watchdog re-enabled Y/N | |
| Watchdog stays enabled Y/N | |

Edit the code to change the watchdog kick period to be 20% longer, ie 4.8s. Run this test code and leave it running overnight.

Check that no watchdog reset occurs. *No bootstrap record should appear.*

Bootstrap record appears Y/N_____

If all bar the last of the above responses are Y's and the last is a N then the test is successful.

Test Successful

9.7 Test

Make a note of TC Good from the housekeeping display _____

Send the command /iTest

Check on the verification display that a 'Successful Acceptance' message is received.

'Successful Acceptance' received Y/N_____

Check on the housekeeping display that TC Good has increased by 1

TC Good increased by 1 Y/N_____

Make a note of TC Bad from the housekeeping display _____

Send the command /iBad660

Check on the housekeeping display that TC Bad has increased by 1

TC Bad increased by 1 Y/N_____

If the above responses are Y's then the test is successful.

Test Successful

10. HEATERS

10.1 Enable/disable automatic heater control

Load the telescope simulator configuration file heater_test.dat

Load a correct heater control table into EEPROM. load "heater1.img" load "heater2.img"

Reset the ICU. icureset

Run a STOL procedure to set the spacecraft voltage to 32V. start scvolts32

In housekeeping the spacecraft voltage should now be set to 32.00V

Spacecraft voltage set to 32.00V in housekeeping Y/N _____

Monitor the telescope simulator temperatures IF_A and SEC1 on the telescope simulator display.

IF_A should fall below 567. When it does the first heater should come on within 10s – the first value in the heater array will be a 1. IF_A should now increase in value. Once it exceeds 583 the first heater should go off within 10s, ie the value will be 0 and IF_A should start to decrease again.

SEC1 should fall below 551. When it does the second heater should come on within 10s – the second value in the heater array will be a 1. SEC1 should now increase in value. Once it exceeds 599 the second heater should go off within 10s, ie the value will be 0 and SEC1 should start to decrease again.

The third heater should cycle 5s on and 5s off – the third value in the heater array will switch between a 1 and a 0 every 5s.

The fourth heater should not come on - the fourth value in the heater array should stay at 0.

Also check that heater control is active, ie iHtrCntrlActive in the housekeeping is set to 1.

| IF_A falls below 567 Y/N | |
|--|--|
| Then first heater comes on within 10s Y/N | |
| Then IF_A rises to above 583 Y/N | |
| Then first heater goes off within 10s Y/N | |
| Then IF_A falls again Y/N | |
| SEC1 falls below 551 Y/N | |
| Then second heater comes on within 10s Y/N | |
| Then SEC1 rises to above 599 Y/N | |

| Then second heater goes off within 10s Y/N | |
|--|--|
| Then SEC1 falls again Y/N | |
| Third heater cycles, 5s on, 5s off Y/N | |
| Fourth heater stays 0 all the time Y/N | |
| iHtrCntrlActive in housekeeping set to 1 Y/N | |

Then load another correct heater control table into EEPROM.

load "heater_alt1.img"
load "heater_alt2.img"

Make sure the table is seen.

/iHtr Off

Make sure that the heater control active flag is set to $0\ \textsc{in}$ the housekeeping /iHtr <code>On</code>

Monitor the telescope simulator temperatures IF_A and SEC1 on the telescope simulator display.

IF_A should fall below 567. When it does the first heater should come on within 10s – the first value in the heater array will be a 1. IF_A should now increase in value. Once it exceeds 583 the first heater should go off within 10s, ie the value will be 0 and IF_A should start to decrease again.

SEC1 should fall below 551. When it does the second heater should come on within 10s – the second value in the heater array will be a 1. SEC1 should now increase in value. Once it exceeds 599 the second heater should go off within 10s, ie the value will be 0 and SEC1 should start to decrease again.

The third heater should not come on – the third value in the heater array should stay at 0. The fourth heater should cycle 5s on and 5s off – the fourth value in the heater array will switch between a 1 and a 0 every 5s.

Also check that heater control is active, ie iHtrCntrlActive in the housekeeping is set to 1.

| IF_A falls below 567 Y/N | |
|--|--|
| Then first heater comes on within 10s Y/N | |
| Then IF_A rises to above 583 Y/N | |
| Then first heater goes off within 10s Y/N | |
| Then IF_A falls again Y/N | |
| SEC1 falls below 551 Y/N | |
| Then second heater comes on within 10s Y/N | |
| Then SEC1 rises to above 599 Y/N | |
| Then second heater goes off within 10s Y/N | |
| Then SEC1 falls again Y/N | |
| Third heater stays 0 all the time Y/N | |
| Fourth heater cycles, 5s on, 5s off Y/N | |
| iHtrCntrlActive in housekeeping set to 1 Y/N | |

Now run a series of stop-start checks.

The heaters are already running. Command them to switch on while they're on and watch for 5 minutes to check that this is handled correctly.

/iHtr On

On the telescope simulator display, the temperatures should rise and fall as before. Check that when IF_A falls below 567 iHtrMain is set to 1 in the housekeeping within 10s, and when SEC1 falls below 551 iHtrForward is set to 1 in the housekeeping within 10s. Also check that when IF_A rises above 583 iHtrMain is set to 0 in the housekeeping within 10s, and when SEC1 rises above 599 iHtrForward is set to 1 in the housekeeping within 10s. iHtrSecondary should always be set to 0, while on the telescope simulator display the fourth heater should cycle 5s on, 5s off. The heater control active flag should be set to 1.

| | Result seen | Expected result | Are seen and expected results the same Y/N |
|-----------------------------|-------------|-----------------|---|
| iHtrMain set to 1 when | | Y | |
| IF_A falls below 567 Y/N | | | |
| iHtrForward set to 1 when | | Y | |
| SEC1 falls below 551 Y/N | | | |
| iHtrMain set to 0 when | | Y | |
| IF_A rises above 583 Y/N | | | |
| iHtrForward set to 0 when | | Y | |
| SEC1 rises above 599 Y/N | | | |
| iHtrSecondary always set to | | Y | |
| 0 Y/N | | | |
| Fourth heater cycles Y/N | | Y | |
| iHtrCntrlActive set to 1 | | Y | |

Switch off the heaters and check that this is handled correctly. Watch for 5 minutes /iHtr Off

On the housekeeping display iHtrCntrlActive should be set to 0 and all so should all heaters. The heater control task should be asleep and its task counter not changing.

| | Result seen | Expected result | Are seen and expected results the same Y/N |
|---------------------------|-------------|-----------------|---|
| iHtrCntrlActive value | | 0 | |
| iHtrMain value | | 0 | |
| iHtrForward value | | 0 | |
| iHtrMetering value | | 0 | |
| iHtrSecondary value | | 0 | |
| Heater Control Task value | | Asleep | |
| Heater Control Task | | No changes | |

SWIFT-UVOT ICU CODE BUILD 5 TEST PLAN

Document: MSSL/SWT-UVOT/MSSL/xx/xxxx.x

| Counter | | |
|---------|--|--|
| | | |

Then test to see whether commanding the heaters to switch off while they are already off is handled correctly.

/iHtr Off

On the housekeeping display iHtrCntrlActive should stay at 0 and all heaters should stay at 0.

| | Result seen | Expected result | Are seen and expected results the same Y/N |
|-----------------------|-------------|--------------------|---|
| iHtrCntrlActive value | | 0 | |
| iHtrMain value | | 0 | |
| iHtrForward value | | 0 | |
| iHtrMetering value | | 0 | |
| iHtrSecondary value | | 0 | |

Finally return the system to its normal state. Watch for 5 minutes.

/iHtr On

On the telescope simulator display, the temperatures should rise and fall as before. Check that when IF_A falls below 567 iHtrMain is set to 1 in the housekeeping within 10s, and when SEC1 falls below 551 iHtrForward is set to 1 in the housekeeping within 10s. Also check that when IF_A rises above 583 iHtrMain is set to 0 in the housekeeping within 10s, and when SEC1 rises above 599 iHtrForward is set to 1 in the housekeeping within 10s. iHtrSecondary should always be set to 0, while on the telescope simulator display the fourth heater should cycle 5s on, 5s off. The heater control active flag should be set to 1. The heater control task should be alive and its counter increasing by 20 per hk packet.

| | Result seen | Expected result | Are seen and expected results the same Y/N |
|-----------------------------|-------------|-----------------|--|
| iHtrMain set to 1 when IF_A | | Y | |
| falls below 567 Y/N | | | |
| iHtrForward set to 1 when | | Y | |
| SEC1 falls below 551 Y/N | | | |
| iHtrMain set to 0 when IF_A | | Y | |
| rises above 583 Y/N | | | |
| iHtrForward set to 0 when | | Y | |
| SEC1 rises above 599 Y/N | | | |
| iHtrSecondary always set to | | Y | |
| 0 Y/N | | | |
| Fourth heater cycles Y/N | | Y | |
| iHtrCntrlActive set to 1 | | Y | |
| Heater Control Task Alive | | Y | |

| Heater Control Task counter | Y | |
|-----------------------------|---|--|
| increases by 20 per hk | | |
| packet | | |

Now make sure that a TDRSS packet (APID 0x3C0) and a realtime copy of it (APID 0x361) are produced when a corrupted heater control table is in EEPROM. First make sure that the TDRSS packets can be seen on ITOS by entering seqprt tdrss

Then load the corrupted table load "heaterc1.img" load "heaterc2.img"

Make sure the table is seen. /iHtr Off Make sure that the heater control active flag is set to 0 in the housekeeping /iHtr On

A TDRSS packet with error 'Corrupted EEPROM Data' and first parameter set to 3 should be received, plus a realtime copy of this packet in housekeeping. The heaters should never come on, which can be ascertained from the housekeeping display – iHtrCntrlActive should be set to 0.

| TDRSS packet received Y/N | |
|--|--|
| Error message 'Corrupted EEPROM Data' received Y/N | |
| First parameter set to 3 Y/N | |
| Realtime copy of packet received Y/N | |
| Heaters never come on Y/N | |

Then, make sure that a TDRSS packet and a realtime copy of it are produced when a heater control table with bad data is in EEPROM.

load "heaterb1.img"
load "heaterb2.img"

Make sure the table is seen. /iHtr Off Make sure that the heater control active flag is set to 0 in the housekeeping /iHtr On

A TDRSS packet with error 'Bad Data in EEPROM' and first parameter set to 3 should be received, plus a realtime copy of this packet in housekeeping. The heaters should never come on, which can be ascertained from the housekeeping display – iHtrCntrlActive should be set to 0.

| TDRSS packet received Y/N | |
|---|--|
| Error message 'Bad Data in EEPROM' received Y/N | |
| First parameter set to 3 Y/N | |
| Realtime copy of packet received Y/N | |
| Heaters never come on Y/N | |

Then, make sure that a TDRSS packet and a realtime copy of it are produced when a heater control table with bad thermistor data is in EEPROM.

load "heaterbt1.img"
load "heaterbt2.img"

Make sure the table is seen. /iHtr Off Make sure that the heater control active flag is set to 0 in the housekeeping /iHtr On

A TDRSS packet with error 'Bad Data in EEPROM' and first parameter set to 3 should be received, plus a realtime copy of this packet in housekeeping. The heaters should never come on, which can be ascertained from the housekeeping display – iHtrCntrlActive should be set to 0.

| TDRSS packet received Y/N | |
|---|--|
| Error message 'Bad Data in EEPROM' received Y/N | |
| First parameter set to 3 Y/N | |
| Realtime copy of packet received Y/N | |
| Heaters never come on Y/N | |

Then, make sure that a TDRSS packet and a realtime copy of it are produced when a heater control table with bad thermistor number data is in EEPROM.

load "heaterbn1.img"
load "heaterbn2.img"

Make sure the table is seen. /iHtr Off Make sure that the heater control active flag is set to 0 in the housekeeping /iHtr On

A TDRSS packet with error 'Bad Data in EEPROM' and first parameter set to 3 should be received, plus a realtime copy of this packet in housekeeping. The heaters should never come on, which can be ascertained from the housekeeping display – iHtrCntrlActive should be set to 0.

| TDRSS packet received Y/N | |
|---------------------------|--|
|---------------------------|--|

| Error message 'Bad Data in EEPROM' received Y/N | |
|---|--|
| First parameter set to 3 Y/N | |
| Realtime copy of packet received Y/N | |
| Heaters never come on Y/N | |

Finally, reload good heater tables.

load "heater1.img"
load "heater2.img"

Make sure the table is seen. /iHtr Off Make sure that the heater control active flag is set to 0 in the housekeeping /iHtr On

The test is successful if the spacecraft voltage is set correctly and all responses in the last column of each table are Y's.

Test Successful _____

10.2 Automatic heater setting

This command is still under debate. A partial test is given below. If the command has been further refined by testing time then please construct a relevant test procedure and append it to the end of this document.

Make sure that the heater table loaded is the one contained in heater1.img and heater2.img. Also make sure that the telescope simulator is running with configuration file heater_test.dat.

Note that heater settings can only be changed when the automatic heater control is off.

Set automatic heater control on first of all /iHtr \mbox{On}

```
Send the command
/iHtrParams Number=3, OnTime=0, CycleTime=0,
    Tmin_Vnom=3200, Tmax_Vdrop=150
```

A verification packet with the message 'Illegal Function Code' should be received.

Message 'Illegal Function Code' received Y/N

Switch off the automatic heater control /iHtr Off

```
Send the command
/iHtrParams Number=3, OnTime=0, CycleTime=0,
   Tmin_Vnom=3200, Tmax_Vdrop=150
```

A 'successful acceptance' verification packet should be received.

'Successful acceptance' received Y/N _____

Switch the automatic heater control back on /iHtr \mbox{On}

Watch the telescope simulator display.

The first two heaters should cycle as described for the first table in the previous section. The third and fourth heaters should be permanently off, ie set to 0.

First and second heaters cycling as before Y/N _____ Third and fourth heaters off Y/N _____

Switch the heater control off and alter the settings again, then switch it back on /iHtr Off /iHtrParams Number=2, Tmin_Vnom=540, Tmax_Vdrop=610, NumThermistors=1, Therm1=4, Therm2=4, Therm3=4 /iHtr On

Watch the telescope simulator display.

The main heater should cycle between the values 567 and 583, triggering on the value of main, and the forward heater should cycle between the values 540 and 610, triggering on the value of forward1.

Main cycles between 567 and 583 on main Y/N_____ Forward cycles between 540 and 610 on forward 1 Y/N_____

Switch the heater control off and alter the settings again, then switch it back on
/iHtr Off
/iHtrParams Number=1, Tmin_Vnom=570, Tmax_Vdrop=580,
NumThermistors=1, Therm1=3, Therm2=3, Therm3=3
/iHtr On

Watch the telescope simulator display.

The main heater should cycle between the values 570 and 580, triggering on the value of main, and the forward heater should cycle between the values 540 and 610, triggering on the value of forward1.

Main cycles between 570 and 580 on main Y/N_____ Forward cycles between 540 and 610 on forward 1 Y/N_____

Switch the heater control off and alter the settings again, then switch it back on /iHtr Off /iHtrParams Number=1, Tmin_Vnom=570, Tmax_Vdrop=580, NumThermistors=1, Therm1=1, Therm2=2, Therm3=7 /iHtr On

Watch the telescope simulator display.

The main heater should cycle between the values 570 and 580, triggering on the value of ref A, and the forward heater should cycle between the values 540 and 610, triggering on the value of forward1.

Main cycles between 570 and 580 on ref A Y/N_____ Forward cycles between 540 and 610 on forward 1 Y/N_____

Switch the heater control off and alter the settings again, then switch it back on /iHtr Off /iHtrParams Number=2, Tmin_Vnom=540, Tmax_Vdrop=610, NumThermistors=1, Therm1=5, Therm2=4, Therm3=4 /iHtr On

Watch the telescope simulator display.

The main heater should cycle between the values 567 and 583, triggering on the value of main, and the forward heater should cycle between the values 540 and 610, triggering on the value of forward2.

Main cycles between 567 and 583 on main Y/N_____ Forward cycles between 540 and 610 on forward 2 Y/N_____

Switch the heater control off and alter the settings again, then switch it back on /iHtr Off

```
/iHtrParams Number=2, Tmin_Vnom=540, Tmax_Vdrop=610,
NumThermistors=2, Therm1=5, Therm2=4, Therm3=4
/iHtr On
```

Watch the telescope simulator display.

The main heater should cycle between the values 567 and 583, triggering on the value of main, and the forward heater should cycle between the values 540 and 610, triggering on the average value of forward1 and forward2.

Main cycles between 567 and 583 on main Y/N_____ Forward cycles between 540 and 610 on ave. of forwards 1 and 2 Y/N_____

Switch the heater control off and alter the settings again, then switch it back on /iHtr Off /iHtrParams Number=1, Tmin_Vnom=570, Tmax_Vdrop=580, NumThermistors=3, Therm1=7, Therm2=1, Therm3=2 /iHtr On

Watch the telescope simulator display.

The main heater should cycle between the values 570 and 580, triggering on the average value of ref A, refB and ref C, and the forward heater should cycle between the values 540 and 610, triggering on the average value of forward1 and forward2.

Main cycles between 570 and 580 on ave. of refs A, B and C Y/N______ Forward cycles between 540 and 610 on ave. of forwards 1 and 2 Y/N______

Now reset to the onboard table values using

/iHtr Off /iHtr On

Watch the telescope simulator display.

The main heater should cycle between the values 567 and 583, triggering on the value of main, and the forward heater should cycle between the values 551 and 599, triggering on the value of forward1.

Main cycles between 567 and 583 on main Y/N_____ Forward cycles between 551 and 599 on forward 1 Y/N_____

If all the responses above are Y's then the test is successful.

| Test Successful | | | |
|-----------------|--|--|--|
| | | | |

11. DCS

11.1 DCS

Command a low priority RTS to run and then interrupt it with a higher priority RTS using /iRTSRun RTS=0x53 /iRTSRun RTS=0x52

Check on the NHK display that a 'DCS Aborting' message and a 'Switching RTS' message have been received.

'DCS Aborting' received Y/N ______ 'Switching RTS' received Y/N ______

Command an RTS to run and then interrupt it with the same RTS using /iRTSRun RTS=0x52 /iRTSRun RTS=0x52

Check on the NHK display that a 'DCS RTS Already Running' message is received.

'DCS RTS Already Running' received Y/N _____

Call a non-existent RTS using /iRTSRun RTS=0xFFF

Check on the NHK display that a 'DCS No Such RTS' message has been received.

'DCS No Such RTS' received Y/N _____

Call an RTS that calls a dummy telecommand with too many parameters using /iRTSRun RTS=0x50

Check on the NHK display that a 'DCS Stack Exceeded' message has been received.

'DCS Stack Exceeded' received Y/N _____

Load a corrupted rts.img file, then reload the flight code using load "test_rts_bad_code.img" load icu.hex

Call an RTS that will encounter the corruption using /iRTSRun RTS=0x53

Check on the NHK display that a 'DCS Invalid Command Token' message has been received.

'DCS Invalid Command Token' received Y/N _____

Reload the original rts.img load "rts.img"

Reload flight code icu.hex.

Check on the housekeeping that the ICU is in the safe state and the RTS Depth is 0.

ICU safe Y/N_____ RTS Depth 0 Y/N_____

Call an RTS that will call itself /iRTSRun RTS=0x51

Check on the NHK display that a 'DCS Call Depth Exceeded' message has been received, and on the housekeeping display that the RTS Depth is 5.

'DCS Call Depth Exceeded' received Y/N ______ RTS Depth 5 Y/N ______

Order a state transition to idle mode. /iState idle

Check on the NHK display that an 'Exit from safe Forbidden' message is received, and from the housekeeping display that the ICU stays in safe mode.

'Exit from safe Forbidden' received Y/N_____ ICU stays in safe mode Y/N_____

Edit the code to force a DCS timeout, compile this test version of the code and run it.

Check on the NHK display that a 'DCS Timeout Aborting RTS' message has been received.

'DCS Timeout Aborting RTS' received Y/N _____

Command two RTS's to run in quick succession, the second having lower priority than the first using /iRTSRun RTS=0x52

/iRTSRun RTS=0x52 /iRTSRun RTS=0x53

Check on the NHK display that a 'DCS Insufficient Priority' message has been received.

'DCS Insufficient Priority' received Y/N

After the RTS finishes check on the housekeeping the following;

Top Level RTS is 0 Y/N_____ Bottom Level RTS is 0 Y/N_____ Task DCS is asleep Y/N_____ Task DCS counter is unchanging Y/N_____

Enable line tracing using /iRTSTrace Enable=On

Call an RTS /iRTSRun RTS=0x52

Check on the NHK display that at least one 'DCS Line Trace' message has been received.

'DCS Line Trace' received Y/N _____

Check on the housekeeping the following;

 Top Level RTS is 0x52 Y/N_____

 Bottom Level RTS is 0x52 Y/N_____

 RTS Line Number changes Y/N_____

 Task DCS is alive Y/N_____

 Task DCS counter is increasing Y/N_____

Disable line tracing using /iRTSTrace Enable=Off

Check on the NHK display that 'DCS Line Trace' messages cease

Messages cease Y/N_____

Also check that the kill command works by sending $/ \verb"iRTSKill"$

Check on the housekeeping display that the RTS stops, and on the NHK that a 'DCS Exiting RTS' message is received.

RTS stops Y/N_____ 'DCS Exiting RTS'received Y/N_____

Call an RTS with too few arguments /iRTSRun RTS=0x500

Check on the NHK display that the messages 'DCS Starting RTS', 'DCS Too Few Arguments' and 'DSC Exiting RTS' are received.

'DCS Starting RTS' received Y/N_____'DCS Too Few Arguments' received Y/N_____'DSC Exiting RTS' received Y/N_____

If all the above responses are Y's then the test is successful.

Test Successful

12. SC1553

Set up the test environment with the debug interface, and run the telescope simulator with the configuration file hk_in_limits.dat, and run the DPU simulator with any one value out of limits, the rest within limits.

Check that as yet no errors are registered by the SC1553 interface. In housekeeping iSC1553Errors and iSC1553IntReg should be set to 0.

| In housekeeping, iSC1553Errors set to 0 Y/N | |
|---|--|
| In housekeeping, iSC1553IntReg set to 0 Y/N | |

Switch off the limit checking /iLimitOff

Make a note of the value of iTMBadPckts in the housekeeping here

Remove the spacecraft interface for 60s.

During this time make sure that the interface interrupt, IHTC and TC packet counters stop.

| In housekeeping, iSC1553Ints does not increment Y/N | |
|---|--|
| In housekeeping, iSC1553IHTC does not increment Y/N | |
| In housekeeping, iSC1553TCPckt does not increment Y/N | |

Reconnect the spacecraft interface to A.

Check that the ICU hasn't crashed via the debug interface.

0xEC5E should not appear.

Check telemetry.

Make sure in housekeeping that iTMBadPckts has increased by 6 (ie once per 10s while interface is disconnected, there may be some jitter on this value due to interacting timing cycles), and that iSC1553Channel is set to A. Check that after reconnection iTMGoodPckts increases by 1 per 10s. Also make sure that the interface interrupt, IHTC and TC packet counters start to increment again – generally they should all have the same value, and increment at a rate of 6 per second (ie about 60 per housekeeping packet), although it is possible for the TC packet counter to drop behind the others in

value by as much as 10. Check the debug interface for an appropriate message.

0x1589 should appear.

| 0xEC5E does NOT appear on debug interface Y/N | |
|---|--|
| In housekeeping, iTMBadPckts increased by 6 Y/N | |
| In housekeeping, iSC1553Channel set to A Y/N | |

| In housekeeping, iTMGoodPckts increments by 1 per 10s Y/N | |
|---|--|
| In housekeeping, iSC1553Ints increments by 60 per 10s Y/N | |
| In housekeeping, iSC1553IHTC increments by 60 per 10s Y/N | |
| In housekeeping, iSC1553TCPckt increments by 60 per 10s Y/N | |
| 0x1589 appears on debug interface Y/N | |

Switch the limit checking back on /iLimitOn

Check that RT to RT packets are arriving correctly in telemetry. *iRT2RTGoodPckts should increase at the same rate as TDRSS packets arrive.*

In housekeeping, iRT2RTGoodPckts increases at the same rate as TDRSS packets arrive Y/N

Make a note of the value of iRT2RTGoodPackts here _____

Disconnect the spacecraft interface for 5mins.

Reconnect the spacecraft interface to B.

Check that RT to RT bad packets are seen correctly in telemetry. *iRT2RTBadPckts should have increased at the same rate as iRT2RTGoodPckts did above.*

| In housekeeping, iRT2RTBadPckts increased at the same rate as | |
|---|--|
| iRT2RTGoodPckts did aboveY/N | |

Check that the ICU hasn't crashed via the debug interface. *0xEC5E should not appear*. Check that housekeeping continues after the interruption. *In the housekeeping packet iSC1553Channel should be B.*

| 0xEC5E does NOT appear on debug interface Y/N | |
|---|--|
| In housekeeping, iSC1553Channel set to B Y/N | |

Now force errors on the SC1553 interface by disconnecting and reconnecting it – about ten times should be sufficient.

In housekeeping iSC1553Errors should increase and iSC1553IntReg should become nonzero.

| In housekeeping, iSC1553Errors increases Y/N | |
|--|--|
| In housekeeping, iSC1553IntReg non-zero Y/N | |

If all the responses in the tables above are Y's then the test is successful.

Test Successful

13. SSI

Switch on the DPU simulator, which will then automatically send heartbeats.

Check the housekeeping packet for the heartbeat counter

In housekeeping iDPUHeartbeats should increment approximately once every 10s. (For information, this value is approximate because the sending and sampling rates beat together, so occasionally a heartbeat may be missed by the sampling.)

| | Result seen | Expected result | Are result seen and expected result the same Y/N |
|--------------------------|----------------|--------------------|--|
| iDPUHeartbeats increment | | 1 per 10s | |
| rate | | | |

Check the housekeeping packet for heartbeat related housekeeping values. Check that iSSIInterrupts and iSSIGood increment at the same rate as the heartbeats are sent.

Check that iSSIBad and iSSIErrors do not increment.

| | Result seen | Expected result | Are result seen and expected result the same Y/N |
|-------------------------------|----------------|--------------------|--|
| iSSIInterrupts increment rate | | 1 per 10s | |
| iSSIGood increment rate | | 1 per 10s | |
| iSSIBad increment rate | | None | |
| iSSIErrors increment rate | | None | |

Now stop the DPU task. /iDPUTask Off

Check that no overflows have occurred so far.

The half-full counter iSSIHalfFulls and the overflow counter iSSIOverflows should be set to 0 in housekeeping.

| | Result seen | Expected result | Are result seen and expected result the same Y/N |
|---------------------|----------------|--------------------|--|
| iSSIHalfFulls value | | 0 | |
| iSSIOverflows value | | 0 | |

Force overflows by increasing the DPU simulator rate to its fastest possible, which is 1 per 4ms, and check the results in housekeeping.

The half-full counter iSSIHalfFulls should increment rapidly and so should iSSIOverflows. They should both reach 0xFFFF and clock over within one minute . For information, the overflow counter iSSIOverflows may briefly register a value and then reset itself to zero - this is expected behaviour.

| | Result seen | Expected result | Are result seen and expected result the same Y/N |
|---------------------------|----------------|--------------------|--|
| iSSIHalfFulls clocks over | | Y | |
| within 1minute | | | |
| iSSIOverflows clocks over | | Y | |
| within 1minute | | | |

Finally restore the DPU simulator to its normal rate and re-enable the DPU task. /iDPUTask <code>On</code>

If all responses in column 4 of all the tables above are Y's then the test is successful.

Test Successful

14. FUNDAMENTAL STATE CHANGES

14.1 Safe to idle transition

Load flight code icu.hex.

Check that the following parameters on the housekeeping display are as given below.

ICU state safe Y/N _____ Vcathode off Y/N _____ Vmcp1 off Y/N _____ Vmcp23 off Y/N _____ Filter wheel blocked Y/N _____

Send the command
/istate state=idle

Check that the following parameters on the housekeeping display are as given below.

ICU state idle Y/N ______ Vcathode off Y/N ______ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel blocked Y/N _____

Check on the NHK display that a 'Centroid Table Load OK' message and a 'Window Table Load OK' message have been received.

'Centroid Table Load OK' received Y/N_____'Window Table Load OK' received Y/N_____

If all the above responses are Y's then the test is successful.

Test Successful

14.2 AT at a never before observed location

Set up the celestial environment with Start autumnsafe

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Note here the RT-RT Good value in the housekeeping_____

Enable a full dump of the RTS's run with the command /iDCSTraceEnable On

Run the ITOS script firstat.proc with the command Start firstat

Check on the housekeeping display that the ICU goes to the idle state.

ICU idle Y/N _____

Check on the housekeeping display that the ICU goes to the slew state, and that the following parameters are as given below. Also check that the RT-RT Good counter increments by 1.

ICU in slew Y/N _____ Filter wheel blocked Y/N_____ RT-RT Good increments by 1 Y/N_____

Check on the housekeeping display that the ICU goes to the settling state, and that the following parameters are as given below.

ICU in settling Y/N _____ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel on filter 2 Y/N _____

Check on the housekeeping display that the ICU goes to the finding state, and that the following parameters are as given below.

ICU in finding Y/N _____

Vcathode nominal Y/N ______ Vmcp1 nominal Y/N ______ Vmcp23 nominal Y/N ______ Filter wheel on filter 3 Y/N _____

Check on the housekeeping display that the ICU goes to the AT state, that the three high voltages are set to nominal and that the filter wheel goes to filter 4, and that this configuration continues for 10s.

| ICU in AT Y/N | _ |
|--------------------------------|---|
| Vcathode nominal Y/N | _ |
| Vmcp1 nominal Y/N | |
| Vmcp23 nominal Y/N | |
| Filter wheel at filter 4 Y/N | |
| Configuration held for 10s Y/N | |

Check on the housekeeping display that the ICU stays in the AT state, that the three high voltages stay nominal and that the filter wheel goes to filter 6, and that this configuration continues for 20s.

| ICU in AT Y/N | _ |
|--------------------------------|---|
| Vcathode nominal Y/N | _ |
| Vmcp1 nominal Y/N | |
| Vmcp23 nominal Y/N | |
| Filter wheel at filter 6 Y/N | |
| Configuration held for 20s Y/N | |

Check on the housekeeping display that the ICU stays in the AT state, that the three high voltages stay nominal and that the filter wheel goes to filter 7, and that this configuration continues for 10s.

| ICU in AT Y/N | |
|--------------------------------|---|
| Vcathode nominal Y/N | |
| Vmcp1 nominal Y/N | |
| Vmcp23 nominal Y/N | |
| Filter wheel at filter 7 Y/N | |
| Configuration held for 10s Y/N | _ |

Check on the housekeeping display that the ICU stays in the AT state, that the three high voltages stay nominal and that the filter wheel goes to filter 9, and that this configuration continues for 10s.

| ICU in AT Y/N | |
|----------------------|---|
| Vcathode nominal Y/N | _ |
| Vmcp1 nominal Y/N | _ |
| Vmcp23 nominal Y/N | _ |

Filter wheel at filter 9 Y/N_____ Configuration held for 10s Y/N_____

Check on the housekeeping display that the ICU stays in the AT state, that the three high voltages stay nominal and that the filter wheel goes to filter 10, and that this configuration continues for 20s.

| ICU in AT Y/N | |
|--------------------------------|---|
| Vcathode nominal Y/N | |
| Vmcp1 nominal Y/N | |
| Vmcp23 nominal Y/N | |
| Filter wheel at filter 10 Y/N | _ |
| Configuration held for 20s Y/N | |

Check on the housekeeping display that the ICU stays in the AT state, that the three high voltages stay nominal and that the filter wheel goes to filter 1, and that this configuration continues for 20s.

| ICU in AT Y/N |
|--------------------------------|
| Vcathode nominal Y/N |
| Vmcp1 nominal Y/N |
| Vmcp23 nominal Y/N |
| Filter wheel at filter 1 Y/N |
| Configuration held for 20s Y/N |

Check on the housekeeping display that the ICU stays in the AT state, that the three high voltages stay nominal and that the filter wheel goes to filter 2, and that this configuration continues for 10s.

| ICU in AT Y/N |
|--------------------------------|
| Vcathode nominal Y/N |
| Vmcp1 nominal Y/N |
| Vmcp23 nominal Y/N |
| Filter wheel at filter 2 Y/N |
| Configuration held for 10s Y/N |

Check on the housekeeping display that the ICU stays in the AT state, that the three high voltages stay nominal and that the filter wheel goes to filter 3, and that this configuration continues for 20s.

ICU in AT Y/N ______ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel at filter 3 Y/N _____ Configuration held for 20s Y/N _____

Check on the housekeeping display that the ICU stays in the AT state, that the three high voltages stay nominal and that the filter wheel goes to filter 4, and that this configuration continues for 10s.

ICU in AT Y/N _____ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel at filter 4 Y/N _____ Configuration held for 10s Y/N ____

Check on the housekeeping display that the ICU stays in the AT state, that the three high voltages stay nominal and that the filter wheel goes to filter 6, and that this configuration continues for 25s.

| ICU in AT Y/N | |
|--------------------------------|---|
| Vcathode nominal Y/N | |
| Vmcp1 nominal Y/N | _ |
| Vmcp23 nominal Y/N | _ |
| Filter wheel at filter 6 Y/N | _ |
| Configuration held for 25s Y/N | |

Check on the housekeeping display that the ICU stays in the AT state, that the three high voltages stay nominal and that the filter wheel goes to filter 7, and that this configuration continues for 15s.

ICU in AT Y/N ______ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel at filter 7 Y/N _____ Configuration held for 15s Y/N _____

Finally, check from the RTS trace that the star catalogue was accessed and returned its values within 1s, and that the ICU began its response to the spacecraft slew warning within 1s.

Star catalogue returned within 1s Y/N_____ Slew warning response began within 1s Y/N_____

Disable the full dump of the RTS's run with the command /iDCSTraceEnable Off

Also check that the NHK message 'Centroid table load complete' was issued during this run.

Centroid table load complete' issued Y/N_____

If all the above responses are Y's then the test is successful.

Test Successful

14.3 AT with no XRT position given

Set up the celestial environment with Start autumnsafe

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Run the ITOS script atnoxrt.proc with the command ${\tt Start}$ atnoxrt

Check on the housekeeping display that the ICU goes to the idle state.

ICU idle Y/N _____

Check on the housekeeping display that the ICU goes to the slew state, and that the following parameters are as given below.

ICU in slew Y/N _____ Filter wheel blocked Y/N_____

Check on the housekeeping display that the ICU goes to the settling state, and that the following parameters are as given below.

ICU in settling Y/N _____ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel on filter 2 Y/N _____

Check on the housekeeping display that the ICU goes to the finding state, and that the following parameters are as given below.

| ICU in finding Y/N |
|------------------------------|
| Vcathode nominal Y/N |
| Vmcp1 nominal Y/N |
| Vmcp23 nominal Y/N |
| Filter wheel on filter 3 Y/N |

Check on the housekeeping display that the ICU goes to the AT state, that the three high voltages are set to nominal and that the filter wheel goes to filter 4, and that this configuration continues for 20s.

ICU in AT Y/N ______ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel at filter 4 Y/N _____ Configuration held for 20s Y/N ____

Check on the housekeeping display that the ICU stays in the AT state, that the three high voltages stay nominal and that the filter wheel goes to filter 6, and that this configuration continues for 10s.

ICU in AT Y/N _____ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel at filter 6 Y/N _____ Configuration held for 10s Y/N _____

Check on the housekeeping display that the ICU stays in the AT state, that the three high voltages stay nominal and that the filter wheel goes to filter 7, and that this configuration continues for 20s.

ICU in AT Y/N ______ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel at filter 7 Y/N _____ Configuration held for 20s Y/N _____

Check on the housekeeping display that the ICU stays in the AT state, that the three high voltages stay nominal and that the filter wheel goes to filter 9, and that this configuration continues for 20s.

ICU in AT Y/N ______ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel at filter 9 Y/N _____ Configuration held for 20s Y/N ____

Check on the housekeeping display that the ICU stays in the AT state, that the three high voltages stay nominal and that the filter wheel goes to filter 10, and that this configuration continues for 10s.

ICU in AT Y/N _____

Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel at filter 10 Y/N _____ Configuration held for 10s Y/N _____

Check on the housekeeping display that the ICU stays in the AT state, that the three high voltages stay nominal and that the filter wheel goes to filter 1, and that this configuration continues for 10s.

ICU in AT Y/N _____ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel at filter 1 Y/N _____ Configuration held for 10s Y/N _____

Check on the housekeeping display that the ICU stays in the AT state, that the three high voltages stay nominal and that the filter wheel goes to filter 2, and that this configuration continues for 20s.

ICU in AT Y/N _____ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel at filter 2 Y/N _____ Configuration held for 20s Y/N _____

Check on the housekeeping display that the ICU stays in the AT state, that the three high voltages stay nominal and that the filter wheel goes to filter 3, and that this configuration continues for 10s.

ICU in AT Y/N ______ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel at filter 3 Y/N _____ Configuration held for 10s Y/N _____

Check on the housekeeping display that the ICU stays in the AT state, that the three high voltages stay nominal and that the filter wheel goes to filter 4, and that this configuration continues for 20s.

ICU in AT Y/N _____ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N_____

Vmcp23 nominal Y/N _____ Filter wheel at filter 4 Y/N_____ Configuration held for 20s Y/N_____

Check on the housekeeping display that the ICU stays in the AT state, that the three high voltages stay nominal and that the filter wheel goes to filter 6, and that this configuration continues for 25s.

| ICU in AT Y/N |
|--------------------------------|
| Vcathode nominal Y/N |
| Vmcp1 nominal Y/N |
| Vmcp23 nominal Y/N |
| Filter wheel at filter 6 Y/N |
| Configuration held for 25s Y/N |

Check on the housekeeping display that the ICU stays in the AT state, that the three high voltages stay nominal and that the filter wheel goes to filter 7, and that this configuration continues for 15s.

| ICU in AT Y/N |
|--------------------------------|
| Vcathode nominal Y/N |
| Vmcp1 nominal Y/N |
| Vmcp23 nominal Y/N |
| Filter wheel at filter 7 Y/N |
| Configuration held for 15s Y/N |

If all the above responses are Y's then the test is successful.

Test Successful

14.4 PT

Set up the celestial environment with Start autumnsafe

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state, and that the star cat task is asleep, and that its counter is not increasing.

ICU safe Y/N _____ Star cat task asleep Y/N_____ Star cat task counter unchanging Y/N______

Run the ITOS script pt.proc with the command Start pt

Check on the housekeeping display that the ICU goes to the idle state.

ICU idle Y/N _____

Check on the housekeeping display that the ICU goes to the slew state, and that the following parameters are as given below, and also that the star cat task comes alive (this may be difficult to see given the housekeeping sampling rate) and its counter increases by 1.

ICU in slew Y/N _____ Filter wheel blocked Y/N_____

Star cat task counter alive Y/N_____ Star cat task counter has increased by 1 Y/N_____

Check on the housekeeping display that the ICU goes to the PT state, that the three high voltages are set to nominal and that the filter wheel goes to filter 5, and that this configuration continues for 10s.

| ICU in PT Y/N | |
|--------------------------------|---|
| Vcathode nominal Y/N | |
| Vmcp1 nominal Y/N | |
| Vmcp23 nominal Y/N | _ |
| Filter wheel at filter 5 Y/N | _ |
| Configuration held for 10s Y/N | |

Check on the housekeeping display that the ICU stays in the PT state, that the three high voltages stay nominal and that the filter wheel goes to filter 6, and that this configuration continues for 20s.

ICU in PT Y/N _____ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel at filter 6 Y/N _____ Configuration held for 20s Y/N _____

Check on the housekeeping display that the ICU stays in the PT state, that the three high voltages stay nominal and that the filter wheel goes to filter 7, and that this configuration continues for 30s.

ICU in PT Y/N ______ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel at filter 7 Y/N _____ Configuration held for 30s Y/N _____

Check on the housekeeping display that the ICU goes to the idle state, that the three high voltages stay nominal and that the filter wheel goes to blocked.

ICU in PT Y/N _____ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel blocked Y/N _____

If all the above responses are Y's then the test is successful.

Test Successful

14.5 Calibration PT – Intensifier Characteristics / Pulse Height

Set up the celestial environment with Start autumnsafe

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Run the ITOS script calibintens.proc with the command $\ensuremath{\mathsf{Start}}$ calibintens

Check on the housekeeping display that the ICU goes to the idle state.

ICU idle Y/N _____

Check on the housekeeping display that the ICU goes to the slew state, and that the following parameters are as given below.

ICU in slew Y/N _____ Filter wheel blocked Y/N_____

Check on the housekeeping display that the ICU goes to the PT state, that the three high voltages are set to nominal and that the filter wheel stays blocked, and that this configuration continues for 20s. Also the Flood LED current should be set to 8 units.

| ICU in PT Y/N |
|--------------------------------|
| Vcathode nominal Y/N |
| Vmcp1 nominal Y/N |
| Vmcp23 nominal Y/N |
| Filter wheel blocked Y/N |
| Configuration held for 20s Y/N |
| Flood LED at 8 units Y/N |
| |

If all the above responses are Y's then the test is successful.

| Test Successful | |
|-----------------|--|
| | |

14.6 A PT with a non-full-image detector window

Set up the celestial environment with Start autumnsafe

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

Run the ITOS script smallwin.proc with the command $\ensuremath{\mathsf{Start}}$ smallwin

Check on the NHK display that a 'Window Table Load OK' message has been received.

'Window Table Load OK' received Y/N_____

Check on the housekeeping display that the ICU goes to the idle state.

ICU idle Y/N _____

Check on the housekeeping display that the ICU goes to the slew state, and that the following parameters are as given below.

ICU in slew Y/N _____ Filter wheel blocked Y/N_____

Check on the housekeeping display that the ICU goes to the PT state, that the three high voltages are set to nominal and that the filter wheel goes to filter 5, and that this configuration continues for 10s.

ICU in PT Y/N _____ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel at filter 5 Y/N _____ Configuration held for 10s Y/N _____

Check on the housekeeping display that the ICU stays in the PT state, that the three high voltages stay nominal and that the filter wheel goes to filter 6, and that this configuration continues for 20s.

ICU in PT Y/N _____ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N_____

Vmcp23 nominal Y/N _____ Filter wheel at filter 6 Y/N_____ Configuration held for 20s Y/N_____

Check on the housekeeping display that the ICU stays in the PT state, that the three high voltages stay nominal and that the filter wheel goes to filter 7, and that this configuration continues for 30s.

| ICU in PT Y/N | |
|---------------------------------|--|
| Vcathode nominal Y/N | |
| Vmcp1 nominal Y/N | |
| Vmcp23 nominal Y/N | |
| Filter wheel at filter 7 Y/N | |
| Configuration held for 30s Y/N_ | |

Check on the NHK display that another 'Window Table Load OK' message has been received.

'Window Table Load OK' received Y/N_____

If all the above responses are Y's then the test is successful.

Test Successful

14.7 Safepointing

Set up the celestial environment with Start autumn

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Run the ITOS script safepoint.proc with the command $\ensuremath{\mathsf{Start}}$ safepoint

Check on the housekeeping display that the ICU goes to the idle state.

ICU idle Y/N _____

Check on the housekeeping display that the ICU goes to the slew state, and that the following parameters are as given below.

ICU in slew Y/N _____ Filter wheel blocked Y/N_____

Check on the housekeeping display that the ICU goes to the safepoint state, and that the following parameters are as given below. Please note that the filter given below is for purposes of this test only – we have not yet been informed by our PI as to which filters will actually be used during safepointing.

ICU in safepoint Y/N _____ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel at filter1 Y/N _____

If all the above responses are Y's then the test is successful.

Test Successful

14.8 Two AT's at the same pointing, with a PT between them

NB: The test script also includes accurate longitude and latitude simulation in the ACS messages. This should not affect the outcome of the test.

Set up the celestial environment with Start autumnsafe

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Run the ITOS script atptat.proc with the command $\ensuremath{\mathsf{Start}}$ atptat

Check on the housekeeping display that the ICU goes to the idle state.

ICU idle Y/N _____

Check on the housekeeping display that the ICU goes to the slew state, and that the following parameters are as given below.

ICU in slew Y/N _____ Filter wheel blocked Y/N_____

Check on the housekeeping display that the ICU goes to the settling state, and that the following parameters are as given below.

ICU in settling Y/N ______ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel on filter 2 Y/N _____

Check on the housekeeping display that the ICU goes to the finding state, and that the following parameters are as given below.

| ICU in finding Y/N |
|------------------------------|
| Vcathode nominal Y/N |
| Vmcp1 nominal Y/N |
| Vmcp23 nominal Y/N |
| Filter wheel on filter 3 Y/N |

Check on the housekeeping display that the ICU goes to the AT state, that the three high voltages are set to nominal and that the filter wheel goes to filter 4, and that this configuration continues for 10s.

ICU in AT Y/N _____ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel at filter 4 Y/N _____ Configuration held for 10s Y/N _____

Check on the housekeeping display that the ICU stays in the AT state, that the three high voltages stay nominal and that the filter wheel goes to filter 6, and that this configuration continues for approximately 15s.

| ICU in AT Y/N | |
|--------------------------------|---|
| Vcathode nominal Y/N | |
| Vmcp1 nominal Y/N | |
| Vmcp23 nominal Y/N | |
| Filter wheel at filter 6 Y/N | |
| Configuration held for 15s Y/N | _ |

Check on the housekeeping display that the ICU goes to the slew state, and that the following parameters are as given below.

ICU in slew Y/N _____ Filter wheel at filter 5 Y/N_____ Vcathode zero Y/N_____

Check on the housekeeping display that the ICU goes to the PT state, that the three high voltages are set to nominal and that the filter wheel goes to filter 5, and that this configuration continues for 10s.

ICU in PT Y/N _____ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel at filter 5 Y/N _____ Configuration held for 10s Y/N ____

Check on the housekeeping display that the ICU stays in the PT state, that the three high voltages stay nominal and that the filter wheel goes to filter 6, and that this configuration continues for approximately 15s.

ICU in PT Y/N _____

Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel at filter 6 Y/N _____ Configuration held for 15s Y/N _____

Check on the housekeeping display that the ICU goes to the slew state, and that the following parameters are as given below.

ICU in slew Y/N _____ Filter wheel at filter 6 Y/N_____

Check on the housekeeping display that the ICU goes to the AT state, that the three high voltages are set to nominal and that the filter wheel goes to filter 7, and that this configuration continues for 10s.

| ICU in AT Y/N | _ |
|--------------------------------|---|
| Vcathode nominal Y/N | _ |
| Vmcp1 nominal Y/N | |
| Vmcp23 nominal Y/N | |
| Filter wheel at filter 7 Y/N | |
| Configuration held for 10s Y/N | |

Check on the housekeeping display that the ICU stays in the AT state, that the three high voltages stay nominal and that the filter wheel goes to filter 9, and that this configuration continues for 10s.

ICU in AT Y/N _____ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel at filter 9 Y/N _____ Configuration held for 10s Y/N _____

If all the above responses are Y's then the test is successful.

Test Successful

14.9 One AT followed by another at almost the same pointing

Set up the celestial environment with Start autumnsafe

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Run the ITOS script shortslew.proc with the command Start shortslew

Check on the housekeeping display that the ICU goes to the idle state.

ICU idle Y/N _____

Check on the housekeeping display that the ICU goes to the slew state, and that the following parameters are as given below.

ICU in slew Y/N _____ Filter wheel blocked Y/N_____

Check on the housekeeping display that the ICU goes to the settling state, and that the following parameters are as given below.

| ICU in settling Y/N | |
|------------------------------|--|
| Vcathode nominal Y/N | |
| Vmcp1 nominal Y/N | |
| Vmcp23 nominal Y/N | |
| Filter wheel on filter 2 Y/N | |

Check on the housekeeping display that the ICU goes to the finding state, and that the following parameters are as given below.

| ICU in finding Y/N |
|------------------------------|
| Vcathode nominal Y/N |
| Vmcp1 nominal Y/N |
| Vmcp23 nominal Y/N |
| Filter wheel on filter 3 Y/N |

Check on the housekeeping display that the ICU goes to the AT state, that the three high voltages are set to nominal and that the filter wheel goes to filter 4, and that this configuration continues for 10s.

ICU in AT Y/N _____ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel at filter 4 Y/N _____ Configuration held for 10s Y/N _____

Check on the housekeeping display that the ICU stays in the AT state, that the three high voltages stay nominal and that the filter wheel goes to filter 6, and that this configuration continues for approximately 15s.

| _ |
|---|
| |
| _ |
| |
| |

Check on the housekeeping display that the ICU goes to the slew state, and that the following parameters are as given below.

ICU in slew Y/N _____ Filter wheel at filter 6 Y/N_____

Check on the housekeeping display that the ICU goes to the settling state, and that the following parameters are as given below.

ICU in settling Y/N _____ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel on filter 2 Y/N _____

Check on the housekeeping display that the ICU goes to the finding state, and that the following parameters are as given below.

| ICU in finding Y/N |
|------------------------------|
| Vcathode nominal Y/N |
| Vmcp1 nominal Y/N |
| Vmcp23 nominal Y/N |
| Filter wheel on filter 3 Y/N |

Check on the housekeeping display that the ICU goes to the AT state, that the three high voltages are set to nominal and that the filter wheel goes to filter 4, and that this configuration continues for 10s.

ICU in AT Y/N _____ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel at filter 4 Y/N _____ Configuration held for 10s Y/N _____

Check on the housekeeping display that the ICU stays in the AT state, that the three high voltages stay nominal and that the filter wheel goes to filter 6, and that this configuration continues for approximately 20s.

| ICU in AT Y/N | |
|--------------------------------|---|
| Vcathode nominal Y/N | - |
| Vmcp1 nominal Y/N | _ |
| Vmcp23 nominal Y/N | |
| Filter wheel at filter 6 Y/N | |
| Configuration held for 20s Y/N | |

If all the above responses are Y's then the test is successful.

Test Successful

14.10 Interruption in finding state

Set up the celestial environment with Start autumnsafe

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Run the ITOS script if 1.proc with the command $\mbox{Start if1}$

Check on the housekeeping display that the ICU goes to the idle state.

ICU idle Y/N _____

Check on the housekeeping display that the ICU goes to the slew state, and that the following parameters are as given below.

ICU in slew Y/N _____ Filter wheel blocked Y/N_____

Check on the housekeeping display that the ICU goes to the settling state, and that the following parameters are as given below.

| ICU in settling Y/N |
|------------------------------|
| Vcathode nominal Y/N |
| Vmcp1 nominal Y/N |
| Vmcp23 nominal Y/N |
| Filter wheel on filter 2 Y/N |

Check on the housekeeping display that the ICU goes to the finding state, and that the following parameters are as given below.

| ICU in finding Y/N |
|------------------------------|
| Vcathode nominal Y/N |
| Vmcp1 nominal Y/N |
| Vmcp23 nominal Y/N |
| Filter wheel on filter 3 Y/N |

Check on the housekeeping display that the ICU goes to the slew state, and that the following parameters are as given below.

ICU in slew Y/N _____ Filter wheel on filter 3 Y/N_____

Check on the housekeeping display that the ICU goes to the PT state, that the three high voltages are set to nominal and that the filter wheel goes to filter 5, and that this configuration continues for 10s.

| ICU in PT Y/N | |
|--------------------------------|---|
| Vcathode nominal Y/N | - |
| Vmcp1 nominal Y/N | _ |
| Vmcp23 nominal Y/N | |
| Filter wheel at filter 5 Y/N | |
| Configuration held for 10s Y/N | |

Check on the housekeeping display that the ICU stays in the PT state, that the three high voltages stay nominal and that the filter wheel goes to filter 6, and that this configuration continues for approximately 15s.

| ICU in PT Y/N | |
|--------------------------------|--|
| Vcathode nominal Y/N | |
| Vmcp1 nominal Y/N | |
| Vmcp23 nominal Y/N | |
| Filter wheel at filter 6 Y/N | |
| Configuration held for 15s Y/N | |

Check on the housekeeping display that the ICU goes to the slew state, and that the following parameters are as given below.

ICU in slew Y/N _____ Filter wheel on filter 6 Y/N_____

Check on the housekeeping display that the ICU goes to the finding state for 100s, and that the following parameters are as given below.

ICU in finding Y/N _____ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel on filter 3 Y/N _____ In finding state for 100s Y/N _____

Check on the housekeeping display that the ICU goes to the AT state, that the three high voltages are set to nominal and that the filter wheel goes to filter 4, and that this configuration continues for 10s.

ICU in AT Y/N _____ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel at filter 4 Y/N _____ Configuration held for 10s Y/N _____

Check on the housekeeping display that the ICU stays in the AT state, that the three high voltages stay nominal and that the filter wheel goes to filter 6, and that this configuration continues for 20s.

ICU in AT Y/N _____ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel at filter 6 Y/N _____ Configuration held for 20s Y/N _____

If all the above responses are Y's then the test is successful.

Test Successful

14.11 Finding state untenable

Set up the celestial environment with Start autumnsafe

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Run the ITOS script if 2.proc with the command Start if2

Check on the housekeeping display that the ICU goes to the idle state.

ICU idle Y/N _____

Check on the housekeeping display that the ICU goes to the slew state, and that the following parameters are as given below.

ICU in slew Y/N _____ Filter wheel blocked Y/N_____

Check on the housekeeping display that the ICU goes to the settling state, and that the following parameters are as given below.

| ICU in settling Y/N |
|------------------------------|
| Vcathode nominal Y/N |
| Vmcp1 nominal Y/N |
| Vmcp23 nominal Y/N |
| Filter wheel on filter 2 Y/N |

Check on the housekeeping display that the ICU goes to the finding state, and that the following parameters are as given below.

| ICU in finding Y/N |
|------------------------------|
| Vcathode nominal Y/N |
| Vmcp1 nominal Y/N |
| Vmcp23 nominal Y/N |
| Filter wheel on filter 3 Y/N |

Check on the housekeeping display that the ICU goes to the slew state, and that the following parameters are as given below.

ICU in slew Y/N _____ Filter wheel on filter 3 Y/N_____

Check on the housekeeping display that the ICU goes to the PT state, that the three high voltages are set to nominal and that the filter wheel goes to filter 5, and that this configuration continues for 10s.

| ICU in PT Y/N | |
|--------------------------------|---|
| Vcathode nominal Y/N | |
| Vmcp1 nominal Y/N | _ |
| Vmcp23 nominal Y/N | _ |
| Filter wheel at filter 5 Y/N | _ |
| Configuration held for 10s Y/N | |

Check on the housekeeping display that the ICU stays in the PT state, that the three high voltages stay nominal and that the filter wheel goes to filter 6, and that this configuration continues for approximately 15s.

| ICU in PT Y/N | |
|--------------------------------|--|
| Vcathode nominal Y/N | |
| Vmcp1 nominal Y/N | |
| Vmcp23 nominal Y/N | |
| Filter wheel at filter 6 Y/N | |
| Configuration held for 15s Y/N | |

Check on the housekeeping display that the ICU goes to the slew state, and that the following parameters are as given below.

ICU in slew Y/N _____ Filter wheel on filter 6 Y/N_____

Check on the housekeeping display that the ICU goes to the finding state, and that the following parameters are as given below.

ICU in finding Y/N ______ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel on filter 3 Y/N _____

Check on the housekeeping display that the ICU goes to the slew state, and that the following parameters are as given below.

ICU in slew Y/N ______ Filter wheel on filter 3 Y/N_____

Check on the housekeeping display that the ICU goes to the PT state, that the three high voltages are set to nominal and that the filter wheel goes to filter 5, and that this configuration continues for 10s.

ICU in PT Y/N _____ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel at filter 5 Y/N _____ Configuration held for 10s Y/N _____

Check on the housekeeping display that the ICU stays in the PT state, that the three high voltages stay nominal and that the filter wheel goes to filter 6, and that this configuration continues for approximately 15s.

| ICU in PT Y/N | |
|---------------------------------|--|
| Vcathode nominal Y/N | |
| Vmcp1 nominal Y/N | |
| Vmcp23 nominal Y/N | |
| Filter wheel at filter 6 Y/N | |
| Configuration held for 15s Y/N_ | |

Check on the housekeeping display that the ICU goes to the slew state, and that the following parameters are as given below.

ICU in slew Y/N _____ Filter wheel on filter 6 Y/N_____

Check on the housekeeping display that the ICU goes to the AT state, that the three high voltages are set to nominal and that the filter wheel goes to filter 4, and that this configuration continues for 10s.

ICU in AT Y/N _____ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel at filter 4 Y/N _____ Configuration held for 10s Y/N ____

Check on the housekeeping display that the ICU stays in the AT state, that the three high voltages stay nominal and that the filter wheel goes to filter 6, and that this configuration continues for approximately 15s.

ICU in AT Y/N _____ Vcathode nominal Y/N _____

Vmcp1 nominal Y/N_____ Vmcp23 nominal Y/N _____ Filter wheel at filter 6 Y/N____ Configuration held for 15s Y/N____

Check on the housekeeping display that the ICU goes to the slew state, and that the following parameters are as given below.

ICU in slew Y/N _____ Filter wheel on filter 6 Y/N_____

Check on the housekeeping display that the ICU goes to the PT state, that the three high voltages are set to nominal and that the filter wheel goes to filter 5, and that this configuration continues for 10s.

| ICU in PT Y/N | _ |
|--------------------------------|---|
| Vcathode nominal Y/N | _ |
| Vmcp1 nominal Y/N | |
| Vmcp23 nominal Y/N | |
| Filter wheel at filter 5 Y/N | |
| Configuration held for 10s Y/N | |

Check on the housekeeping display that the ICU stays in the PT state, that the three high voltages stay nominal and that the filter wheel goes to filter 6, and that this configuration continues for approximately 15s.

| ICU in PT Y/N | |
|--------------------------------|---|
| Vcathode nominal Y/N | |
| Vmcp1 nominal Y/N | |
| Vmcp23 nominal Y/N | |
| Filter wheel at filter 6 Y/N | |
| Configuration held for 15s Y/N | _ |

Check on the housekeeping display that the ICU goes to the slew state, and that the following parameters are as given below.

ICU in slew Y/N _____ Filter wheel on filter 6 Y/N_____

Check on the housekeeping display that the ICU goes to the AT state, that the three high voltages are set to nominal and that the filter wheel goes to filter 7, and that this configuration continues for 10s.

ICU in AT Y/N _____ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____

Vmcp23 nominal Y/N _____ Filter wheel at filter 7 Y/N_____ Configuration held for 10s Y/N_____

Check on the housekeeping display that the ICU stays in the AT state, that the three high voltages stay nominal and that the filter wheel goes to filter 9, and that this configuration continues for 10s.

ICU in AT Y/N _____ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel at filter 9 Y/N _____ Configuration held for 10s Y/N _____

If all the above responses are Y's then the test is successful.

Test Successful

14.12 A PT interrupted by an AT

Set up the celestial environment with Start autumnsafe

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Run the ITOS script ptatpt.proc with the command Start ptatpt

Check on the housekeeping display that the ICU goes to the idle state.

ICU idle Y/N _____

Check on the housekeeping display that the ICU goes through the slew state to the PT state, that the three high voltages are set to nominal and that the filter wheel goes to filter 5.

ICU in PT Y/N _____ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel at filter 5 Y/N _____ Configuration held for 10s Y/N _____

Check on the housekeeping display that the ICU then goes through a slew to the AT state.

ICU in AT Y/N _____

Check on the housekeeping display that the ICU then goes through a slew back to the PT state, that the three high voltages again become nominal and that the filter wheel goes to filter 6, and that this configuration continues for 20s, i.e the PT restarts at the point of interruption

| ICU in PT Y/N | _ |
|--------------------------------|---|
| Vcathode nominal Y/N | _ |
| Vmcp1 nominal Y/N | |
| Vmcp23 nominal Y/N | |
| Filter wheel at filter 6 Y/N | |
| Configuration held for 20s Y/N | |

Check on the housekeeping display that the ICU stays in the PT state, that the three high voltages stay nominal and that the filter wheel goes to filter 7, and that this configuration continues for 30s.

ICU in PT Y/N _____ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel at filter 7 Y/N _____ Configuration held for 30s Y/N _____

Check on the housekeeping display that the ICU goes to the idle state, that the three high voltages stay nominal and that the filter wheel goes to blocked.

ICU in PT Y/N ______ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel blocked Y/N _____

If all the above responses are Y's then the test is successful.

Test Successful

14.13 Safehold

Load flight code icu.hex.

Command the ICU to the idle state /istate state=idle

Alter the spacecraft simulator ACS messages so that the 'safehold' flag is set.

Make sure that the ICU safes itself.

ICU goes to safe state Y/N_____

If the above response is Y then the test is successful.

Test Successful

15. BRIGHT SOURCE AVOIDANCE

15.1 Requested AT with Sun in field of view.

Set up the celestial environment with Start springsun

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Run the ITOS script atsun.proc with the command ${\tt Start}$ ${\tt atsun}$

Check on the housekeeping display that the ICU goes to the idle state.

ICU idle Y/N _____

Also check on the housekeeping display that the sun constraint is OK and the sun angular distance is approximately 60.

Sun constraint OK Y/N_____ Sun angular distance 60 Y/N_____

Watching the proc and NHK displays, note the time between the FONEXTOBSINFO command and the 'Bright Star Present' NHK (see below) appearing. This should be 5s or less.

Warning interval less than or equal to 5s Y/N_____

Check on the housekeeping display that the ICU goes to the slew state, and that the following parameters are as given below.

ICU in slew Y/N ______ Filter wheel blocked Y/N ______

Check on the housekeeping display that the ICU goes to the idle state, and that the following parameters are as given below.

ICU idle Y/N _____ Vcathode off Y/N _____ Vmcp1 at 70% of nominal Y/N____

Vmcp23 at 70% of nominal Y/N _____ Filter wheel blocked Y/N_____

Also check on the housekeeping display that the sun constraint is CLOSE and the sun angular distance is approximately 40.

Sun constraint CLOSE Y/N_____ Sun angular distance 40 Y/N_____

Check on the NHK display that a 'Bright Planet Present' message has been received, with its second parameter set to 8.

'Bright Planet Present' received Y/N_____ Second parameter set to 8 Y/N_____

Upload a new avoidance angles table, where all avoidance angles are set to zero. Load ???.img

Run the ITOS script atsun.proc with the command $\ensuremath{\mathsf{Start}}$ atsun

Check on the housekeeping display that the ICU goes to the slew state, followed by the settling state.

ICU in slew Y/N_____ ICU in settling Y/N_____

Check on the NHK display that no 'Bright Planet Present' message has been received.

'Bright Planet Present' received Y/N_____

Upload the original avoidance angle table.

If all the above responses except the last are Y's and the last is a N then the test is successful.

Test Successful

15.2 Requested AT with Earth in field of view

Set up the celestial environment with Start springearth

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Also check on the housekeeping display that the earth constraint is OK and the earth angular distance is approximately 100.

Earth constraint OK Y/N_____ Earth angular distance 100 Y/N_____

Run the ITOS script attearth.proc with the command $\ensuremath{\mathsf{Start}}$ attearth

Check on the housekeeping display that the ICU goes to the idle state.

ICU idle Y/N _____

Check on the housekeeping display that the ICU goes to the slew state, and that the following parameters are as given below.

ICU in slew Y/N _____ Filter wheel blocked Y/N_____

Check on the housekeeping display that the ICU goes to the idle state, and that the following parameters are as given below.

ICU idle Y/N _____ Vcathode off Y/N _____ Vmcp1 at 70% of nominal Y/N ____ Vmcp23 at 70% of nominal Y/N ____ Filter wheel blocked Y/N _____

Also check on the housekeeping display that the earth constraint is CLOSE and the earth angular distance is approximately 90.

Earth constraint CLOSE Y/N_____ Earth angular distance 90 Y/N_____

Upload a new avoidance angles table, where all avoidance angles are set to zero. Load ???.img

Run the ITOS script atearth.proc with the command ${\tt Start}$ atearth

Check on the housekeeping display that the ICU goes to the slew state, followed by the settling state, and that the Earth constraint is always OK.

ICU in slew Y/N_____ ICU in settling Y/N_____ Earth constraint OK Y/N_____

Upload the original avoidance angle table.

If all the above responses are Y's then the test is successful.

Test Successful

15.3 Requested AT with Moon in field of view

Set up the celestial environment with Start autumnmoon

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Also check on the housekeeping display that the moon constraint is OK and the moon angular distance is approximately 62.

Moon constraint OK Y/N_____ Moon angular distance 62 Y/N_____

Run the ITOS script atmoon.proc with the command Start atmoon

Check on the housekeeping display that the ICU goes to the idle state.

ICU idle Y/N _____

Check on the housekeeping display that the ICU goes to the slew state, and that the following parameters are as given below.

ICU in slew Y/N _____ Filter wheel blocked Y/N_____

Check on the housekeeping display that the ICU goes to the idle state, and that the following parameters are as given below.

ICU idle Y/N ______ Vcathode off Y/N _____ Vmcp1 at 70% of nominal Y/N _____ Vmcp23 at 70% of nominal Y/N ____ Filter wheel blocked Y/N _____

Also check on the housekeeping display that the moon constraint is CLOSE and the moon angular distance is approximately 29.

Moon constraint CLOSE Y/N_____ Moon angular distance 29 Y/N_____

Check on the NHK display that a 'Bright Planet Present' message has been received, with its second parameter set to 9.

'Bright Planet Present' received Y/N_____ Second parameter set to 9 Y/N_____

Upload a new avoidance angles table, where all avoidance angles are set to zero. Load ???.img

Run the ITOS script atmoon.proc with the command $\ensuremath{\mathsf{Start}}$ atmoon

Check on the housekeeping display that the ICU goes to the slew state, followed by the settling state.

ICU in slew Y/N_____ ICU in settling Y/N_____

Check on the NHK display that no 'Bright Planet Present' message has been received.

'Bright Planet Present' received Y/N_____

Upload the original avoidance angle table.

If all the above responses except the last are Y's and the last is N then the test is successful.

Test Successful

15.4 Requested AT with a planet in the field of view

Set up the celestial environment with Start springjupiter

Load flight code icu.hex.

Enable a full dump of the RTS's run with the command / iDCSTraceEnable On

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Run the ITOS script atplanet.proc with the command Start atplanet

Check on the housekeeping display that the ICU goes to the idle state.

ICU idle Y/N _____

Check on the housekeeping display that the ICU goes to the slew state, and that the following parameters are as given below.

ICU in slew Y/N _____ Filter wheel blocked Y/N_____

Check on the housekeeping display that the ICU goes to the idle state, and that the following parameters are as given below.

ICU idle Y/N _____ Vcathode off Y/N _____ Vmcp1 at 70% of nominal Y/N ____ Vmcp23 at 70% of nominal Y/N ____ Filter wheel blocked Y/N _____

Check on the NHK display that a 'Bright Planet Present' message has been received, with its first parameter set to 3.

'Bright Planet Present' received Y/N_____ First parameter set to 3 Y/N_____

Check from the RTS trace that the planet locater was accessed and returned its values within 1s.

Planet locater returned within 1s Y/N_____

Disable the full dump of the RTS's run with the command /iDCSTraceEnable Off

Upload a new avoidance angles table, where all avoidance angles are set to zero. Load ???.img

Run the ITOS script atplanet.proc with the command Start atplanet

Check on the housekeeping display that the ICU goes to the slew state, followed by the settling state.

ICU in slew Y/N_____ ICU in settling Y/N_____

Check on the NHK display that no 'Bright Planet Present' message has been received.

'Bright Planet Present' received Y/N_____

Upload the original avoidance angle table.

If all the above responses except the last are Y's, and the last is a N, then the test is successful.

Test Successful

15.5 Requested AT with a bright star in the field of view

Set up the celestial environment with Start springcanopus

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Run the ITOS script atstar.proc with the command $\ensuremath{\mathsf{Start}}$ at star

Check on the housekeeping display that the ICU goes to the idle state.

ICU idle Y/N _____

Check on the housekeeping display that the ICU goes to the slew state, and that the following parameters are as given below.

ICU in slew Y/N _____ Filter wheel blocked Y/N_____

Check on the housekeeping display that the ICU goes to the idle state, and that the following parameters are as given below.

ICU idle Y/N _____ Vcathode off Y/N _____ Vmcp1 at 70% of nominal Y/N ____ Vmcp23 at 70% of nominal Y/N ____ Filter wheel blocked Y/N_____

Check on the NHK display that a 'Bright Star Present' message has been received.

'Bright Star Present' received Y/N_____

Upload a new avoidance angles table, where all avoidance angles are set to zero. Load ???.img

Run the ITOS script atstar.proc with the command Start atstar

Check on the housekeeping display that the ICU goes to the slew state, followed by the settling state.

ICU in slew Y/N_____ ICU in settling Y/N_____

Check on the NHK display that no 'Bright Star Present' message has been received.

'Bright Star Present' received Y/N_____

Upload the original avoidance angle table.

If all the above responses except the last are Y's and the last is N then the test is successful.

Test Successful

15.6 AT exposure shortened due to presence of dim stars

Set up the celestial environment with (and this isn't a misprint) Start springcanopus

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Run the ITOS script at short.proc with the command $\ensuremath{\mathsf{Start}}$ at short

Check on the housekeeping display that the ICU goes to the idle state.

ICU idle Y/N _____

Check on the housekeeping display that the ICU goes to the slew, settling and finding states.

ICU in slew Y/N ______ ICU in settling Y/N_____ ICU in finding Y/N_____

Check on the housekeeping display that the ICU goes to the AT state, that the three high voltages are set to nominal and that the filter wheel goes to filter ???, and that this configuration continues for ???s.

| ICU in AT Y/N | |
|---------------------------------|---|
| Vcathode nominal Y/N | |
| Vmcp1 nominal Y/N | _ |
| Vmcp23 nominal Y/N | _ |
| Filter wheel at filter ??? Y/N | |
| Configuration held for ???s Y/N | |

Check on the housekeeping display that the ICU stays in the AT state, that the three high voltages stay nominal and that the filter wheel goes to filter ???, and that this configuration continues for ???s.

| ICU in AT Y/N |
|----------------------|
| Vcathode nominal Y/N |
| Vmcp1 nominal Y/N |
| Vmcp23 nominal Y/N |

Filter wheel at filter ??? Y/N_____ Configuration held for ???s Y/N_____

Check on the housekeeping display that the ICU stays in the AT state, that the three high voltages stay nominal and that the filter wheel goes to filter ???, and that this configuration continues for ???s.

| ICU in AT Y/N | |
|----------------------------------|--|
| Vcathode nominal Y/N | |
| Vmcp1 nominal Y/N | |
| Vmcp23 nominal Y/N | |
| Filter wheel at filter ??? Y/N | |
| Configuration held for ???s Y/N_ | |

Check on the NHK display that the messages 'Too Many Accumulated Counts', 'No Useable Filters in Config', 'Reducing Requested Exp Time' and 'UVOT Mode Exhausted' messages have been received.

| 'Too Many Accumulated Counts' received Y/N |
|---|
| 'No Useable Filters in Config' received Y/N |
| 'Reducing Requested Exposure' received Y/N |
| 'UVOT Mode Exhausted' received Y/N |

If all the above responses are Y's then the test is successful.

Test Successful

15.7 Requested PT with Sun in field of view.

Set up the celestial environment with Start springsun

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Also check on the housekeeping display that the sun constraint is OK and the sun angular distance is approximately 60.

Sun constraint OK Y/N_____ Sun angular distance 60 Y/N_____

Run the ITOS script ptsun.proc with the command Start ptsun

Check on the housekeeping display that the ICU goes to the idle state.

ICU idle Y/N _____

Check on the housekeeping display that the ICU goes to the slew state, and that the following parameters are as given below.

ICU in slew Y/N _____ Filter wheel blocked Y/N_____

Check on the housekeeping display that the ICU goes to the idle state, and that the following parameters are as given below.

ICU idle Y/N _____ Vcathode off Y/N _____ Vmcp1 at 70% of nominal Y/N ____ Vmcp23 at 70% of nominal Y/N ____ Filter wheel blocked Y/N _____

Also check on the housekeeping display that the sun constraint is CLOSE and the sun angular distance is approximately 40.

Sun constraint CLOSE Y/N_____ Sun angular distance 40 Y/N_____

Check on the NHK display that a 'Bright Planet Present' message has been received, with its second parameter set to 8.

| 'Bright Planet Present' received Y/N | |
|--------------------------------------|--|
| Second parameter set to 8 Y/N | |

If all the above responses are Y's then the test is successful.

Test Successful

15.8 Requested PT with Earth in field of view

Set up the celestial environment with Start springearth

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Also check on the housekeeping display that the earth constraint is OK and the earth angular distance is approximately 100.

Earth constraint OK Y/N_____ Earth angular distance 100 Y/N_____

Run the ITOS script ptearth.proc with the command Start ptearth

Check on the housekeeping display that the ICU goes to the idle state.

ICU idle Y/N _____

Check on the housekeeping display that the ICU goes to the slew state, and that the following parameters are as given below.

ICU in slew Y/N _____ Filter wheel blocked Y/N_____

Check on the housekeeping display that the ICU goes to the idle state, and that the following parameters are as given below.

ICU idle Y/N _____ Vcathode off Y/N _____ Vmcp1 at 70% of nominal Y/N ____ Vmcp23 at 70% of nominal Y/N ____ Filter wheel blocked Y/N_____

Also check on the housekeeping display that the earth constraint is CLOSE and the earth angular distance is approximately 90.

Earth constraint CLOSE Y/N_____ Earth angular distance 90 Y/N_____

If all the above responses are Y's then the test is successful.

Test Successful

15.9 Requested PT with Moon in field of view

Set up the celestial environment with Start autumnmoon

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Also check on the housekeeping display that the moon constraint is OK and the moon angular distance is approximately 62.

Moon constraint OK Y/N_____ Moon angular distance 62 Y/N_____

Run the ITOS script ptmoon.proc with the command Start ptmoon

Check on the housekeeping display that the ICU goes to the idle state.

ICU idle Y/N _____

Check on the housekeeping display that the ICU goes to the slew state, and that the following parameters are as given below.

ICU in slew Y/N _____ Filter wheel blocked Y/N_____

Check on the housekeeping display that the ICU goes to the idle state, and that the following parameters are as given below.

ICU idle Y/N ______ Vcathode off Y/N _____ Vmcp1 at 70% of nominal Y/N ____ Vmcp23 at 70% of nominal Y/N ____ Filter wheel blocked Y/N _____

Also check on the housekeeping display that the moon constraint is CLOSE and the moon angular distance is approximately 29.

Moon constraint CLOSE Y/N_____ Moon angular distance 29 Y/N_____

Check on the NHK display that a 'Bright Planet Present' message has been received, with its second parameter set to 9.

| 'Bright Planet Present' received Y/N | |
|--------------------------------------|--|
| Second parameter set to 9 Y/N | |

If all the above responses are Y's then the test is successful.

Test Successful

15.10 Requested PT with a planet in the field of view

Set up the celestial environment with Start springjupiter

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Run the ITOS script ptplanet.proc with the command $\ensuremath{\mathsf{Start}}$ ptplanet

Check on the housekeeping display that the ICU goes to the idle state.

ICU idle Y/N _____

Check on the housekeeping display that the ICU goes to the slew state, and that the following parameters are as given below.

ICU in slew Y/N _____ Filter wheel blocked Y/N_____

Check on the housekeeping display that the ICU goes to the idle state, and that the following parameters are as given below.

ICU idle Y/N _____ Vcathode off Y/N _____ Vmcp1 at 70% of nominal Y/N ____ Vmcp23 at 70% of nominal Y/N ____ Filter wheel blocked Y/N _____

Check on the NHK display that a 'Bright Planet Present' message has been received, with its first parameter set to 3.

'Bright Planet Present' received Y/N_____ First parameter set to 3 Y/N_____

If all the above responses are Y's then the test is successful.

Test Successful

15.11 Requested PT with a bright star in the field of view

Set up the celestial environment with Start springcanopus

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Run the ITOS script ptstar.proc with the command $\ensuremath{\mathsf{Start}}$ ptstar

Check on the housekeeping display that the ICU goes to the idle state.

ICU idle Y/N _____

Check on the housekeeping display that the ICU goes to the slew state, and that the following parameters are as given below.

ICU in slew Y/N _____ Filter wheel blocked Y/N_____

Check on the housekeeping display that the ICU goes to the idle state, and that the following parameters are as given below.

ICU idle Y/N _____ Vcathode off Y/N _____ Vmcp1 at 70% of nominal Y/N ____ Vmcp23 at 70% of nominal Y/N ____ Filter wheel blocked Y/N _____

Check on the NHK display that a 'Bright Star Present' message has been received.

'Bright Star Present' received Y/N_____

If all the above responses are Y's then the test is successful.

|--|

15.12 PT exposure shortened due to presence of dim stars

Set up the celestial environment with (and this is not a misprint) Start springcanopus

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Run the ITOS script ptshort.proc with the command Start ptshort

Check on the housekeeping display that the ICU goes to the idle state.

ICU idle Y/N _____

Check on the housekeeping display that the ICU goes to the slew state, and that the following parameters are as given below.

ICU in slew Y/N _____ Filter wheel blocked Y/N_____

Check on the housekeeping display that the ICU goes to the PT state, that the three high voltages are set to nominal and that the filter wheel goes to filter 5, and that this configuration continues for ???s.

| ICU in PT Y/N | |
|---------------------------------|---|
| Vcathode nominal Y/N | |
| Vmcp1 nominal Y/N | |
| Vmcp23 nominal Y/N | _ |
| Filter wheel at filter 5 Y/N | _ |
| Configuration held for ???s Y/N | |

Check on the housekeeping display that the ICU stays in the PT state, that the three high voltages stay nominal and that the filter wheel goes to filter 6, and that this configuration continues for ???s.

| ICU in PT Y/N |
|------------------------------|
| Vcathode nominal Y/N |
| Vmcp1 nominal Y/N |
| Vmcp23 nominal Y/N |
| Filter wheel at filter 6 Y/N |

Configuration held for ???s Y/N_____

Check on the housekeeping display that the ICU stays in the PT state, that the three high voltages stay nominal and that the filter wheel goes to filter 7, and that this configuration continues for ???s.

ICU in PT Y/N ______ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel at filter 7 Y/N _____ Configuration held for ???s Y/N _____

Check on the NHK display that the messages 'Too Many Accumulated Counts', 'No Useable Filters in Config', 'Reducing Requested Exp Time' and 'UVOT Mode Exhausted' messages have been received.

'Too Many Accumulated Counts' received Y/N_____
'No Useable Filters in Config' received Y/N_____
'Reducing Requested Exposure' received Y/N_____
'UVOT Mode Exhausted' received Y/N_____

If all the above responses are Y's then the test is successful.

Test Successful

15.13 Several bright stars in the field of view

Set up the celestial environment with Start autumnsafe

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Run the ITOS script threebright.proc with the command Start threebright

Check on the housekeeping display that the ICU goes to the idle state.

ICU idle Y/N _____

Check on the housekeeping display that the ICU goes to the slew state, and that the following parameters are as given below.

ICU in slew Y/N _____ Filter wheel blocked Y/N_____

Check on the housekeeping display that the ICU goes to the idle state, and that the following parameters are as given below.

ICU idle Y/N _____ Vcathode off Y/N _____ Vmcp1 at 70% of nominal Y/N ____ Vmcp23 at 70% of nominal Y/N ____ Filter wheel blocked Y/N_____

Check on the ICU Events display that three 'Bright Star Report' messages have been received.

Three 'Bright Star Report' messages received Y/N_____

If all the above responses are Y's then the test is successful.

15.14 Drift towards Sun, Moon or Earth

Set up the celestial environment with Start autumnsafe

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Command the ICU to the idle state with /iState State=idle

Check on the housekeeping display that the ICU goes to the idle state.

ICU idle Y/N _____

Change the ACS message on whichever simulator is available to move the Sun to just within the Sun avoidance angle.

Check on the housekeeping display that the ICU goes to the safe state.

ICU safe Y/N _____

Command the ICU to the idle state with /iState State=idle

Check on the housekeeping display that the ICU goes to the idle state.

ICU idle Y/N _____

Change the ACS message on whichever simulator is available to move the Moon to just within the Moon avoidance angle.

Check on the housekeeping display that the ICU goes to the safe state.

ICU safe Y/N _____

Command the ICU to the idle state with /iState State=idle

Check on the housekeeping display that the ICU goes to the idle state.

ICU idle Y/N _____

Change the ACS message on whichever simulator is available to move the Earth to just within the Earth avoidance angle.

Check on the housekeeping display that the ICU goes to the safe state.

ICU safe Y/N _____

If all the above responses are Y's then the test is successful.

Test Successful

16. STATE CHANGES INVOLVING THE SAA

16.1 Safe to idle transition in the SAA

Load flight code icu.hex.

Check that the following parameters on the housekeeping display are as given below.

ICU state safe Y/N _____ Vcathode off Y/N _____ Vmcp1 off Y/N _____ Vmcp23 off Y/N _____ Filter wheel blocked Y/N _____

Set the SAA flag high using Start saaon

Check on the SCACS display that the SAA flag is high

SAA flag set Y/N_____

Send the command /istate state=idle

Check that the following parameters on the housekeeping display are as given below.

ICU state SAA Y/N ______ Vcathode off Y/N ______ Vmcp1 at 70% of nominal Y/N _____ Vmcp23 at 70% of nominal Y/N _____ Filter wheel blocked Y/N _____

Check on the NHK display that a 'Centroid Table Load OK' message and a 'Window Table Load OK' message have been received.

'Centroid Table Load OK' received Y/N______ 'Window Table Load OK' received Y/N______

If all the above responses are Y's then the test is successful.

Test Successful

16.2 Entering and exiting SAA during slew

NB: This test also checks on the ability of the code to handle a boundary condition, in that the SAA flag is set for the first time in the same ACS message as the is_settled flag becomes false at the start of the slew.

Set up the celestial environment with Start autumnsafe

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Run the ITOS script slewio.proc with the command Start slewio

Check on the housekeeping display that the ICU goes to the idle state.

ICU idle Y/N _____

Check on the housekeeping display that the ICU goes to the slew state, and that the following parameters are as given below.

ICU in slew Y/N ______ Filter wheel blocked Y/N______

Check on the housekeeping display that the ICU goes to the slewSAA state, and that the following parameters are as given below.

ICU in slewSAA Y/N _____ Vcathode stays where it was at point of interruption Y/N _____ Vmcp1 stays where it was at point of interruption Y/N _____ Vmcp23 stays where it was at point of interruption Y/N _____ Filter wheel blocked Y/N

Check on the NHK display that a 'State Transition Complete' message has been received.

'State Transition Complete' received Y/N_____

Check on the housekeeping display that the ICU goes to the slew state, and that the following parameters are as given below.

ICU in slew Y/N _____ Filter wheel blocked Y/N_____

If all the above responses are Y's then the test is successful.

Test Successful

16.3 Starting the slew while in the SAA and exiting it during slew

Set up the celestial environment with Start autumnsafe

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Run the ITOS script slewo.proc with the command Start slewo

Check on the housekeeping display that the ICU goes to the idle state.

ICU idle Y/N _____

Check on the housekeeping display that the ICU goes to the SAA state, and that the following parameters are as given below.

ICU in SAA Y/N _____ Vcathode off Y/N _____ Vmcp1 at 70% of nominal Y/N ____ Vmcp23 at 70% of nominal Y/N ____ Filter wheel blocked Y/N_____

Check on the housekeeping display that the ICU goes to the slewSAA state, and that the following parameters are as given below.

ICU in slewSAA Y/N _____ Vcathode off Y/N _____ Vmcp1 at 70% of nominal Y/N ____ Vmcp23 at 70% of nominal Y/N ____ Filter wheel blocked Y/N_____

Check on the housekeeping display that the ICU goes to the slew state, and that the following parameters are as given below.

ICU in slew Y/N _____ Filter wheel blocked Y/N_____

If all the above responses are Y's then the test is successful.

Test Successful

16.4 Entering the SAA while slewing and exiting it in the settling state

Set up the celestial environment with Start autumnsafe

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state,.

ICU safe Y/N _____

Run the ITOS script setto.proc with the command ${\tt Start \ setto}$

Check on the housekeeping display that the ICU goes to the idle state.

ICU idle Y/N _____

Check on the housekeeping display that the ICU goes to the SAA state, and that the following parameters are as given below.

ICU in SAA Y/N ______ Vcathode off Y/N _____ Vmcp1 at 70% of nominal Y/N _____ Vmcp23 at 70% of nominal Y/N ____ Filter wheel blocked Y/N _____

Check on the housekeeping display that the ICU goes to the slewSAA state, and that the following parameters are as given below.

| ICU in slewSAA Y/N | |
|------------------------------|--|
| Vcathode off Y/N | |
| Vmcp1 at 70% of nominal Y/N | |
| Vmcp23 at 70% of nominal Y/N | |
| Filter wheel blocked Y/N | |

Check on the housekeeping display that the ICU goes to the SAA state, and that the following parameters are as given below.

| ICU in SAA Y/N | |
|------------------------------|--|
| Vcathode off Y/N | |
| Vmcp1 at 70% of nominal Y/N | |
| Vmcp23 at 70% of nominal Y/N | |
| Filter wheel blocked Y/N | |

Check on the housekeeping display that the ICU goes to the settling state, and that the following parameters are as given below.

ICU in settling Y/N ______ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel at filter 2 Y/N _____

If all the above responses are Y's then the test is successful.

Test Successful

16.5 Entering and exiting the SAA in the settling state

Set up the celestial environment with Start autumnsafe

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Run the ITOS script settio.proc with the command $\ensuremath{\mathsf{Start}}$ settio

Check on the housekeeping display that the ICU goes to the idle state.

ICU idle Y/N _____

Check on the housekeeping display that the ICU goes to the slew state, and that the following parameters are as given below.

ICU in slew Y/N _____ Filter wheel blocked Y/N_____

Check on the housekeeping display that the ICU goes to the settling state, and that the following parameters are as given below.

| ICU in settling Y/N | |
|------------------------------|---|
| Vcathode nominal Y/N | _ |
| Vmcp1 nominal Y/N | _ |
| Vmcp23 nominal Y/N | _ |
| Filter wheel at filter 2 Y/N | |

Check on the housekeeping display that the ICU goes to the SAA state, and that the following parameters are as given below.

| ICU in SAA Y/N | |
|------------------------------|--|
| Vcathode off Y/N | |
| Vmcp1 at 70% of nominal Y/N | |
| Vmcp23 at 70% of nominal Y/N | |
| Filter wheel at filter 2 Y/N | |

Check on the housekeeping display that the ICU goes to the settling state, and that the following parameters are as given below.

ICU in settling Y/N _____ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel at filter 2 Y/N _____

If all the above responses are Y's then the test is successful.

Test Successful

16.6 Entering and exiting the SAA in the finding state

Set up the celestial environment with Start autumnsafe

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Run the ITOS script findio.proc with the command $\ensuremath{\mathsf{Start}}$ findio

Check on the housekeeping display that the ICU goes to the idle state.

ICU idle Y/N _____

Check on the housekeeping display that the ICU goes to the slew state, and that the following parameters are as given below.

ICU in slew Y/N _____ Filter wheel blocked Y/N_____

Check on the housekeeping display that the ICU goes to the settling state, and that the following parameters are as given below.

| ICU in settling Y/N | _ |
|------------------------------|---|
| Vcathode nominal Y/N | |
| Vmcp1 nominal Y/N | |
| Vmcp23 nominal Y/N | |
| Filter wheel at filter 2 Y/N | |

Check on the housekeeping display that the ICU goes to the finding state, and that the following parameters are as given below.

| ICU in finding Y/N |
|------------------------------|
| Vcathode nominal Y/N |
| Vmcp1 nominal Y/N |
| Vmcp23 nominal Y/N |
| Filter wheel at filter 3 Y/N |

Check on the housekeeping display that the ICU goes to the SAA state, and that the following parameters are as given below.

ICU in SAA Y/N ______ Vcathode off Y/N _____ Vmcp1 at 70% of nominal Y/N _____ Vmcp23 at 70% of nominal Y/N ____ Filter wheel at filter 3 Y/N _____

Check on the housekeeping display that the ICU goes to the finding state, and that the following parameters are as given below.

ICU in finding Y/N ______ Vcathode nominal Y/N ______ Vmcp1 nominal Y/N ______ Vmcp23 nominal Y/N ______ Filter wheel at filter 3 Y/N ______

If all the above responses are Y's then the test is successful.

Test Successful

16.7 Staying a long time in the SAA in the finding state

Set up the celestial environment with Start autumnsafe

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Run the ITOS script getretry.proc with the command Start getretry

Check on the housekeeping display that the ICU goes to the idle state.

ICU idle Y/N _____

Check on the housekeeping display that the ICU goes to the slew state, and that the following parameters are as given below.

ICU in slew Y/N _____ Filter wheel blocked Y/N_____

Check on the housekeeping display that the ICU goes to the settling state, and that the following parameters are as given below.

| ICU in settling Y/N | _ |
|------------------------------|---|
| Vcathode nominal Y/N | |
| Vmcp1 nominal Y/N | |
| Vmcp23 nominal Y/N | |
| Filter wheel at filter 2 Y/N | |

Check on the housekeeping display that the ICU goes to the finding state, and that the following parameters are as given below.

| ICU in finding Y/N |
|------------------------------|
| Vcathode nominal Y/N |
| Vmcp1 nominal Y/N |
| Vmcp23 nominal Y/N |
| Filter wheel at filter 3 Y/N |

Check on the housekeeping display that the ICU goes to the SAA state, and that the following parameters are as given below.

ICU in SAA Y/N _____ Vcathode off Y/N _____ Vmcp1 at 70% of nominal Y/N _____ Vmcp23 at 70% of nominal Y/N ____ Filter wheel at filter 3 Y/N _____

Check on the housekeeping display that the ICU goes to the finding state, and that the following parameters are as given below.

ICU in finding Y/N ______ Vcathode nominal Y/N ______ Vmcp1 nominal Y/N ______ Vmcp23 nominal Y/N ______ Filter wheel at filter 3 Y/N ______

If all the above responses are Y's then the test is successful.

Test Successful

16.8 Entering the SAA during slew and leaving it in the finding state

Set up the celestial environment with Start autumnsafe

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Run the ITOS script slewifindo.proc with the command Start slewifindo

Check on the housekeeping display that the ICU goes to the idle state.

ICU idle Y/N _____

Check on the housekeeping display that the ICU goes to the slew state, and that the following parameters are as given below.

ICU in slew Y/N _____ Filter wheel blocked Y/N_____

Check on the housekeeping display that the ICU goes to the slewSAA state, and that the following parameters are as given below.

ICU in slewSAA Y/N _____ Vcathode off Y/N _____ Vmcp1 at 70% of nominal Y/N _____ Vmcp23 at 70% of nominal Y/N ____ Filter wheel blocked Y/N _____

Check on the housekeeping display that the ICU goes to the SAA state, and that the following parameters are as given below.

| ICU in SAA Y/N | |
|------------------------------|--|
| Vcathode off Y/N | |
| Vmcp1 at 70% of nominal Y/N | |
| Vmcp23 at 70% of nominal Y/N | |
| Filter wheel blocked Y/N | |

Check on the housekeeping display that the ICU goes to the finding state, and that the following parameters are as given below.

ICU in finding Y/N _____ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel at filter 3 Y/N _____

If all the above responses are Y's then the test is successful.

Test Successful

16.9 Entering the SAA in the settling state and exiting it in the finding state

Set up the celestial environment with Start autumnsafe

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Run the ITOS script settifindo.proc with the command $\ensuremath{\mathsf{Start}}$ settifindo

Check on the housekeeping display that the ICU goes to the idle state.

ICU idle Y/N _____

Check on the housekeeping display that the ICU goes to the slew state, and that the following parameters are as given below.

ICU in slew Y/N _____ Filter wheel blocked Y/N_____

Check on the housekeeping display that the ICU goes to the settling state, and that the following parameters are as given below.

| ICU in settling Y/N |
|------------------------------|
| Vcathode nominal Y/N |
| Vmcp1 nominal Y/N |
| Vmcp23 nominal Y/N |
| Filter wheel at filter 2 Y/N |

Check on the housekeeping display that the ICU goes to the SAA state, and that the following parameters are as given below.

| ICU in SAA Y/N | |
|------------------------------|--|
| Vcathode off Y/N | |
| Vmcp1 at 70% of nominal Y/N | |
| Vmcp23 at 70% of nominal Y/N | |
| Filter wheel at filter 2 Y/N | |

Check on the housekeeping display that the ICU goes to the finding state, and that the following parameters are as given below.

ICU in finding Y/N _____ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel at filter 3 Y/N _____

If all the above responses are Y's then the test is successful.

Test Successful

16.10 Entering and exiting the SAA during an AT exposure

Set up the celestial environment with Start autumnsafe

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Run the ITOS script atio.proc with the command $\ensuremath{\mathsf{Start}}$ atio

Check on the housekeeping display that the ICU goes to the idle state.

ICU idle Y/N _____

Check on the housekeeping display that the ICU goes to the slew state, and that the following parameters are as given below.

ICU in slew Y/N _____ Filter wheel blocked Y/N_____

Check on the housekeeping display that the ICU goes to the settling state, and that the following parameters are as given below.

| ICU in settling Y/N | |
|------------------------------|--|
| Vcathode nominal Y/N | |
| Vmcp1 nominal Y/N | |
| Vmcp23 nominal Y/N | |
| Filter wheel on filter 2 Y/N | |

Check on the housekeeping display that the ICU goes to the finding state, and that the following parameters are as given below.

| ICU in finding Y/N |
|------------------------------|
| Vcathode nominal Y/N |
| Vmcp1 nominal Y/N |
| Vmcp23 nominal Y/N |
| Filter wheel on filter 3 Y/N |

Check on the housekeeping display that the ICU goes to the AT state, and that the following parameters are as given below.

ICU in AT Y/N _____ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel at filter 4 Y/N _____ Stays in this configuration for 10s Y/N _____

Check on the housekeeping display that the ICU goes to the AT state, and that the following parameters are as given below.

ICU in AT Y/N _____ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel at filter 6 Y/N _____ Stays in this configuration for 15s Y/N _____

Check on the housekeeping display that the ICU goes to the SAA state, and that the following parameters are as given below.

ICU in SAA Y/N _____ Vcathode off Y/N _____ Vmcp1 at 70% of nominal Y/N ____ Vmcp23 at 70% of nominal Y/N ____ Filter wheel at filter 6 Y/N _____

Check on the housekeeping display that the ICU goes back to the AT state, and that the following parameters are as given below.

ICU in AT Y/N ______ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel at filter 7 Y/N _____ Stays in this configuration for 15s Y/N _____

Now load a new table with a different restart action, and note this action here;

Rerun the test as above. Make sure that after the SAA interruption the new restart action is seen.

New restart action seen Y/N_____

Now load a new table with a different exposure completion criterion, and note this criterion here;

Rerun the test as above. Make sure that after the SAA interruption the new criterion is applied.

New criterion applied Y/N_____

If all the above responses are Y's then the test is successful.

Test Successful

16.11 Entering the SAA during slew and exiting it during an AT exposure

Note that to force the direct slew to AT transition first an AT with a finding chart for this location must be done. Consequently a number of already checked state transitions are run through before the new ones are checked.

Set up the celestial environment with Start autumnsafe

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Run the ITOS script ato.proc with the command $\ensuremath{\mathsf{Start}}$ ato

Check on the housekeeping display that the ICU goes to the idle state.

ICU idle Y/N _____

Check on the housekeeping display that the ICU goes to the slew state.

ICU in slew Y/N _____

Check on the housekeeping display that the ICU goes to the settling state.

ICU in settling Y/N _____

Check on the housekeeping display that the ICU goes to the finding state.

ICU in finding Y/N _____

Check on the housekeeping display that the ICU goes to the AT state.

ICU in AT Y/N _____

Check on the housekeeping display that the ICU goes to the slew state.

ICU slew Y/N _____

Check on the housekeeping display that the ICU goes to the PT state.

ICU in PT Y/N _____

Check on the housekeeping display that the ICU goes to the slew state, and that the following parameters are as given below.

ICU in slew Y/N _____ Filter wheel at filter 5 Y/N_____

Check on the housekeeping display that the ICU goes to the slewSAA state, and that the following parameters are as given below.

ICU in slewSAA Y/N _____ Vcathode off Y/N _____ Vmcp1 at 70% of nominal Y/N _____ Vmcp23 at 70% of nominal Y/N ____ Filter wheel at filter 5 Y/N _____

Check on the housekeeping display that the ICU goes to the SAA state, and that the following parameters are as given below.

| ICU in SAA Y/N | |
|------------------------------|--|
| Vcathode off Y/N | |
| Vmcp1 at 70% of nominal Y/N | |
| Vmcp23 at 70% of nominal Y/N | |
| Filter wheel at filter 5 Y/N | |

Check on the housekeeping display that the ICU goes to the AT state, and that the following parameters are as given below.

| ICU in AT Y/N | |
|---|--|
| Vcathode nominal Y/N | |
| Vmcp1 nominal Y/N | |
| Vmcp23 nominal Y/N | |
| Filter wheel at filter 7 Y/N | |
| Stays in this configuration for 10s Y/N | |

If all the above responses are Y's then the test is successful.

| Test Successful | |
|-----------------|--|
|-----------------|--|

16.12 Entering and leaving the SAA during a PT exposure

Set up the celestial environment with Start autumnsafe

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Run the ITOS script ptio.proc with the command $\ensuremath{\mathsf{Start}}$ ptio

Check on the housekeeping display that the ICU goes to the idle state.

ICU idle Y/N _____

Check on the housekeeping display that the ICU goes to the slew state, and that the following parameters are as given below.

ICU in slew Y/N _____ Filter wheel blocked Y/N_____

Check on the housekeeping display that the ICU goes to the PT state, and that the following parameters are as given below.

| ICU in PT Y/N | _ |
|------------------------------|---|
| Vcathode nominal Y/N | |
| Vmcp1 nominal Y/N | _ |
| Vmcp23 nominal Y/N | |
| Filter wheel at filter 5 Y/N | |

Check on the housekeeping display that the ICU goes to the SAA state, and that the following parameters are as given below.

| ICU in SAA Y/N | |
|------------------------------|--|
| Vcathode off Y/N | |
| Vmcp1 at 70% of nominal Y/N | |
| Vmcp23 at 70% of nominal Y/N | |
| Filter wheel at filter 5 Y/N | |

Check on the housekeeping display that the ICU goes back to the PT state, and that the following parameters are as given below.

ICU in PT Y/N _____ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel at filter 6 Y/N ____

Now alter in the script the start of the SAA interruption, so that it starts within the first 10% of the first exposure.

Rerun the test as above, and make sure that after the SAA interruption the ICU goes back to the PT state and restarts the first exposure, ie stays at filter 5.

After SAA interruption ICU in PT Y/N_____ Filter wheel at filter 5 Y/N_____

If all the above responses are Y's then the test is successful.

Test Successful

16.13 Entering the SAA during slew and exiting it during a PT exposure

Set up the celestial environment with Start autumnsafe

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Run the ITOS script pto.proc with the command Start $\ensuremath{\text{pto}}$

Check on the housekeeping display that the ICU goes to the idle state.

ICU idle Y/N _____

Check on the housekeeping display that the ICU goes to the slew state, and that the following parameters are as given below.

ICU in slew Y/N _____ Filter wheel blocked Y/N_____

Check on the housekeeping display that the ICU goes to the slewSAA state, and that the following parameters are as given below.

ICU in slewSAA Y/N _____ Vcathode off Y/N _____ Vmcp1 at 70% of nominal Y/N ____ Vmcp23 at 70% of nominal Y/N ____ Filter wheel blocked Y/N _____

Check on the housekeeping display that the ICU goes to the SAA state, and that the following parameters are as given below.

| ICU in SAA Y/N | |
|------------------------------|--|
| Vcathode off Y/N | |
| Vmcp1 at 70% of nominal Y/N | |
| Vmcp23 at 70% of nominal Y/N | |
| Filter wheel blocked Y/N | |

Check on the housekeeping display that the ICU goes to the PT state, and that the following parameters are as given below.

ICU in PT Y/N _____ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel at filter 5 Y/N _____

If all the above responses are Y's then the test is successful.

Test Successful

16.14 Entering and exiting the SAA during a safe pointing

Set up the celestial environment with Start autumnsafe

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Run the ITOS script sfptio.proc with the command $\ensuremath{\mathsf{Start}}$ sfptio

Check on the housekeeping display that the ICU goes to the idle state.

ICU idle Y/N _____

Check on the housekeeping display that the ICU goes to the slew state, and that the following parameters are as given below.

ICU in slew Y/N _____ Filter wheel blocked Y/N_____

Check on the housekeeping display that the ICU goes to the safepoint state, and that the following parameters are as given below.

| ICU in safepoint Y/N | |
|------------------------------|---|
| Vcathode nominal Y/N | |
| Vmcp1 nominal Y/N | |
| Vmcp23 nominal Y/N | _ |
| Filter wheel at filter 1 Y/N | |

Check on the housekeeping display that the ICU goes to the SAA state, and that the following parameters are as given below.

| ICU in SAA Y/N | |
|------------------------------|--|
| Vcathode off Y/N | |
| Vmcp1 at 70% of nominal Y/N | |
| Vmcp23 at 70% of nominal Y/N | |
| Filter wheel at filter 1 Y/N | |

Check on the housekeeping display that the ICU goes to the safepoint state, and that the following parameters are as given below.

ICU in safepoint Y/N _____ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel at filter 1 Y/N _____

If all the above responses are Y's then the test is successful.

Test Successful

16.15 Entering the SAA during slew and exiting it during a safe pointing

Set up the celestial environment with Start autumnsafe

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Run the ITOS script sfpto.proc with the command ${\tt Start \ sfpto}$

Check on the housekeeping display that the ICU goes to the idle state.

ICU idle Y/N _____

Check on the housekeeping display that the ICU goes to the SAA state, and that the following parameters are as given below.

ICU in SAA Y/N _____ Vcathode off Y/N _____ Vmcp1 at 70% of nominal Y/N ____ Vmcp23 at 70% of nominal Y/N ____ Filter wheel blocked Y/N_____

Check on the housekeeping display that the ICU goes to the slewSAA state, and that the following parameters are as given below.

ICU in slewSAA Y/N _____ Vcathode off Y/N _____ Vmcp1 at 70% of nominal Y/N ____ Vmcp23 at 70% of nominal Y/N ____ Filter wheel blocked Y/N_____

Check on the housekeeping display that the ICU goes to the SAA state, and that the following parameters are as given below.

| ICU in SAA Y/N | |
|------------------------------|--|
| Vcathode off Y/N | |
| Vmcp1 at 70% of nominal Y/N | |
| Vmcp23 at 70% of nominal Y/N | |
| Filter wheel blocked Y/N | |

Check on the housekeeping display that the ICU goes to the safepoint state, and that the following parameters are as given below.

ICU in safepoint Y/N _____ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel at filter 1 Y/N _____

If all the above responses are Y's then the test is successful.

Test Successful

16.16 Entering and exiting the SAA while in the idle state

Set up the celestial environment with Start autumn

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Run the ITOS script idleio.proc with the command $\ensuremath{\mathsf{Start}}$ idleio

Check on the housekeeping display that the ICU goes to the idle state.

ICU idle Y/N _____

Check on the housekeeping display that the ICU goes to the SAA state, and that the following parameters are as given below.

ICU in SAA Y/N ______ Vcathode off Y/N _____ Vmcp1 at 70% of nominal Y/N ____ Vmcp23 at 70% of nominal Y/N ____ Filter wheel blocked Y/N _____

Check on the housekeeping display that the ICU goes back to the idle state, and that the following parameters are as given below.

| ICU idle Y/N | |
|------------------------------|--|
| Vcathode off Y/N | |
| Vmcp1 at 70% of nominal Y/N | |
| Vmcp23 at 70% of nominal Y/N | |
| Filter wheel blocked Y/N | |

If all the above responses are Y's then the test is successful.

Test Successful

16.17 Entering and exiting the SAA in the safe state

Set up the celestial environment with Start autumn

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Run the ITOS script safeio.proc with the command ${\tt Start}$ safeio

Check on the housekeeping display that the ICU stays in the safe state, that the three high voltages are off and that the filter wheel is blocked throughout.

ICU safe Y/N _____ Vcathode off Y/N _____ Vmcp1 off Y/N _____ Vmcp23 off Y/N _____ Filter wheel blocked Y/N _____

If all the above responses are Y's then the test is successful.

Test Successful

17. ERROR CONDITIONS

17.1 Loss of spacecraft messaging

Load flight code icu.hex.

Command the ICU to the idle state using /iState State=Idle

Check on the housekeeping display that the ICU has gone to the idle state, and that the following parameters are as given below.

ICU idle Y/N _____ Vcathode off Y/N _____ Vmcp1 at 70% of nominal Y/N ____ Vmcp23 at 70% of nominal Y/N ____ Filter wheel blocked Y/N _____

Unplug the spacecraft simulator network cable from the wall, then reconnect it 1 minute later, or if using the SWRI simulator, then quit stoi and restart it 1 minute later.

After reconnection, check on the housekeeping display that the ICU has gone to the safe state, that the three high voltages are off and that the filter wheel is blocked.

ICU safe Y/N ______ Vcathode off Y/N ______ Vmcp1 off Y/N ______ Vmcp23 off Y/N ______ Filter wheel blocked Y/N _____

Check on the NHK display that an 'ACS Missing' message has been received.

'ACS Missing' received Y/N_____

If all the above responses are Y's then the test is successful.

Test Successful

17.2 Loss of spacecraft messaging during exposure

Load flight code icu.hex.

Run the ITOS script firstat.proc with the command Start firstat

Once the AT state has been reached, disconnect the spacecraft simulator for approx 45s. Make sure that the watchdog does not trip.

Watchdog trips Y/N_____

If the above response is N then the test is successful.

Test Successful

17.3 Out of limits triggering a power off UVOT request

Change the test environment so that it is as standard except for the telescope simulator running with out-of-limits configuration file hk_low_high.dat, and the DPU simulator running with one or two values out of limits.

Load flight code icu.hex.

From the spacecraft display (or the stoi.out log if using the SWRI simulator), make a note here of the number of SACPWROFFUVOT requests issued so far ______

```
Load a partially configured limit checking table using the commands
load "limpart1.img"
load "limpart2.img"
```

Check on the housekeeping display that limit checking and the limit checking task are enabled and the limit checking task counter is increasing by 10 per hk packet.

Limit checking status 1 Y/N_____ Limit checking task alive Y/N_____ Limit checking task counter increasing by 10 per hk packet Y/N_____

Make sure that the new table is seen using the commands /ilimitoff /ilimiton

Check on the housekeeping display that limit checking, task and counter are disabled and then re-enabled

Limit checking status 0 Y/N_____ Limit checking task asleep Y/N_____ Limit checking task counter unchanging Y/N_____

Limit checking re-enabled Y/N_____

Check on the spacecraft display that another SACPWROFFUVOT request is issued.

SACPWROFFUVOT request issued Y/N_____

If the above response is Y then the test is successful.

Test Successful

17.4 Out of limits triggering a power off UVOT TM request

Change the test environment so that it is as standard except for the telescope simulator running with out-of-limits configuration file hk_low_high.dat, and the DPU simulator running with one or two values out of limits.

Load flight code icu.hex.

From the spacecraft display, make a note here of the number of SACPWROFFUVOTTM requests issued so far _____

Load a partially configured limit checking table using the commands load "lim???.img" load "lim???.img"

Make sure that the new table is seen using the commands /ilimitoff /ilimiton

Check on the spacecraft display (or the stoi.out log if using the SWRI simulator) that another SACPWROFFUVOTTM request is issued.

SACPWROFFUVOTTM request issued Y/N_____

If the above response is Y then the test is successful.

Test Successful

17.5 TMPSU out of limits

Make sure that the test environment is normal, as detailed in the introduction to this document. If necessary reload the standard limit checking table using the commands load "???l.img" load "???l.img" and make sure that the new table is seen using the slightly different commands (which are themselves being tested here) /ilimit enable=off /ilimit enable=on

Set up the celestial environment with Start autumnsafe

Load flight code icu.hex.

Start a PT exposure by running the ITOS script pt.proc with the command Start $\ensuremath{\text{pt}}$

Check on the housekeeping display that the ICU, after slewing, gets to the PT state, that the three high voltages are set to nominal and that the filter wheel goes to filter 5.

ICU in PT Y/N ______ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel at filter 5 Y/N _____

Now command the TMPSU to an out-of-limits value with the command ???

Check on the housekeeping display that within 10s the ICU goes to the safe state, that the three high voltages are turned off and that the filter wheel is blocked.

ICU safe within 10sY/N _____ Vcathode off Y/N _____ Vmcp1 off Y/N _____ Vmcp23 off Y/N _____ Filter wheel blocked Y/N _____

Check on the NHK display that a 'Limit Exceeded' message has been received.

'Limit Exceeded' received Y/N_____

Load flight code icu.hex.

Turn limit checking off with /ilimitoff

Start a PT exposure by running the ITOS script pt.proc with the command Start $\ensuremath{\text{pt}}$

Check on the housekeeping display that the ICU, after slewing, gets to the PT state, that the three high voltages are set to nominal and that the filter wheel goes to filter 5.

| ICU in PT Y/N |
|------------------------------|
| Vcathode nominal Y/N |
| Vmcp1 nominal Y/N |
| Vmcp23 nominal Y/N |
| Filter wheel at filter 5 Y/N |

Check on the housekeeping display that the ICU stays in the PT state, that the three high voltages are set to nominal and that the filter wheel is at filter 5.

| ICU in PT Y/N |
|------------------------------|
| Vcathode nominal Y/N |
| Vmcp1 nominal Y/N |
| Vmcp23 nominal Y/N |
| Filter wheel at filter 5 Y/N |

Load a new limit table where the action on a TMPSU limit being exceeded is to issue a warning message.

Load flight code icu.hex

Now command the TMPSU to an out-of-limits value with the command ???

Check that the warning message is issued.

Warning message issued Y/N_____

Reload the standard limit table.

If all the above responses are Y's then the test is successful.

Test Successful

17.6 BPE out of limits

Set up the celestial environment with Start autumnsafe

Load flight code icu.hex.

Start a PT exposure by running the ITOS script pt.proc with the command Start $\ensuremath{\text{pt}}$

Check on the housekeeping display that the ICU, after slewing, gets to the PT state, that the three high voltages are set to nominal and that the filter wheel goes to filter 5.

ICU in PT Y/N ______ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel at filter 5Y/N _____

Now command the BPE to an out-of-limits value with the command ???

Check on the housekeeping display that within 10s the ICU goes to the safe state, that the three high voltages are turned off and that the filter wheel is blocked.

ICU safe within 10s Y/N _____ Vcathode off Y/N _____ Vmcp1 off Y/N _____ Vmcp23 off Y/N _____ Filter wheel blocked Y/N _____

Load flight code icu.hex.

Turn limit checking off with /ilimitoff

Start a PT exposure by running the ITOS script pt.proc with the command Start $\ensuremath{\text{pt}}$

Check on the housekeeping display that the ICU, after slewing, gets to the PT state, that the three high voltages are set to nominal and that the filter wheel goes to filter 5.

ICU in PT Y/N ______ Vcathode nominal Y/N _____

Vmcp1 nominal Y/N_____ Vmcp23 nominal Y/N _____ Filter wheel at filter 5 Y/N_____

Check on the housekeeping display that the ICU stays in the PT state, that the three high voltages are set to nominal and that the filter wheel is at filter 5.

ICU in PT Y/N _____ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel at filter 5 Y/N _____

Load a new limit table where the action on a BPE limit being exceeded is to issue a warning message.

Load flight code icu.hex

Now command the BPE to an out-of-limits value with the command ???

Check that the warning message is issued.

Warning message issued Y/N_____

Reload the standard limit table.

If all the above responses are Y's then the test is successful.

Test Successful

17.7 DPU out of limits

Set up the celestial environment with Start autumnsafe

Load flight code icu.hex.

Start a PT exposure by running the ITOS script pt.proc with the command Start $\ensuremath{\text{pt}}$

Check on the housekeeping display that the ICU, after slewing, gets to the PT state, that the three high voltages are set to nominal and that the filter wheel goes to filter 5

ICU in PT Y/N _____ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel at filter 5Y/N _____

Now command the DPU to an out-of-limits value with the command ???

Check on the housekeeping display that within 10s the ICU goes to the safe state, that the three high voltages are turned off and that the filter wheel is blocked.

ICU safe within 10s Y/N _____ Vcathode off Y/N _____ Vmcp1 off Y/N _____ Vmcp23 off Y/N _____ Filter wheel blocked Y/N _____

Load flight code icu.hex.

Turn limit checking off with /ilimitoff

Start a PT exposure by running the ITOS script pt.proc with the command Start $\ensuremath{\text{pt}}$

Check on the housekeeping display that the ICU, after slewing, gets to the PT state, that the three high voltages are set to nominal and that the filter wheel goes to filter 5.

ICU in PT Y/N ______ Vcathode nominal Y/N _____

Vmcp1 nominal Y/N_____ Vmcp23 nominal Y/N _____ Filter wheel at filter 5 Y/N_____

Check on the housekeeping display that the ICU stays in the PT state, that the three high voltages are set to nominal and that the filter wheel is at filter 5.

ICU in PT Y/N _____ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel at filter 5 Y/N _____

Load a new limit table where the action on a DPU limit being exceeded is to issue a warning message.

Load flight code icu.hex

Now command the DPU to an out-of-limits value with the command ???

Check that the warning message is issued.

Warning message issued Y/N_____

Reload the standard limit table.

If all the above responses are Y's then the test is successful.

Test Successful

17.8 DPUHB out of limits

Set up the celestial environment with Start autumnsafe

Load flight code icu.hex.

Start a PT exposure by running the ITOS script pt.proc with the command Start $\ensuremath{\text{pt}}$

Check on the housekeeping display that the ICU, after slewing, gets to the PT state, that the three high voltages are set to nominal and that the filter wheel goes to filter 5

ICU in PT Y/N ______ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel at filter 5 YN _____

Now command the DPUHB to an out-of-limits value with the command ???

Check on the housekeeping display that within 10s the ICU goes to the safe state, that the three high voltages are turned off and that the filter wheel is blocked.

ICU safe within 10s Y/N _____ Vcathode off Y/N _____ Vmcp1 off Y/N _____ Vmcp23 off Y/N _____ Filter wheel blocked Y/N _____

Load flight code icu.hex.

Turn limit checking off with /ilimitoff

Start a PT exposure by running the ITOS script pt.proc with the command Start $\ensuremath{\text{pt}}$

Check on the housekeeping display that the ICU, after slewing, gets to the PT state, that the three high voltages are set to nominal and that the filter wheel goes to filter 5.

ICU in PT Y/N ______ Vcathode nominal Y/N _____

Vmcp1 nominal Y/N_____ Vmcp23 nominal Y/N _____ Filter wheel at filter 5 Y/N_____

Check on the housekeeping display that the ICU stays in the PT state, that the three high voltages are set to nominal and that the filter wheel is at filter 5.

ICU in PT Y/N _____ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel at filter 5 Y/N _____

Load a new limit table where the action on a DPUHB limit being exceeded is to issue a warning message.

Load flight code icu.hex

Now command the DPUHB to an out-of-limits value with the command ???

Check that the warning message is issued.

Warning message issued Y/N_____

Reload the standard limit table.

If all the above responses are Y's then the test is successful.

Test Successful

17.9 Bad is_settled flag in ACS

Set up the celestial environment with Start autumnsafe

Load flight code icu.hex.

Run the ITOS proc badacs1.proc with the command ${\tt Start\ badacs1}$

Check on the housekeeping display that the ICU, after slewing, gets to the PT state, that the three high voltages are set to nominal and that the filter wheel goes to filter 5

ICU in PT Y/N ______ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel at filter 5 Y/N _____

Check on the housekeeping display that the ICU goes to the safe state, that the three high voltages go off and that the filter wheel is blocked.

ICU safe Y/N _____ Vcathode off Y/N _____ Vmcp1 off Y/N _____ Vmcp23 off Y/N _____ Filter wheel blocked Y/N _____

If all the above responses are Y's then the test is successful.

Test Successful

17.10 A glitch in the is_settled flag

Set up the celestial environment with Start autumnsafe

Load flight code icu.hex .

Command the ICU to the idle state using /iState State=Idle

Check on the housekeeping display that the ICU has gone to the idle state.

ICU idle Y/N _____

Run the ITOS proc badacs2.proc with the command ${\tt Start\ badacs2}$

Check on the housekeeping display that the ICU, after slewing, gets to the PT state, that the three high voltages are set to nominal and that the filter wheel goes to filter 5, and this configuration is held for 10s.

| ICU in PT Y/N |
|--------------------------------|
| Vcathode nominal Y/N |
| Vmcp1 nominal Y/N |
| Vmcp23 nominal Y/N |
| Filter wheel at filter 5 Y/N |
| Configuration held for 10s Y/N |

If all the above responses are Y's then the test is successful.

Test Successful

17.11 Bad pointing values

NB The case of an ACS message with all values set to 0 is automatically tested every time the autumnsafe ITOS procedure is run.

Alter the database so that there are no limits set for possible right ascension, declination, roll and spacecraft voltage values in the SACSIMSETATT command and for possible right ascension, declination and roll values in the FONEXTOBSINFO command.

Load flight code icu.hex.

Command the ICU to the idle state using /iState State=Idle

Check on the housekeeping display that the ICU has gone to the idle state.

ICU idle Y/N _____

Change the RA value in the ACS messages with the commands ${\tt RA=0xfff}$ Start changeatt

Check on the housekeeping display that the ICU goes to the safe state, that the three high voltages go off and that the filter wheel is blocked.

ICU safe Y/N _____ Vcathode off Y/N _____ Vmcp1 off Y/N _____ Vmcp23 off Y/N _____ Filter wheel blocked Y/N _____

Check that an NHK 'Bad Value' message is received.

'Bad Value' received Y/N_____

Change the declination value in the ACS messages with the commands $RA{=}0$ $\mbox{Dec=}0{\times}\mbox{fff}$ Start changeatt

Check on the housekeeping display that the ICU goes to the safe state, that the three high voltages go off and that the filter wheel is blocked.

ICU safe Y/N _____

Vcathode off Y/N _____ Vmcp1 off Y/N _____ Vmcp23 off Y/N _____ Filter wheel blocked Y/N _____

Check that an NHK 'Bad Value' message is received.

'Bad Value' received Y/N_____

Change the roll value in the ACS messages with the commands $\mbox{Dec=0}$ Roll=0xffff Start changeatt

Check on the housekeeping display that the ICU goes to the safe state, that the three high voltages go off and that the filter wheel is blocked.

ICU safe Y/N _____ Vcathode off Y/N _____ Vmcp1 off Y/N _____ Vmcp23 off Y/N _____ Filter wheel blocked Y/N _____

Check that an NHK 'Bad Value' message is received.

'Bad Value' received Y/N_____

Change the spacecraft voltage value in the ACS messages with the commands ${\tt Dec=0}$ ${\tt Busvolt=0xfff}$ Start changeatt

Check on the housekeeping display that the ICU goes to the safe state, that the three high voltages go off and that the filter wheel is blocked.

ICU safe Y/N _____ Vcathode off Y/N _____ Vmcp1 off Y/N _____ Vmcp23 off Y/N _____ Filter wheel blocked Y/N _____

Check that an NHK 'Bad Value' message is received.

'Bad Value' received Y/N_____

Change the spacecraft voltage value in the ACS messages with the commands

Busvolt=0 Start changeatt

Check on the ACS display that the voltage has automatically been assigned 30V.

Spacecraft voltage 30V Y/N_____

Change to the idle state with /istate state=idle

Fool the ICU into thinking a slew has started by sending the command /sislewwarning

Change the RA value in the FONEXTOBSINFO messages with the commands fomra=0xffff Start sendfom

Check on the housekeeping display that the ICU goes to the safe state, that the three high voltages go off and that the filter wheel is blocked.

ICU safe Y/N _____ Vcathode off Y/N _____ Vmcp1 off Y/N _____ Vmcp23 off Y/N _____ Filter wheel blocked Y/N _____

Check that an NHK 'Bad Value' message is received.

'Bad Value' received Y/N_____

Change to the idle state with /istate state=idle

Fool the ICU into thinking a slew has started by sending the command /sislewwarning

Change the declination value in the FONEXTOBSINFO messages with the commands fomra=0 fomdec=0xffff Start sendfom

Check on the housekeeping display that the ICU goes to the safe state, that the three high voltages go off and that the filter wheel is blocked.

ICU safe Y/N _____ Vcathode off Y/N _____

Vmcp1 off Y/N_____ Vmcp23 off Y/N _____ Filter wheel blocked Y/N_____

Check that an NHK 'Bad Value' message is received.

'Bad Value' received Y/N_____

Change to the idle state with /istate state=idle

Fool the ICU into thinking a slew has started by sending the command /sislewwarning

Change the roll value in the FONEXTOBSINFO messages with the commands fomdec=0 fomroll=0xffff Start sendfom

Check on the housekeeping display that the ICU goes to the safe state, that the three high voltages go off and that the filter wheel is blocked.

ICU safe Y/N _____ Vcathode off Y/N _____ Vmcp1 off Y/N _____ Vmcp23 off Y/N _____ Filter wheel blocked Y/N _____

Check that an NHK 'Bad Value' message is received.

'Bad Value' received Y/N_____

Change to the idle state with /istate state=idle

Fool the ICU into thinking a slew has started by sending the command /sislewwarning

Change the attitude values in the FONEXTOBSINFO messages with the commands fomra=0 fomdec=0 fomroll=0 Start sendfom

Check that no error messages are received.

Error messages received Y/N_____

NB: Return the database to normal now.

If all the above responses bar the last are Y's and the last is N then the test is successful.

Test Successful

17.12 Slewing towards the Sun

Set up the celestial environment with Start springsun

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Check on the housekeeping display that the sun constraint violation flag is set to OK.

Sun constraint violation OK Y/N_____

Run the ITOS script looksun.proc with the command Start looksun

Check on the housekeeping display that the ICU goes to the idle state.

ICU idle Y/N _____

Check on the housekeeping display that the ICU goes to the slew state, and that the following parameters are as given below.

ICU in slew Y/N _____ Filter wheel blocked Y/N_____

Check on the housekeeping display that the ICU goes to the idle state, and that the following parameters are as given below.

ICU idle Y/N ______ Vcathode off Y/N ______ Vmcp1 stays where it was at the point of interruption Y/N ______ Vmcp23 stays where it was at the point of interruption Y/N ______ Filter wheel blocked Y/N _____

Check on the housekeeping display that the sun constraint violation flag is set to CLOSE.

Sun constraint violation CLOSE Y/N_____

If all the above responses are Y's then the test is successful.

Test Successful

17.13 Slewing towards the Earth

Set up the celestial environment with Start autumnsafe

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Check on the housekeeping display that the earth constraint violation flag is set to OK.

Earth constraint violation OK Y/N_____

Run the ITOS script lookearth.proc with the command Start lookearth

Check on the housekeeping display that the ICU goes to the idle state.

ICU idle Y/N _____

Check on the housekeeping display that the ICU goes to the slew state, and that the following parameters are as given below.

ICU in slew Y/N _____ Filter wheel blocked Y/N_____

Check on the housekeeping display that the ICU goes to the idle state, and that the following parameters are as given below.

ICU safe Y/N _____ Vcathode off Y/N _____ Vmcp1 stays where it was at the point of interruption Y/N _____ Vmcp23 stays where it was at the point of interruption Y/N _____ Filter wheel blocked Y/N _____

Check on the housekeeping display that the earth constraint violation flag is set to CLOSE.

Earth constraint violation CLOSE Y/N_____

If all the above responses are Y's then the test is successful.

Test Successful

17.14 Drift off target once settled

Set up the celestial environment with Start autumnsafe

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Run the ITOS script drift.proc with the command ${\tt Start}\ {\tt drift}$

Check on the housekeeping display that the ICU, after going to idle and then slewing, gets to the PT state, that the three high voltages are set to nominal and that the filter wheel goes to filter 5.

ICU in PT Y/N ______ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel at filter 5 Y/N _____

Check on the housekeeping display stays in the PT state, that the three high voltages are set to nominal and that the filter wheel goes to filter 6.

| ICU in PT Y/N |
|------------------------------|
| Vcathode nominal Y/N |
| Vmcp1 nominal Y/N |
| Vmcp23 nominal Y/N |
| Filter wheel at filter 6 Y/N |

Then check that 25s after the first exposure started the ICU goes to the safe state, that the three high voltages go off and that the filter wheel is blocked.

| ICU safe Y/N |
|--------------------------|
| Vcathode off Y/N |
| Vmcp1 off Y/N |
| Vmcp23 off Y/N |
| Filter wheel blocked Y/N |

Check on the NHK display that an 'Unacceptable Differential Drift' message has been received.

'Unacceptable Differential Drift' received Y/N_____

Wait one minute and check on the NHK display that another 'Unacceptable Differential Drift' message has been received. Check that this is timestamped one minute after the first.

'Unacceptable Differential Drift' received Y/N_____ Timestamps one minute apart Y/N_____

Now load a new limit table, where the default action on ACS going out of limits is no-op.

Load flight code icu.hex

Run the ITOS script drift.proc with the command $\ensuremath{\mathsf{Start}}$ drift

Check on the housekeeping display that the ICU, after going to idle and then slewing, gets to the PT state, that the three high voltages are set to nominal and that the filter wheel goes to filter 5.

ICU in PT Y/N _____ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N _____ Vmcp23 nominal Y/N _____ Filter wheel at filter 5 Y/N _____

Check on the housekeeping display stays in the PT state, that the three high voltages are set to nominal and that the filter wheel goes to filter 6.

| ICU in PT Y/N |
|------------------------------|
| Vcathode nominal Y/N |
| Vmcp1 nominal Y/N |
| Vmcp23 nominal Y/N |
| Filter wheel at filter 6 Y/N |

Check on the housekeeping display stays in the PT state, that the three high voltages are set to nominal and that the filter wheel goes to filter 7 ie the ICU has not safed itself.

| ICU in PT Y/N |
|------------------------------|
| Vcathode nominal Y/N |
| Vmcp1 nominal Y/N |
| Vmcp23 nominal Y/N |
| Filter wheel at filter 7 Y/N |

If all the above responses are Y's then the test is successful.

Test Successful

17.15 Settled on wrong target

Set up the celestial environment with Start autumnsafe

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Run the ITOS script wrongtarget.proc with the command Start wrongtarget

Check on the housekeeping display that the ICU goes to the idle state.

ICU idle Y/N _____

Check on the housekeeping display that the ICU goes to the slew state, and that the following parameters are as given below.

ICU in slew Y/N _____ Filter wheel blocked Y/N_____

Then check that after 20s the ICU goes to the safe state, that the three high voltages go off and that the filter wheel is blocked.

| ICU safe Y/N | _ |
|--------------------------|---|
| Vcathode off Y/N | |
| Vmcp1 off Y/N | |
| Vmcp23 off Y/N | |
| Filter wheel blocked Y/N | |

Check on the NHK display that a 'Not at Predicted Position' message has been received.

'Not at Predicted Position' received Y/N_____

If all the above responses are Y's then the test is successful.

|--|

17.16 Corrupted star catalogue

If this test is being run immediately after test 4.1 then the star catalogue memory will actually be corrupted. If not, then edit the code so that the starcat task always returns a corrupted EEPROM message.

Set up the celestial environment with Start autumnsafe

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Run the ITOS script pt.proc with the command Start $\ensuremath{\text{pt}}$

Check on the housekeeping display that the ICU goes to the idle state.

ICU idle Y/N _____

Check on the housekeeping display that the ICU goes to the slew state, and that the following parameters are as given below.

ICU in slew Y/N _____ Filter wheel blocked Y/N_____

Check on the housekeeping display that the ICU goes to the idle state, and that the following parameters are as given below.

ICU idle Y/N ______ Vcathode off Y/N _____ Vmcp1 at 70% of nominal Y/N _____ Vmcp23 at 70% of nominal Y/N ____ Filter wheel blocked Y/N _____

Check on the NHK display that a 'Corrupted EEPROM Data' message has been received, with first parameter 0004 and second parameter EEEE.

'Corrupted EEPROM Data' received Y/N_____
First parameter 0004 Y/N_____
Second parameter EEEE Y/N_____

NB Now either take the edits out of the code or reload the star catalogue using

Load "cat.img" Load "pointers.img" Load "addendum.img"

If all the above responses are Y's then the test is successful.

Test Successful

17.17 Unknown UVOT modes

Set up the celestial environment with Start autumnsafe

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Run the ITOS script getnoatmode.proc with the command Start getnoatmode

Check on the housekeeping display that the ICU goes to the idle state.

ICU idle Y/N _____

Check on the housekeeping display that the ICU goes to the slew state, and that the following parameters are as given below.

ICU in slew Y/N _____ Filter wheel blocked Y/N_____

Check on the housekeeping display that the ICU goes to the idle state, and that the following parameters are as given below.

ICU idle Y/N _____ Vcathode off Y/N _____ Vmcp1 at 70% of nominal Y/N ____ Vmcp23 at 70% of nominal Y/N ____ Filter wheel blocked Y/N _____

Check on the NHK display that a 'No Such UVOT AT Mode' message has been received.

'No Such UVOT AT Mode' received Y/N_____

Run the ITOS script getnoptmode.proc with the command Start getnoptmode

Check on the housekeeping display that the ICU stays in the idle state.

ICU idle Y/N _____

Check on the housekeeping display that the ICU goes to the slew state, and that the following parameters are as given below.

ICU in slew Y/N _____ Filter wheel blocked Y/N_____

Check on the housekeeping display that the ICU goes to the idle state, and that the following parameters are as given below.

| ICU idle Y/N | |
|------------------------------|--|
| Vcathode off Y/N | |
| Vmcp1 at 70% of nominal Y/N | |
| Vmcp23 at 70% of nominal Y/N | |
| Filter wheel blocked Y/N | |

Check on the NHK display that a 'No Such UVOT PT Mode' message has been received.

'No Such UVOT PT Mode' received Y/N_____

If all the above responses are Y's then the test is successful.

Test Successful

17.18 Bright star store exhausted

Edit the code so that the bright star store will only contain three values.

Set up the celestial environment with Start springcanopus

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Run the ITOS script ptstar.proc with the command $\ensuremath{\mathsf{Start}}$ ptstar

Check on the housekeeping display that the ICU goes to the idle state.

ICU idle Y/N _____

Check on the housekeeping display that the ICU goes to the slew state, and that the following parameters are as given below.

ICU in slew Y/N _____ Filter wheel blocked Y/N_____

Check on the housekeeping display that the ICU goes to the idle state, and that the following parameters are as given below.

| ICU idle Y/N | |
|------------------------------|--|
| Vcathode off Y/N | |
| Vmcp1 at 70% ofnominal Y/N | |
| Vmcp23 at 70% of nominal Y/N | |
| Filter wheel blocked Y/N | |

Check on the NHK display that a 'Bright Star Store Exhausted' message has been received.

'Bright Star Store Exhausted' received Y/N_____

If all the above responses are Y's then the test is successful.

Test Successful

| 17.19 Exposures commanded while UVOT is safed |
|---|
| Load flight code icu.hex. |
| Check on the housekeeping display that the ICU is in the safe state. |
| ICU safe Y/N |
| Run an ITOS script to start an AT without taking the UVOT out of the safe state. |
| Check on the housekeeping display that the ICU stays in the safe state throughout. |
| ICU safe Y/N |
| Run an ITOS script to start a PT without taking the UVOT out of the safe state. |
| Check on the housekeeping display that the ICU stays in the safe state throughout. |
| ICU safe Y/N |
| Run an ITOS script to start a safepointing without taking the UVOT out of the safe state. |
| Check on the housekeeping display that the ICU stays in the safe state throughout. |
| ICU safe Y/N |
| If all the above responses are Y's then the test is successful. |
| Test Successful |
| |

18. MANUAL STATE TRANSITIONS

18.1 Manual state transitions

Load flight code icu.hex.

Load an altered state transition table, which will change state when allowable but otherwise perform no-op, using Load "???.img"

In the table below, for each line, check that UVOT is in the current state, and command it to go to the next state. In some cases a series of state changes is given - this is because to access some states repetition of previously checked transitions is necessary. In each case check that the response is as given. The last transition in the series is the one being checked. A disallowed transition will receive a 'Forbidden State Transition' NHK message. The state change command, eg for slew, is

/iState State=slew

| Current state | Next state | Response expected | Response as |
|---------------|------------|------------------------------|--------------|
| Safe | Slew | 'Forbidden State Transition' | expected Y/N |
| Safe | SlewSAA | 'Forbidden State Transition' | |
| Safe | AT | 'Forbidden State Transition' | |
| Safe | PT | 'Forbidden State Transition' | |
| Safe | Safepoint | 'Forbidden State Transition' | |
| Safe | Settling | 'Forbidden State Transition' | |
| Safe | Finding | 'Forbidden State Transition' | |
| Safe | SAA | 'Forbidden State Transition' | |
| Safe | Safe | 'Forbidden State Transition' | |
| Safe | Idle | Transition to Idle | |
| Idle | SlewSAA | 'Forbidden State Transition' | |
| Idle | Settling | 'Forbidden State Transition' | |
| Idle | Finding | 'Forbidden State Transition' | |
| Idle | AT | 'Forbidden State Transition' | |
| Idle | PT | 'Forbidden State Transition' | |
| Idle | Safepoint | 'Forbidden State Transition' | |
| Idle | Idle | 'Forbidden State Transition' | |
| Idle | Slew | Transition to Slew | |
| Slew | Idle | Transition to Idle | |
| Idle | SAA | Transition to SAA | |
| SAA | Idle | Transition to Idle | |
| Idle | Safe | Transition to Safe | |
| Safe | to Idle to | 'Forbidden State Transition' | |

| | SAA to Slew | | |
|-----------|-----------------------------|------------------------------|--|
| SAA | SAA | 'Forbidden State Transition' | |
| SAA | SlewSAA | Transition to SlewSAA | |
| SlewSAA | SAA | Transition to SAA | |
| SAA | AT | Transition to AT | |
| AT | SAA | Transition to SAA | |
| SAA | PT | Transition to PT | |
| PT | SAA | Transition to SAA | |
| SAA | Safepoint | Transition to Safepoint | |
| Safepoint | SAA | Transition to SAA | |
| SAA | Settling | Transition to Settling | |
| Settling | SAA | Transition to SAA | |
| SAA | Finding | Transition to Finding | |
| Finding | SAA | Transition to SAA | |
| SAA | Safe | Transition to Safe | |
| Safe | to Idle to | 'Forbidden State Transition' | |
| | SAA to | | |
| | SlewSAA to | | |
| | AT | | |
| SlewSAA | PT | 'Forbidden State Transition' | |
| SlewSAA | Safepoint | 'Forbidden State Transition' | |
| SlewSAA | Idle | 'Forbidden State Transition' | |
| SlewSAA | Settling | 'Forbidden State Transition' | |
| SlewSAA | Finding | 'Forbidden State Transition' | |
| SlewSAA | SlewSAA | 'Forbidden State Transition' | |
| SlewSAA | Slew | Transition to Slew | |
| Slew | SlewSAA | Transition to SlewSAA | |
| SlewSAA | Safe | Transition to Safe | |
| Safe | to Idle to | 'Forbidden State Transition' | |
| | Slew to Slew | | |
| Slew | SAA | 'Forbidden State Transition' | |
| Slew | AT | Transition to AT | |
| AT | Slew | Transition to Slew | |
| Slew | PT | Transition to PT | |
| PT | Slew | Transition to Slew | |
| Slew | Safepoint | Transition to Safepoint | |
| Safepoint | Slew | Transition to Slew | |
| Slew | Settling | Transition to Settling | |
| Settling | Slew | Transition to Slew | |
| Slew | Finding | Transition to Finding | |
| Finding | Slew | Transition to Slew | |
| Slew | Safe | Transition to Safe | |
| Safe | to Idle to Slew to AT to | 'Forbidden State Transition' | |
| | Settling | | |

'Forbidden State Transition' AT Finding AT PT 'Forbidden State Transition' AT Safepoint 'Forbidden State Transition' 'Forbidden State Transition' AT SlewSAA AT AT Transition to AT AT Idle Transition to Idle Idle to Slew to AT Transition to Safe to Safe to Idle to 'Forbidden State Transition' Safe Slew to PT to Settling 'Forbidden State Transition' PT Finding PT 'Forbidden State Transition' AT PT Safepoint 'Forbidden State Transition' PT 'Forbidden State Transition' SlewSAA PT PT Transition to PT PT Idle Transition to Idle to Slew to PT Transition to Safe Idle to Safe to Idle to Safe Transition to Safepoinnt Slew to Safepoint 'Forbidden State Transition' Safepoint Settling Safepoint Finding 'Forbidden State Transition' 'Forbidden State Transition' Safepoint AT PT 'Forbidden State Transition' Safepoint Safepoint SlewSAA 'Forbidden State Transition' Safepoint Transition to Safepoint Safepoint Transition to Idle Safepoint Idle Idle to Slew to Transition to Safe Safepoint to Safe Safe to Idle to 'Forbidden State Transition' Slew to Settling to SlewSAA Settling 'Forbidden State Transition' AT Settling PT 'Forbidden State Transition' Settling Safepoint 'Forbidden State Transition' Settling Settling 'Forbidden State Transition' Settling Finding Transition to Finding Finding Idle Transition to Idle

SWIFT-UVOT ICU CODE BUILD 5 TEST PLAN Document: MSSL/SWT-UVOT/MSSL/xx/xxxx.x

Transition to Idle

Idle

to Slew to

Settling to

Idle

| Idle | to Slew to Settling to | Transition to Safe | |
|---------|---------------------------|------------------------------|--|
| | Safe | | |
| Safe | to Idle to | 'Forbidden State Transition' | |
| | Slew to | | |
| | Settling to | | |
| | Finding to | | |
| | Settling | | |
| Finding | Finding | 'Forbidden State Transition' | |
| Finding | PT | 'Forbidden State Transition' | |
| Finding | Safepoint | 'Forbidden State Transition' | |
| Finding | SlewSAA | 'Forbidden State Transition' | |
| Finding | AT | Transition to AT | |
| AT | to Slew to | Transition to Safe | |
| | Settling to | | |
| | Finding to | | |
| | Safe | | |

If all the responses in column 4 of the table above are Y's then the test is successful.

Test Successful

19. CORRUPTED TABLES

19.1 Random corruption

Note that the star catalogue tables are not tested here as they have already been tested in section 17.16.

Load two tables that will corrupt all the non-star catalogue tables in EEPROM B using Load "corrtbll.img" Load "corrtbl2.img"

Load flight code icu.hex.

Check on the NHK display that two 'Corrupted EEPROM Data' messages are received, one with a first parameter of 3 and the other with a first parameter 0x23.

'Corrupted EEPROM Data 0003' received Y/N_____'Corrupted EEPROM Data 0023' received Y/N_____

Try to ramp up the high voltages, run an RTS, and change state, using /iHVEnable On /iHVRamp Vmcp23, Value=110, RampRate=0 /iHVEnable Off /iRTSRun RTS=0x52 /iState Idle

None of these should work.

 High voltages would not move Y/N_____

 RTS would not run Y/N_____

 ICU state stayed safe Y/N_____

Load the second heater table using Load "heater2.img"

Reload flight code icu.hex.

Check on the NHK display that a 'Corrupted EEPROM Data' message is received, with a first parameter of 3.

'Corrupted EEPROM Data 0003' received Y/N_____

Load the first heater table using Load "heater1.img"

Reload flight code icu.hex.

Check on the NHK display that two 'Corrupted EEPROM Data' messages are received, one with a first parameter of 2 and the other with a first parameter 0x22.

'Corrupted EEPROM Data 0002' received Y/N_____'Corrupted EEPROM Data 0022' received Y/N_____

Try to ramp up the high voltages, run an RTS, and change state, using /iHVEnable On /iHVRamp Vmcp23, Value=110, RampRate=0 /iHVEnable Off /iRTSRun RTS=0x52 /iState Idle

None of these should work.

 High voltages would not move Y/N_____

 RTS would not run Y/N_____

 ICU state stayed safe Y/N_____

Load the second limit table using Load "lim2.img"

Reload flight code icu.hex.

Check on the NHK display that a 'Corrupted EEPROM Data' message is received, with a first parameter of 2.

'Corrupted EEPROM Data 0002' received Y/N_____

Load the first limit table using Load "lim1.img"

Reload flight code icu.hex.

Check on the NHK display that two 'Corrupted EEPROM Data' messages are received, one with a first parameter of 1 and the other with a first parameter 0x21.

'Corrupted EEPROM Data 0001' received Y/N_____'Corrupted EEPROM Data 0021' received Y/N_____

Try to ramp up the high voltages, run an RTS, and change state, using /iHVEnable On /iHVRamp Vmcp23, Value=110, RampRate=0

/iHVEnable Off /iRTSRun RTS=0x52 /iState Idle

None of these should work.

 High voltages would not move Y/N_____

 RTS would not run Y/N_____

 ICU state stayed safe Y/N______

Load the second HV table using Load "hv2.img"

Reload flight code icu.hex.

Check on the NHK display that a 'Corrupted EEPROM Data' message is received, with a first parameter of 2.

'Corrupted EEPROM Data 0001' received Y/N_____

Try to ramp up the high voltages, run an RTS, and change state, using

/iHVEnable On /iHVRamp Vmcp23, Value=110, RampRate=0 /iHVEnable Off /iRTSRun RTS=0x52 /iState Idle

None of these should work.

 High voltages would not move Y/N_____

 RTS would not run Y/N_____

 ICU state stayed safe Y/N______

Load the first HV table using Load "hv1.img"

Reload flight code icu.hex.

Check on the NHK display that a 'Corrupted EEPROM Data' message is received, with a first parameter of 0xA.

'Corrupted EEPROM Data 000a' received Y/N_____

Try to ramp up the high voltages, run an RTS, and change state, using /iHVEnable On /iHVRamp Vmcp23, Value=110, RampRate=0

/iHVEnable Off /iRTSRun RTS=0x52 /iState Idle

None of these should work.

 High voltages would not move Y/N_____

 RTS would not run Y/N_____

 ICU state stayed safe Y/N______

Load the state table using Load "state_changes_eeprom_0ff600.img"

Reload flight code icu.hex.

Check on the NHK display that a 'Corrupted EEPROM Data' message is received, with a first parameter of 0xE.

'Corrupted EEPROM Data 000e' received Y/N_____

Try to ramp up the high voltages, run an RTS, and change state, using /iHVEnable On /iHVRamp Vmcp23, Value=110, RampRate=0 /iHVEnable Off /iRTSRun RTS=0x52 /iState Idle

None of these should work.

 High voltages would not move Y/N_____

 RTS would not run Y/N_____

 ICU state stayed safe Y/N_____

Load the count rate table using Load "count_rate_table_eeprom_Off380.img"

Reload flight code icu.hex.

Check on the NHK display that a 'Corrupted EEPROM Data' message is received, with a first parameter of 0x7.

'Corrupted EEPROM Data 0007' received Y/N_____

Try to ramp up the high voltages, run an RTS, and change state, using /iHVEnable On /iHVRamp Vmcp23, Value=110, RampRate=0

/iHVEnable Off /iRTSRun RTS=0x52 /iState Idle

None of these should work.

 High voltages would not move Y/N_____

 RTS would not run Y/N_____

 ICU state stayed safe Y/N______

Load the AT configuration tables using Load "at_config_eeprom_0fe380.img" Load "at_config_eeprom_0f6280.img"

Reload flight code icu.hex.

Check on the NHK display that a 'Corrupted EEPROM Data' message is received, with a first parameter of 0xF.

'Corrupted EEPROM Data 000f' received Y/N_____

Try to ramp up the high voltages, run an RTS, and change state, using /iHVEnable On /iHVRamp Vmcp23, Value=110, RampRate=0 /iHVEnable Off /iRTSRun RTS=0x52 /iState Idle

None of these should work.

 High voltages would not move Y/N_____

 RTS would not run Y/N_____

 ICU state stayed safe Y/N_____

Load the PT configuration ID tables using Load "pt_config_id_eeprom_0f8480.img" Load "pt_config_id_eeprom_0f8380.img"

Reload flight code icu.hex.

Check on the NHK display that a 'Corrupted EEPROM Data' message is received, with a first parameter of 0x8.

'Corrupted EEPROM Data 0008' received Y/N_____

Try to ramp up the high voltages, run an RTS, and change state, using

/iHVEnable On /iHVRamp Vmcp23, Value=110, RampRate=0 /iHVEnable Off /iRTSRun RTS=0x52 /iState Idle

None of these should work.

 High voltages would not move Y/N_____

 RTS would not run Y/N_____

 ICU state stayed safe Y/N_____

Load the PT configuration table using Load "pt_config_eeprom_0fa380.img"

Reload flight code icu.hex.

Check on the NHK display that a 'Corrupted EEPROM Data' message is received, with a first parameter of 0x9.

'Corrupted EEPROM Data 0009' received Y/N_____

Try to ramp up the high voltages, run an RTS, and change state, using /iHVEnable On /iHVRamp Vmcp23, Value=110, RampRate=0 /iHVEnable Off /iRTSRun RTS=0x52 /iState Idle

None of these should work.

 High voltages would not move Y/N_____

 RTS would not run Y/N_____

 ICU state stayed safe Y/N_____

Load the standard table using Load "standard_eeprom_Offf80.img"

Reload flight code icu.hex.

Check on the NHK display that a 'Corrupted EEPROM Data' message is received, with a first parameter of 0x5.

'Corrupted EEPROM Data 0005' received Y/N_____

Try to ramp up the high voltages, run an RTS, and change state, using

/iHVEnable On /iHVRamp Vmcp23, Value=110, RampRate=0 /iHVEnable Off /iRTSRun RTS=0x52 /iState Idle

None of these should work.

 High voltages would not move Y/N_____

 RTS would not run Y/N_____

 ICU state stayed safe Y/N______

Load the avoidance angles table using Load "avoidance_eeprom_0ff500.img"

Reload flight code icu.hex.

Check on the NHK display that a 'Corrupted EEPROM Data' message is received, with a first parameter of 0xD.

'Corrupted EEPROM Data 000d' received Y/N_____

Try to ramp up the high voltages, run an RTS, and change state, using /iHVEnable On /iHVRamp Vmcp23, Value=110, RampRate=0 /iHVEnable Off /iRTSRun RTS=0x52 /iState Idle

None of these should work.

 High voltages would not move Y/N_____

 RTS would not run Y/N_____

 ICU state stayed safe Y/N_____

Load the error action table using Load "errors_table_eeprom_0f8280.img"

Reload flight code icu.hex.

Run a test RTS, number 0x20, using /iRTSRun Number=0x20

Check on the NHK display that a 'Corrupted EEPROM Data' message is received, with a first parameters of 0x10.

'Corrupted EEPROM Data 0010' received Y/N_____

Try to ramp up the high voltages, run an RTS, and change state, using

/iHVEnable On /iHVRamp Vmcp23, Value=110, RampRate=0 /iHVEnable Off /iRTSRun RTS=0x52 /iState Idle

None of these should work.

 High voltages would not move Y/N_____

 RTS would not run Y/N_____

 ICU state stayed safe Y/N______

Load the RTS index table using Load "rts.img"

Poke this table so that there is a corruption in the test RTS using ???

Reload flight code icu.hex.

Run a test RTS, number 0x20, using /iRTSRun Number=0x20

Check on the NHK display that a 'Corrupted EEPROM Data' message is received, with a first parameter of 0xC.

'Corrupted EEPROM Data 000c' received Y/N_____

Try to ramp up the high voltages, run an RTS, and change state, using /iHVEnable On /iHVRamp Vmcp23, Value=110, RampRate=0 /iHVEnable Off /iRTSRun RTS=0x52 /iState Idle

None of these should work.

 High voltages would not move Y/N_____

 RTS would not run Y/N_____

 ICU state stayed safe Y/N______

Undo the poke using ???

Reload flight code icu.hex.

Run a test RTS, number 0x20, using /iRTSRun Number=0x20

Check on the NHK display that a 'Corrupted EEPROM Data' message is received, with a first parameter of 0xB.

'Corrupted EEPROM Data 000b' received Y/N_____

Try to ramp up the high voltages, run an RTS, and change state, using /iHVEnable On /iHVRamp Vmcp23, Value=110, RampRate=0 /iHVEnable Off /iRTSRun RTS=0x52 /iState Idle

None of these should work.

 High voltages would not move Y/N_____

 RTS would not run Y/N_____

 ICU state stayed safe Y/N_____

Load the command database table using Load "dbase2_eeprom_080300.img"

Reload flight code icu.hex.

Try to ramp up the high voltages, run an RTS, and change state, using /iHVEnable On /iHVRamp Vmcp23, Value=110, RampRate=0 /iHVEnable Off /iRTSRun RTS=0x52 /iState Idle

All of these should now work.

Vmcp23 ramped up Y/N_____ RTS ran Y/N_____ ICU went to idle Y/N_____

Run a test RTS, number 0x20, using /iRTSRun Number=0x20

Check on the NHK display that no 'Corrupted EEPROM Data' messages are received.

'Corrupted EEPROM Data' messages received Y/N_____

If all the responses above bar the last are Y's and the last is N then the test is successful.

Test Successful

19.2 Corrupted token in DCS

Note that this is an extremely unlikely fault, which can only be caused by mistakes in the compilation of the RTS tables on the ground.

Poke the RTS table to create a bad token, and poke the CRC value for the table to accept this bad value, using ???

Load flight code icu.hex.

Run a test RTS, number 0x20, using /iRTSRun Number=0x20

Check on the NHK display that a 'DCS Invalid Command Token' message is received.

'DCS Invalid Command Token' message received Y/N_____

If the response above is Y then the test is successful.

Test Successful

20. FORCED STATE CHANGES TO SAFE, IDLE OR SLEW

20.1 From slew to safe

Set up the celestial environment with Start autumnsafe

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Run the ITOS script safefromslew.proc with the command Start safefromslew

Check on the housekeeping display that the ICU follows its usual sequence until it reaches the slew state (this has been tested many times by now and need not be tested in detail here). Then check that it goes to the safe state correctly.

ICU reaches slew state Y/N_____ ICU then goes to safe state Y/N_____ Vcathode off Y/N _____ Vmcp1 off Y/N_____ Vmcp23 off Y/N _____ Filter wheel blocked Y/N____

If the responses above are all Y's then the test is successful.

Test Successful

20.2 From slewSAA to safe

Set up the celestial environment with Start autumnsafe

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Run the ITOS script safefromslewsaa.proc with the command Start safefromslewsaa

Check on the housekeeping display that the ICU follows its usual sequence until it reaches the slewSAA state (this has been tested many times by now and need not be tested in detail here). Then check that it goes to the safe state correctly.

ICU reaches slewSAA state Y/N_____ ICU then goes to safe state Y/N_____ Vcathode off Y/N _____ Vmcp1 off Y/N_____ Vmcp23 off Y/N _____ Filter wheel blocked Y/N_____

If the responses above are all Y's then the test is successful.

Test Successful

20.3 From idle to safe

Set up the celestial environment with Start autumnsafe

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Run the ITOS script safefromidle.proc with the command Start safefromidle

Check on the housekeeping display that the ICU follows its usual sequence until it reaches the idle state (this has been tested many times by now and need not be tested in detail here). Then check that it goes to the safe state correctly.

ICU reaches idle state Y/N_____ ICU then goes to safe state Y/N_____ Vcathode off Y/N _____ Vmcp1 off Y/N_____ Vmcp23 off Y/N _____ Filter wheel blocked Y/N____

If the responses above are all Y's then the test is successful.

Test Successful

20.4 From settling to safe

Set up the celestial environment with Start autumnsafe

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Run the ITOS script safefromsett.proc with the command $\ensuremath{\mathsf{Start}}$ safefromsett

Check on the housekeeping display that the ICU follows its usual sequence until it reaches the settling state (this has been tested many times by now and need not be tested in detail here). Then check that it goes to the safe state correctly.

ICU reaches settling state Y/N_____ ICU then goes to safe state Y/N_____ Vcathode off Y/N _____ Vmcp1 off Y/N_____ Vmcp23 off Y/N _____ Filter wheel blocked Y/N____

If the responses above are all Y's then the test is successful.

Test Successful

20.5 From finding to safe

Set up the celestial environment with Start autumnsafe

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Run the ITOS script safefromfind.proc with the command Start safefromfind

Check on the housekeeping display that the ICU follows its usual sequence until it reaches the finding state (this has been tested many times by now and need not be tested in detail here). Then check that it goes to the safe state correctly.

ICU reaches finding state Y/N_____ ICU then goes to safe state Y/N_____ Vcathode off Y/N _____ Vmcp1 off Y/N_____ Vmcp23 off Y/N _____ Filter wheel blocked Y/N____

If the responses above are all Y's then the test is successful.

Test Successful

20.6 From AT to safe

Set up the celestial environment with Start autumnsafe

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Run the ITOS script safefromat.proc with the command Start safefromat

Check on the housekeeping display that the ICU follows its usual sequence until it reaches the AT state (this has been tested many times by now and need not be tested in detail here). Then check that it goes to the safe state correctly.

ICU reaches AT state Y/N_____ ICU then goes to safe state Y/N_____ Vcathode off Y/N _____ Vmcp1 off Y/N_____ Vmcp23 off Y/N _____ Filter wheel blocked Y/N_____

If the responses above are all Y's then the test is successful.

Test Successful

20.7 From PT to safe

Set up the celestial environment with Start autumnsafe

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Run the ITOS script safefrompt.proc with the command Start safefrompt

Check on the housekeeping display that the ICU follows its usual sequence until it reaches the PT state (this has been tested many times by now and need not be tested in detail here). Then check that it goes to the safe state correctly.

ICU reaches PT state Y/N_____ ICU then goes to safe state Y/N_____ Vcathode off Y/N _____ Vmcp1 off Y/N_____ Vmcp23 off Y/N _____ Filter wheel blocked Y/N____

If the responses above are all Y's then the test is successful.

Test Successful

20.8 From safepointing to safe

Set up the celestial environment with Start autumnsafe

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Run the ITOS script safefromsafept.proc with the command Start safefromsafept

Check on the housekeeping display that the ICU follows its usual sequence until it reaches the safepointing state (this has been tested many times by now and need not be tested in detail here). Then check that it goes to the safe state correctly.

ICU reaches safepointing state Y/N_____ ICU then goes to safe state Y/N_____ Vcathode off Y/N _____ Vmcp1 off Y/N_____ Vmcp23 off Y/N _____ Filter wheel blocked Y/N____

If the responses above are all Y's then the test is successful.

Test Successful

20.9 From SAA to safe

Set up the celestial environment with Start autumnsafe

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Run the ITOS script safefromsaa.proc with the command Start safefromsaa

Check on the housekeeping display that the ICU follows its usual sequence until it reaches the SAA state (this has been tested many times by now and need not be tested in detail here). Then check that it goes to the safe state correctly.

ICU reaches SAA state Y/N_____ ICU then goes to safe state Y/N_____ Vcathode off Y/N _____ Vmcp1 off Y/N_____ Vmcp23 off Y/N _____ Filter wheel blocked Y/N____

If the responses above are all Y's then the test is successful.

Test Successful

20.10 From settling to idle

Set up the celestial environment with Start autumnsafe

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Run the ITOS script idlefromsett.proc with the command $\ensuremath{\mathsf{Start}}$ idlefromsett

Check on the housekeeping display that the ICU follows its usual sequence until it reaches the settling state (this has been tested many times by now and need not be tested in detail here). Then check that it goes to the idle state correctly.

ICU reaches settling state Y/N_____ ICU then goes to idle state Y/N_____ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N_____ Vmcp23 nominal Y/N _____ Filter wheel blocked Y/N_____

If the responses above are all Y's then the test is successful.

Test Successful

20.11 From finding to idle

Set up the celestial environment with Start autumnsafe

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Run the ITOS script idlefromfind.proc with the command $\ensuremath{\mathsf{Start}}$ idlefromfind

Check on the housekeeping display that the ICU follows its usual sequence until it reaches the finding state (this has been tested many times by now and need not be tested in detail here). Then check that it goes to the idle state correctly.

ICU reaches finding state Y/N_____ ICU then goes to idle state Y/N_____ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N_____ Vmcp23 nominal Y/N _____ Filter wheel blocked Y/N_____

If the responses above are all Y's then the test is successful.

Test Successful

20.12 From AT to idle

Set up the celestial environment with Start autumnsafe

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Run the ITOS script idlefromat.proc with the command Start idlefromat

Check on the housekeeping display that the ICU follows its usual sequence until it reaches the AT state (this has been tested many times by now and need not be tested in detail here). Then check that it goes to the idle state correctly.

ICU reaches AT state Y/N_____ ICU then goes to idle state Y/N_____ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N_____ Vmcp23 nominal Y/N _____ Filter wheel blocked Y/N_____

If the responses above are all Y's then the test is successful.

Test Successful

20.13 From PT to idle

Set up the celestial environment with Start autumnsafe

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Run the ITOS script idlefrompt.proc with the command Start idlefrompt

Check on the housekeeping display that the ICU follows its usual sequence until it reaches the PT state (this has been tested many times by now and need not be tested in detail here). Then check that it goes to the idle state correctly.

ICU reaches PT state Y/N_____ ICU then goes to idle state Y/N_____ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N_____ Vmcp23 nominal Y/N_____ Filter wheel blocked Y/N_____

If the responses above are all Y's then the test is successful.

Test Successful

20.14 From safepointing to idle

Set up the celestial environment with Start autumnsafe

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Run the ITOS script idlefromsafept.proc with the command Start idlefromsafept

Check on the housekeeping display that the ICU follows its usual sequence until it reaches the safepointing state (this has been tested many times by now and need not be tested in detail here). Then check that it goes to the idle state correctly.

ICU reaches safepointing state Y/N_____ ICU then goes to idle state Y/N_____ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N_____ Vmcp23 nominal Y/N_____ Filter wheel blocked Y/N_____

If the responses above are all Y's then the test is successful.

Test Successful

20.15 From settling and safepointing to slew

Set up the celestial environment with Start autumnsafe

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Run the ITOS script manyslew.proc with the command Start manyslew

Check on the housekeeping display that the ICU follows its usual sequence until it reaches the settling state (this has been tested many times by now and need not be tested in detail here). Then check that it goes to the slew state correctly.

ICU reaches settling state Y/N_____ ICU then goes to slew state Y/N_____ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N_____ Vmcp23 nominal Y/N _____ Filter wheel at filter 2 Y/N_____

Then check on the housekeeping display that the ICU follows its usual sequence until it reaches the safepointing state (this has been tested many times by now and need not be tested in detail here). Then check that it goes to the slew state correctly.

ICU reaches safepointing state Y/N_____ ICU then goes to slew state Y/N_____ Vcathode nominal Y/N _____ Vmcp1 nominal Y/N_____ Vmcp23 nominal Y/N _____ Filter wheel at filter 1 Y/N_____

If the responses above are all Y's then the test is successful.

Test Successful

21. SOAK TEST

21.1 72hr Soak

Load flight code icu.hex.

Check on the housekeeping display that the ICU is in the safe state.

ICU safe Y/N _____

Run the ITOS script soaktest.proc with the command ${\tt Start \ soaktest}$

After 72hrs check that the code has not crashed.

Code crashed Y/N_____

If the above response is N then the test is successful.

Test Successful